

INSIDE TRACK
with Jeff Shamblin,
Ethertronics | 27



For PCB Antennas,
Materials Make
the Difference | 51



Portable Testers
Offer 10-MHz
Bandwidth | 92



microwaves&rf

OCTOBER 2016

TRUSTED ENGINEERING RESOURCE FOR OVER 50 YEARS

www.mwrf.com

ANNUAL

Salary & Career

REPORT

60% 55% 50% 35% 23%

p | 35

SEARCH
PARTS

FAST

sourceesb

Parts Enter part... Enter List

\$10.00 Powered by Penton*

Your Trusted Source www.SourceESB.com



High performance VNAs for any application

In the Lab | On the Manufacturing Floor | In the Field

With a wide variety of Vector Network Analyzers (VNAs) to suit your application and budget, Anritsu has the perfect solution to your VNA needs.

From RF to THz and value to high performance, Anritsu allows you to select the right VNA for you. Designers can choose the VectorStar® family for premium measurement performance while manufacturers can utilize the ShockLine™ family for speed and cost-effectiveness.

Our extensive range of VNAs now includes the NEW 2 or 4-port ShockLine performance line (with NEW E-band option) and the world's first 40 GHz USB VNA.

No matter what your application, Anritsu has your VNA needs covered.

Learn more: www.goanritsu.com/MWRFVNA

1-800-ANRITSU
www.anritsu.com

© 2016 Anritsu Company

Anritsu
envision : ensure



Planar Monolithics Industries, Inc.

Monopulse Comparators

PMI designs and manufactures a variety of coaxial monopulse comparators for beamforming antenna applications up to 26.5 GHz. Form, fit and functional designs can also be replicated to specific requirements. Standard models with various options are available at PMI's website (Link below)

http://pmi-rf.com/Products/monopulse_comparators/features.htm

Model: MPC-20R2G21R2G-CD-LNF 8 Input Monopulse Comparator with Gain

Frequency	20.2 - 21.2 GHz
Gain	0 dB, 5 dB Nom. (Selectable)
Noise Temperature /Figure	100 K / 1.3 dB Noise Figure
Phase Balance	±3° Maximum
DC Supply	+12 VDC @ 700 mA, -12 VDC @ 100 mA
Temperature	-55 °C to +85 °C



Package Size:
6.25" x Ø4.80" x 2.00"
Connectors: SMA (F)

Model: PMC-3G3D5G-6D8-SFF 4 Input Monopulse Comparator

Frequency	3.0 to 3.5 GHz
Insertion Loss	0.8 dB Max. - Measured 0.4 dB
VSWR	1.25:1 Max. - Measured 1.25:1
Isolation	23 dB Min. - Measured 25.052 dB
Amplitude Balance	±0.4 dB Max. - Measured ±0.2681 dB
Phase Balance	±5° Maximum - Measured ±3.2°
RF Input Power	Average: 11 Watt Max. Peak: 0.1 kW Max.
Temperature	-55 °C to +85 °C



Package Size:
3.23" x 3.23" x 0.43"
Connectors: SMA (F)

Model: PD-CD-001-1, 4 Way Phase Shift Power Divider with 0°, 90°, 180°, 270° Outputs

Frequency	9.3 - 9.9 GHz
Insertion Loss	8.0 dB Max. - Measured 6.97 dB Max
VSWR	2.0:1 Max. - Measured 1.60:1 Max.
Amplitude Balance	±0.5 dB Max. - Measured ±0.2 dB Max.
Phase Balance	±7.0° Max. - Measured ±4° Max.
RF Input Power	28 W CW, 750 W Peak
Temperature	-32 °C to +77 °C Operating



Package Size:
2.35" x 1.7" x 0.5"
Connectors: SMA (F)

Amplifiers – Solid State
Attenuators – Variable/
Programmable
Couplers (Quadrature,
180° & Directional)
Detectors – RF/Microwave
DLVAs, ERLVAs
& SDLVAs
DTOs, VCOs, PLO, DROs,
& Frequency Synthesizers
Filters & Switched
Filter Banks
Form, Fit, Functional
Products & Services
Frequency Discriminators
& IFMs
Integrated MIC/MMIC
Assemblies (IMAs)
IQ Vector Modulators
Limiters – RF/Microwave
Log Amplifiers
Millimeter Wave
Components
(Up to 50 GHz)
Miscellaneous Products
Monopulse Comparators
Multifunction Integrated
Assemblies (MIAs)
Phase Shifters & Bi-Phase
Modulators
Power Dividers/Combiners
(Passive & Active)
Pulse Modulators (SPST)
Rack & Chassis Mount
Products
Receiver Front Ends
& Transceivers
SDLVAs, ERLVAs
& DLVAs
Single Side Band
Modulators
SMT & QFN Products
Switch Matrices
Switched Filter Banks
Switches – Solid State
Systems – Fly Eye Radars
Threshold Detectors
USB Products



Austin, Texas
October 30 – November 4, 2016
amta2016.org
Booth: L01

MILCOM2016

Baltimore, MD
November 1-3, 2016
www.milcom.org
Booth: 3004

West Coast Operation:

4921 Robert J. Mathews Pkwy, Suite 1
El Dorado Hills, CA 95762 USA
Tel: 916-542-1401, Fax: 916-265-2597

East Coast Operation:

7311-F Grove Road
Frederick, MD 21704 USA
Tel: 301-662-5019, Fax: 301-662-1731

sales@pmi-rf.com • www.pmi-rf.com

ISO9001-2008 REGISTERED

The Smart Choice for Small Spaces



**Coilcraft is the brand engineers trust most
when specifying tiny inductors for wearable technology**

Boost the performance and battery life of your wearable products with these tiny RF and power inductors from Coilcraft:

- Wirewound chip inductors as small as 0201 size for wireless communications
- Shielded power inductors as thin as 0.71 mm for power management
- Coupled inductors as small as 2.2 x 1.45 mm for LED display drivers

You can get started by using our suite of web tools to quickly locate the perfect inductors for your design. Compare and analyze multiple parts based on your true operating conditions, and then order free evaluation samples with just a click.

Learn why we're the biggest name in ultra-miniature inductors. Visit us at **www.coilcraft.com**.



WWW.COILCRAFT.COM



L-3 NARDA-MITEQ...DEPENDABLE VARIABLE ATTENUATOR PRODUCTS



MINIATURE

Variable

BROADBAND

Variable

HIGH-POWER

Variable



narda  **MITEQ**

Innovative RF Variable Attenuator Products

L-3 Narda-MITEQ has the newest, most complete and dependable attenuator product line on the market today for demanding aerospace, defense and test applications. Our solutions include miniature, broadband and high-power products that are ready to ship now.

- Miniature Variable Products – Low minimum insertion loss, small compact enclosures with an adjustable attenuation range of up to 30 dB, and operational temperatures up to 105 °C
- Broadband Products – Smooth continuous operation and an adjustable attenuation range of up to 20 dB
- High-Power Products – Up to 10 dB or 20 dB adjustable attenuation at power levels up to 500 W

Learn more about all we have to offer by visiting us at nardamiteq.com or call us at (631) 231-1700.

SWITCH-N-SAVE


NEW!

RF Switches

by

CEL

SWAP THEM WITH OTHER
SUPPLIER SWITCHES FOR
BIG SAVINGS



LOWER COST SOLUTIONS

Cost Savings for New and Existing Customers



HIGHER RF PERFORMANCE

Better RF Performance than other RF Switches



HIGH JAPANESE QUALITY

Manufactured in Japan with High Quality, Packaging and Testing

CEL Part Numbers	Switch Type	MAX Freq. (GHz)	Insertion Loss (dB)		Isolation (dB)		P0.1dB (dBm)		Package Type
			2.5 GHz	6.0 GHz	2.5 GHz	6.0 GHz	2.5 GHz	6.0 GHz	
CG2179M2	SPDT	3.0	0.45	N/A	26	N/A	+30	N/A	 (1.25 x 2.0 x 0.9)
CG2214M6	SPDT	3.0	0.35	N/A	25	N/A	+30	N/A	 (1.1 x 1.5 x 0.55)
CG2163X3	SPDT	6.0	0.40	0.50	40	31	+29	+28	 (1.5 x 1.5 x 0.37)
CG2185X2	SPDT	6.0	0.35	0.40	28	26	+29	+29	 (1.0 x 1.0 x 0.37)
CG2176X3	Absorptive SPDT	6.0	0.45	0.55	30	22	+35	+37	 (1.5 x 1.5 x 0.37)
CG2415M6	SPDT	6.0	0.35	0.45	32	26	+31	+31	 (1.1 x 1.5 x 0.55)
CG2430X1	SP3T	6.0	0.50	0.60	28	25	+28	+28	 (1.5 x 1.5 x 0.37)

CEL

WWW.CEL.COM/SWITCHES

In This Issue

FEATURES

35 COVER STORY:

ANNUAL SALARY & CAREER REPORT: ALL QUIET ON THE COMPENSATION FRONT

Although concerns and challenges exist, the RF/microwave industry is continuing to provide stable salaries along with high job compensation.

51 MATERIALS MAKE THE DIFFERENCE IN LOW-PIM PCB ANTENNAS

Certain characteristics of circuit materials can indicate whether a material will contribute to higher or lower levels of PIM for a printed-circuit RF/microwave antenna.

75 UWB BANDPASS FILTER INCLUDES NOTCHED BAND


Leveraging two interdigital coupled three-line structures with bandpass characteristics, this compact ultrawideband filter incorporates a notched band with 25-dB rejection.

80 SPLIT-RING RESONATORS ADD TO SIW BANDPASS FILTER

Complementary split-ring resonators etched into substrate-integrated-waveguide circuits can form the basis of broadband PCB bandpass filters at microwave frequencies.




35



51

48



INDUSTRY TRENDS & ANALYSIS

48 ENGINEERING ESSENTIALS SAW vs. BAW Technology

86 DIFFERENCE BETWEEN MIMO and MMICs

PRODUCT TECHNOLOGY

- 92 50-GHz Portable Testers
- 96 Wi-Fi Future Up in Air
- 99 Multiport VNA
- 100 Dual-Superhet-Channel Module
- 101 20-MHz YIG Oscillators

NEWS & COLUMNS

10 ONLINE CONTENTS

13 EDITORIAL

18 FEEDBACK

20 NEWS

27 INSIDE TRACK with Jeff Shamblin, Ethertronics



32 R&D ROUNDUP

90 APPLICATION NOTES

104 ADVERTISERS INDEX



75

defense electronics

Starts on p. **57**



80

JOIN US ONLINE



follow us @MicrowavesRF



become a fan at
facebook.com/microwavesRF



Wireless Connectivity Solutions for the Internet of Things



Visit Us at Electronica • Hall A4 Booth 557 • Munich, Germany • November 8-11, 2016



| Automotive

AEC-Q100 Qualified 20 MHz to 3 GHz SPDT RF Switch: SKYA21001

For general purpose RF signal routing

AEC-Q100 Level 2 Qualified 0.1 to 6 GHz SPDT Switch: SKYA21003

For 3G / 4G LTE / 4G LTE-A in-cabin, cellular telematics and general purpose RF signal routing



| CATV

Broadband 75 Ω CATV Low-noise Amplifiers (40 MHz to 1 GHz): SKY65450-92LF, SKY65452-92LF

For terrestrial and set-top boxes, cable modems and gateways, personal and digital video recorders

High Linearity SPDT 75 Ω Switches (5 to 1800 MHz): SKY13547-490LF, SKY13548-385LF

For cable modems, set-top boxes, filter band switching and DOCSIS 3.1 configurations

1218 MHz CATV MMIC Power Doubler: ACA1216

For HFC/FTTC node and ORM RF amplifiers that require highest bit delivery efficiency and low power consumption



| Connected Home

2.4 GHz ZigBee®/Thread/Bluetooth® Smart Front-end Module: SKY66112-11

For in-home appliances, smart thermostats, smart lighting, sensors and Internet of Things (IoT) devices

GPS/GNSS/GNSS Pre-filter + LNA Front-end Module: SKY65720-11

For GPS/GNSS/BDS receiver applications



| Wearables

Low-power Bluetooth® Low Energy Front-end Module: SKY66111-11

Range extension for fitness trackers, sport and smart watches



| Wireless Infrastructure

200 to 3800 MHz Ultra Broadband Low-noise Amplifier: SKY67159-396LF

For FDD and TDD 2G / 3G / 4G LTE small cell base stations, land mobile radios and broad market applications

High Linearity, High Efficiency Small Cell Power Amplifier Modules: AWB71xx, AWB72xx

For picocell, femtocell, and customer premises equipment (CPE) applications

Please visit our Internet of Things site at www.skyworksinc.com/IoT

BETTER COMMUNICATION SOLUTIONS



Public Safety



Satcom, mmWave
& Military



Aeronautical/Space
Transportation



AMER, EMEA,
& D.A.S

MECA 5G Products & Equipment

MECA Electronics designs and manufactures an extensive line of RF/Microwave Equipment and Components with industry leading performance including D.A.S. Equipment, Low PIM Products, supports 5G & Millimeter-Wave, Power Dividers & Combiners, Directional & Hybrid Couplers, Fixed & Variable Attenuators, RF Terminations, Circulators/Isolators, DC Blocks & Bias Tees, Adapters & Jumpers. Models available in industry common connector styles: N, SMA, 2.92mm, TNC, BNC, 7/16, 4.1/9.5 & 4.3/10.0 DIN as well as

QMA, Reverse Polarity SMA, TNC and various mounting solutions. Since 1961 MECA Electronics (Microwave Equipment & Components of America) has served the RF/Microwave industry with equipment and passive components covering Hz to 40 GHz. MECA is a privately held ISO9001:2008 Certified, global designer and manufacturer for the communications industry with products manufactured in the United States of America We stock products so that you do not need to.



Low PIM Couplers



Low PIM Attenuators



Low PIM Terminations



Power Divider/Combiner



**Products in STOCK
when you need it!**



Low PIM & D.A.S Equipment



Circulators/Isolators



RFPartsOnDemand.com

Online



Attenuators/Terminations



e-MECA.com
Since 1961

MECA Electronics, Inc.

Microwave Equipment & Components of America

The Professional's Choice for RF/Microwave Passive Components

459 E. Main St., Denville, NJ 07834

Tel: 973-625-0661 • Fax: 973-625-9277 • Sales@e-MECA.com



iBwove



The Trusted Name in RF, Microwave & Millimeterwave ICs

Featured MACOM MMIC Devices

Application	Function	Part Number
SATCOM	Ka-Band Power Amplifier	MAAP-011289, 28 - 30.5 GHz
	Doubler Power Amplifier	MAFC-011009, 28 - 30 GHz
	L-Band Power Amplifier Module	MAAP-011060, 1616 - 1627 MHz
Test & Measurement	Wideband Power Amplifier	MAAP-011247, DC - 22 GHz
	Wideband Low Noise Amplifier	MAAL-011141, DC - 26.5 GHz
	Wideband DBL BAL Mixer	MAMX-011036, 8 - 43 GHz
Aerospace & Defense	Octave Band VCO	MAOC-415000, 10 - 20 GHz
	Power Amplifier	MAAP-011232, 0.1 - 3 GHz
Industrial, Scientific & Medical	Low Noise Amplifier	MAAL-011129, 18 - 32 GHz
	Gain Block	MAAM-011206, DC - 15 GHz
Wired Broadband	Variable Gain Amplifier	MAAM-011194, 45 - 1218 MHz
	Gain Block	MAAM-011220, 45 - 1218 MHz
	Very Low Noise Amplifier	MAAL-011136, 45 - 1218 MHz

Aerospace & Defense

Industrial, Scientific & Medical

Satellite Communications

Test & Measurement

Wired Broadband

MACOM delivers a leading portfolio of high-performance DC to 100 GHz MMICs


For over 60 years MACOM design and application experts have driven RF, Microwave and mmW innovation. Our engineers are delivering a new generation of wideband, high-performance MMICs for T&M, SATCOM, A&D, wired broadband and ISM applications.

Our 27 new MMIC products offer optimal performance, bandwidth, packaging and reliability to meet your most demanding requirements. New products include:

- › High Linearity SATCOM PAs
- › Wideband Amplifiers & Mixers
- › Single Bias LNAs & Gain Blocks
- › Broadband VCOs
- › V-, E- & W-Band Products
- › mmW Switches
- › Wideband Detectors
- › Broadband 75 ohm Amplifiers

Ka-Band 3 W Power Amplifier Ideal for Satellite Communications

Psat (dBm) and PAE (%) vs Frequency (GHz)



MACOM™

Partners from RF to Light

Learn more and get datasheet:

www.macom.com/mmics



THE POWER OF 5G ON TEST REQUIREMENTS

<http://mwrf.com/blog/power-5g-test-requirements>

With Fifth-Generation (5G) wireless communications systems imminent, test-equipment designers and suppliers are carrying a heavy load. In fact, it's no exaggeration to say that the expected needs of next-generation wireless networks are shaping the next generation of RF/microwave test equipment.

FROM ESOTERIC TECH TO MARKET MAINSTAY

<http://mwrf.com/active-components/amplifiers-heighten-performance-satisfy-next-wave>

The pressing needs of today's applications are prompting amplifier suppliers to deliver new products to meet current high-frequency demands.

One specific area that is now driving a significant amount of product development is small-cell infrastructure, which is a growing market. As many are turning to small cells to drive wireless networks, amplifier suppliers are launching new products in support of this need.



FLEXIBLE, COST-EFFECTIVE SOLUTIONS TRANSFORM THE MILITARY SECTOR


<http://mwrf.com/defense/gan-open-systems-low-swap-platforms-transform-military-sector>

To support current aerospace and defense systems, technology has moved beyond traditional constructs and iterations to completely new approaches and solutions. The RF/microwave industry faces the task of providing ever-advancing electronic-warfare (EW) solutions while meeting size, weight, and power (SWaP) constraints.

A PRIMER ON CIRCULATORS AND ISOLATORS

<http://mwrf.com/components/primer-circulators-and-isolators>


Circulators and isolators are three-port passive electronic devices that are absolutely essential for directing the flow of microwave signals in RF equipment and systems. Here's everything you need to know about them.



join us online  

twitter.com/MicrowavesRF facebook.com/microwavesrf

If your 5G idea works here...



it will work here.

Autonomous vehicles navigating through traffic. Hands free.

Soon it will be reality. A world connected as never before. Always available. Low latency. Ultra reliable. That's the promise of 5G. New spectrum. New waveforms. Millimeter-waves. More. Keysight offers the world's first 5G simulation, design and test environment able to emulate your real-world 5G wireless thesis. With deep expertise to help you navigate 5G risk and complexity. So you can go from 5G ideas to 5G reality faster.

HARDWARE + SOFTWARE + PEOPLE = 5G INSIGHTS

5G

Get the latest app notes,
white papers and tutorials
www.keysight.com/find/5G-Insight

USA: 800 829 4444 CAN: 877 894 4414

© Keysight Technologies, Inc. 2016



Unlocking Measurement Insights

Agilent's Electronic Measurement Group is now **Keysight Technologies**.

100W POWER AMPLIFIERS

700-2700 MHz



\$8,995_{each}

48 dB Gain, ± 1.7 dB Flatness

Output power up to 100W with consistent performance across a wide frequency range for a fraction of the cost of competitive products! Mini-Circuits' new HPA-272+ high power rack mount amplifiers are ideal for a wide variety of high power test applications including EMI, reliability testing, power stress testing, and burn-in of multiple units at once. This model provides 48 dB gain with ± 1.7 dB gain flatness over its entire frequency range and 89 dB reverse isolation. Housed in a rugged, 19-inch rack-mountable chassis, the amplifier operates on a self-contained 110/220V power supply and includes internal cooling, making it easy to use in most lab environments. Extensive built-in safety features include over-temperature protection and the ability to withstand opens and shorts at the output.* They're available off the shelf for an outstanding value, so place your order on minicircuits.com today for delivery as soon as tomorrow!

*at 3 dB compression point.



Editorial

CHRIS DeMARTINO

Technical Editor

chris.demartinol@penton.com



EDI CON Achieves First-Pass Success

EDI CON USA 2016 was held in Boston from Sept. 20 to 22, marking the first time the event took place here in the United States. The show had lots to offer in terms of both the exhibition as well as the wide variety of technical sessions. Many companies used this event as an opportunity to showcase their newest products, while the technical sessions covered a vast array of topics.

Among the technical sessions that I took in was one on 5G modulation-scheme candidates, presented by Kay-Uwe Sander from Rohde & Schwarz. The modulation-scheme candidates he mentioned were orthogonal frequency division multiplexing (OFDM), filter bank multi-carrier (FBMC) with offset-QAM, universal filtered multi-carrier (UFMC), generalized frequency division multiplexing (GFDM), and filtered-OFDM (F-OFDM). While I won't get into all the details here, this is definitely a topic under much investigation. With all of the talk surrounding 5G, we can surely expect to hear more about modulation schemes in the future.

Another technical session I decided to see was Dan Swanson's presentation, "Intuitive Microwave Filter Design with EM Simulation." In this session, Swanson described a design flow for both cavity and microstrip filters, demonstrating how to effectively use electromagnetic (EM) simulation. I thought this was a good presentation that could benefit anyone who is involved with microwave filter design.

Another point of interest was solid-state RF energy. Klaus Werner from the RF Energy Alliance spoke on this topic, discussing the future challenges and opportunities associated with solid-state RF energy. Magnetron-based microwave ovens have been in people's home for so long, which is why it is difficult to imagine anything different. However, people like Werner believe that solid-state RF energy will eventually overtake magnetrons. Werner has high expectations for solid-state RF energy, as he believes the technology will soon reach a number of markets.

The exhibition floor was an opportunity for many companies to showcase their latest and greatest. A number of new products were displayed, some of which have already been featured by Microwaves & RF. In addition, I was able to see a nice demo from Mitsubishi Electric. The company proved that its gallium-nitride (GaN) technology can deliver 70 W of output power at Ku-band (13.75 to 14.5 GHz).

Lastly, those who missed EDI CON this year will have another opportunity. The event will once again return to Boston in 2017. **mw**

JOIN US ONLINE twitter.com/MicrowavesRF
become a fan at facebook.com/MicrowavesRF



PIN DIODE LIMITERS 1 WATT CW 1 - 40 GHz (Very High Frequency)



Many Models Available in Stock

- Very High frequency Wide Band
- 1 Watt CW Power Handling Capability
- Fast Response & Short Recovery Time (10 nsec typical)
- Hermetically Sealed Module

Typical Performance @ + 25 Deg. C

MODEL	FREQ. RANGE (GHz)	MAXIMUM ¹ INSERTION LOSS (dB)	TYP LIM THRESHOLD (dBm)	MAX LEAKAGE ² @ 1W CW INPUT (dBm)
LP1-26A	1 - 26	3.5	+9	+20
LP2-26A	12 - 26	3.5	+9	+20
LP18-26A	18 - 26	3.0	+9	+19
LP18-40A	18 - 40	4.0	+9	+19
LP1-40A	1 - 40	4.5	+9	+20
LP2-40A	2 - 40	4.5	+9	+20
LP26-40A	26 - 40	4.0	+9	+19

Notes: 1. Insertion Loss and VSWR (2 : 1) tested at -10 dBm.

Notes: 2. Power rating derated to 20% @ +125 Deg. C.

Other Products: Detectors, Amplifiers, Switches, Comb Generators, Impulse Generators, Multipliers, Integrated Subassemblies

Please call for Detailed Brochures



155 Baytech Drive, San Jose, CA 95134
Tel: (408) 941-8399 . Fax: (408) 941-8388
Email: Info@herotek.com
Website: www.herotek.com
Visa/Mastercard Accepted

UP TO 100 Watt AMPLIFIERS

NOW! 100 kHz to 26.5 GHz



\$995
from ea. qty. (1-9)

High-powered performance across wide frequency ranges. Mini-Circuits' class A/AB linear amplifiers have set a standard for wideband high-power performance throughout the RF and microwave industry. Rugged and reliable, they feature over-voltage and over-temperature protections and can withstand opens and shorts at the output! Available with or without heat sinks, they're perfect for demanding test lab environments and for integrating directly into customer assemblies. With standard models covering frequencies from 100 kHz up to 26.5 GHz, chances are we have a solution for your needs in stock. Place your order on minicircuits.com today for delivery as soon as tomorrow! Need a custom model? Give us a call and talk to our engineers about your special requirements!


Model	Frequency (MHz)	Gain (dB)	Pout @ Comp.		\$ Price* (Qty. 1-9)
			1 dB (W)	3 dB (W)	
NEW! ZHL-100W-272+	700-2700	48	79	100	7995
ZVM-273HP+	13000-26500	14.5	0.5	0.5	2195
ZVE-3W-83+	2000-8000	35	2	3	1295
ZVE-3W-183+	5900-18000	35	2	3	1295
ZHL-4W-422+	500-4200	25	3	4	1160
ZHL-5W-422+	500-4200	25	3	5	1670
ZHL-5W-2G+	800-2000	45	5	5	995
ZHL-10W-2G+	800-2000	43	10	12	1295
• ZHL-16W-43+	1800-4000	45	12	16	1595
• ZHL-20W-13+	20-1000	50	13	20	1395
• ZHL-20W-13SW+	20-1000	50	13	20	1445
LZY-22+	0.1-200	43	16	30	1495
ZHL-30W-262+	2300-2550	50	20	32	1995
ZHL-30W-252+	700-2500	50	25	40	2995
LZY-2+	500-1000	47	32	38	2195
LZY-1+	20-512	42	50	50	1995
• ZHL-50W-52+	50-500	50	63	63	1395
• ZHL-100W-52+	50-500	50	63	79	1995
• ZHL-100W-GAN+	20-500	42	79	100	2395
ZHL-100W-13+	800-1000	50	79	100	2195
ZHL-100W-352+	3000-3500	50	100	100	3595
ZHL-100W-43+	3500-4000	50	100	100	3595

Listed performance data typical, see minicircuits.com for more details.

• Protected under U.S. Patent 7,348,854

*Price Includes Heatsink





SUPER ULTRA WIDEBAND AMPLIFIERS

up to +27 dBm output... **0.1 to 21 GHz**

Ultra wide coverage and super flat gain make our ZVA family ideal for ECM, instrumentation, and test systems. With output power up to 0.5 Watts, they're simply some of the most usable amplifiers you'll find, for a wide range of applications and architectures!

All of our ZVA models are unconditionally stable, ruggedly constructed, and able to withstand open or short circuits at full output. For more details, from data sheets to environmental ratings, pricing, and real-time availability, just go to minicircuits.com!

All models IN STOCK!

 RoHS compliant


\$845
from ea.

Electrical Specifications (-55 to +85°C base plate temperature)

Model	Frequency (GHz)	Gain (dB)	P1dB (dBm)	IP3 (dBm)	NF (dB)	Price \$ *
NEW ZVA-183WX+	0.1-18	28±2	27	35	3.0	1345.00
ZVA-183X+	0.7-18	26±1	24	33	3.0	845.00
ZVA-213X+	0.8-21	26±2	24	33	3.0	945.00

* Heat sink must be provided to limit base plate temperature. To order with heat sink, remove "X" from model number and add \$50 to price.

Wideband Performance



 **Mini-Circuits®**

RENT

Test Equipment

Visit us www.atecorp.com



IN STOCK & CALIBRATED

RF Power Amplifiers
Data Acquisition Systems
Oscilloscopes · Antennas
E & H Field Strength Generators
Real-Time Spectrum Analyzers
Network Analyzers · Sweepers
Precision Power Analyzers
Power Supplies · Loads
Signal Generators & more...



INDUSTRY PARTNERS

Aeroflex · Agilent · Anritsu
Amplifier Research · Com-Power
CA Instruments · CPI · ETS-Lindgren
EM Test · IFI · Narda · Ophir
Rohde & Schwarz · Sorensen · Teseq
Texttronix · Yokogawa & more...



ADVANCED TEST EQUIPMENT RENTALS
The Knowledge. The Equipment. The Solution.

Call Now 800-404-ATEC (2832)

OCTOBER | 2016

microwaves&rf

Powered by Penton*

EDITORIAL

CONTENT DIRECTOR: **NANCY K. FRIEDRICH** nancy.friedrich@penton.com
TECHNICAL CONTRIBUTOR: **JACK BROWNE** jack.browne@penton.com
TECHNICAL ENGINEERING EDITOR: **CHRIS DeMARTINO** chris.demartino@penton.com
CONTENT PRODUCTION DIRECTOR: **MICHAEL BROWNE** michael.browne@penton.com
PRODUCTION EDITOR: **JEREMY COHEN** jeremy.cohen@penton.com
CONTENT PRODUCTION SPECIALIST: **ROGER ENGELKE** roger.engelke@penton.com
CONTENT OPTIMIZATION SPECIALIST: **WES SHOCKLEY** wes.shockley@penton.com
ASSOCIATE CONTENT PRODUCER: **LEAH SCULLY** leah.scully@penton.com
ASSOCIATE CONTENT PRODUCER: **JAMES MORRA** james.morra@penton.com

ART DEPARTMENT

GROUP DESIGN DIRECTOR: **ANTHONY VITOLO** tony.vitolo@penton.com
SENIOR ARTIST: **JIM MILLER** jim.miller@penton.com
CONTENT DESIGN SPECIALIST: **JOCELYN HARTZOG** jocelyn.hartzog@penton.com
CONTENT & DESIGN PRODUCTION MANAGER: **JULIE JANTZER-WARD** julie.jantzer-ward@penton.com

PRODUCTION

GROUP PRODUCTION MANAGER: **CAREY SWEETEN** carey.sweeten@penton.com
PRODUCTION MANAGER: **VICKI MCCARTY** vicki.mccarty@penton.com
CLASSIFIED PRODUCTION COORDINATOR: **LINDA SARGENT** linda.sargent@penton.com

AUDIENCE MARKETING

USER MARKETING DIRECTOR: **BRENDA ROODE** brenda.roode@penton.com
USER MARKETING MANAGER: **DEBBIE BRADY** debbie.brady@penton.com
FREE SUBSCRIPTION/STATUS OF SUBSCRIPTION/ADDRESS CHANGE/MISSING BACK ISSUES
OMEDA T | 847.513.6022 TOLL FREE | 866.505.7173

SALES & MARKETING

MANAGING DIRECTOR: **TRACY SMITH** T | 913.967.1324 F | 913.514.6881 tracy.smith@penton.com
REGIONAL SALES REPRESENTATIVES
AZ, NM, TX: **GREGORY MONTGOMERY** T | 480.254.5540 gregory.montgomery@penton.com
AK, CA, CO, ID, MT, ND, NV, OR, SD, UT, WA, WI, WY, W/CANADA: **JAMIE ALLEN** T | 415.608.1959
F | 913.514.3667 jamie.allen@penton.com
AL, AR, IA, IL, IN, KS, KY, LA, MI, MN, MO, MS, NE, OH, OK, TN: **PAUL MILNAMOW** T | 312.840.8462
paul.milnamow@penton.com
CT, DE, FL, GA, MA, MD, ME, NC, NH, NJ, NY, RI, PA, SC, VA, VT, WV, EASTERN CANADA:
SHANNON ALO-MENDOSA T | 978.501.7303 shannon.alo-mendosa@penton.com
INTERNATIONAL SALES
GERMANY, AUSTRIA, SWITZERLAND: **CHRISTIAN HOELSCHER** T | 011.49.89.95002778
christian.hoelscher@hudsonmedia.com
BELGIUM, NETHERLANDS, LUXEMBURG UNITED KINGDOM, SCANDINAVIA, FRANCE, SPAIN, PORTUGAL:
JAMES RHOADES-BROWN T | +011 44 1932 564999 M | +011 44 1932 564998
james.rhoadesbrown@hudsonmedia.com
PAN-ASIA: **HELEN LAI** T | 886 2-2727 7799 helen@twoway.com

PLEASE SEND INSERTION ORDERS TO: orders@penton.com
PENTON REPRINTS: **WRIGHT'S MEDIA** T | 877.652.5295 penton@wrightsmedia.com

LIST RENTALS:

SMARTREACH CLIENT SERVICES MANAGER: **JAMES ADDISON** T | 212.204.4318 james.addison@penton.com

ONLINE

PRODUCT DEVELOPMENT DIRECTOR: **RYAN MALEC** ryan.malec@penton.com

DESIGN ENGINEERING & SOURCING GROUP

EXECUTIVE DIRECTOR OF CONTENT AND USER ENGAGEMENT: **NANCY K. FRIEDRICH**
GROUP DIRECTOR OF OPERATIONS: **CHRISTINA CAVANO**
GROUP DIRECTOR OF MARKETING: **JANE COOPER**

PENTON

CHIEF EXECUTIVE OFFICER: **DAVID KIESELSTEIN** david.kieselstein@penton.com
CHIEF FINANCIAL OFFICER: **NICOLA ALLAIS** nicola.allais@penton.com
INDUSTRY GROUP, PRESIDENT: **PAUL MILLER** paul.miller@penton.com
1166 AVENUE OF THE AMERICAS, 10TH FLOOR NEW YORK, NY 10036 T | 212.204.4200

Penton

Electronic Design | Machine Design | Microwaves & RF | Source ESB | Hydraulics & Pneumatics |
Global Purchasing | Distribution Resource | Power Electronics | Defense Electronics

RF Amplifiers and Sub-Assemblies for Every Application

Delivery from Stock to 2 Weeks ARO from the catalog or built to your specifications!

- Competitive Pricing & Fast Delivery
- Military Reliability & Qualification
- Various Options: Temperature Compensation, Input Limiter Protection, Detectors/TTL & More
- Unconditionally Stable (100% tested)

ISO 9001:2000
and AS9100B
CERTIFIED

OCTAVE BAND LOW NOISE AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1dB	3rd Order ICP	VSWR
CA01-2110	0.5-1.0	28	1.0 MAX, 0.7 TYP	+10 MIN	+20 dBm	2.0:1
CA12-2110	1.0-2.0	30	1.0 MAX, 0.7 TYP	+10 MIN	+20 dBm	2.0:1
CA24-2111	2.0-4.0	29	1.1 MAX, 0.95 TYP	+10 MIN	+20 dBm	2.0:1
CA48-2111	4.0-8.0	29	1.3 MAX, 1.0 TYP	+10 MIN	+20 dBm	2.0:1
CA812-3111	8.0-12.0	27	1.6 MAX, 1.4 TYP	+10 MIN	+20 dBm	2.0:1
CA1218-4111	12.0-18.0	25	1.9 MAX, 1.7 TYP	+10 MIN	+20 dBm	2.0:1
CA1826-2110	18.0-26.5	32	3.0 MAX, 2.5 TYP	+10 MIN	+20 dBm	2.0:1

NARROW BAND LOW NOISE AND MEDIUM POWER AMPLIFIERS

CA01-2111	0.4 - 0.5	28	0.6 MAX, 0.4 TYP	+10 MIN	+20 dBm	2.0:1
CA01-2113	0.8 - 1.0	28	0.6 MAX, 0.4 TYP	+10 MIN	+20 dBm	2.0:1
CA12-3117	1.2 - 1.6	25	0.6 MAX, 0.4 TYP	+10 MIN	+20 dBm	2.0:1
CA23-3111	2.2 - 2.4	30	0.6 MAX, 0.45 TYP	+10 MIN	+20 dBm	2.0:1
CA23-3116	2.7 - 2.9	29	0.7 MAX, 0.5 TYP	+10 MIN	+20 dBm	2.0:1
CA34-2110	3.7 - 4.2	28	1.0 MAX, 0.5 TYP	+10 MIN	+20 dBm	2.0:1
CA56-3110	5.4 - 5.9	40	1.0 MAX, 0.5 TYP	+10 MIN	+20 dBm	2.0:1
CA78-4110	7.25 - 7.75	32	1.2 MAX, 1.0 TYP	+10 MIN	+20 dBm	2.0:1
CA910-3110	9.0 - 10.6	25	1.4 MAX, 1.2 TYP	+10 MIN	+20 dBm	2.0:1
CA1315-3110	13.75 - 15.4	25	1.6 MAX, 1.4 TYP	+10 MIN	+20 dBm	2.0:1
CA12-3114	1.35 - 1.85	30	4.0 MAX, 3.0 TYP	+33 MIN	+41 dBm	2.0:1
CA34-6116	3.1 - 3.5	40	4.5 MAX, 3.5 TYP	+35 MIN	+43 dBm	2.0:1
CA56-5114	5.9 - 6.4	30	5.0 MAX, 4.0 TYP	+30 MIN	+40 dBm	2.0:1
CA812-6115	8.0 - 12.0	30	4.5 MAX, 3.5 TYP	+30 MIN	+40 dBm	2.0:1
CA812-6116	8.0 - 12.0	30	5.0 MAX, 4.0 TYP	+33 MIN	+41 dBm	2.0:1
CA1213-7110	12.2 - 13.25	28	6.0 MAX, 5.5 TYP	+33 MIN	+42 dBm	2.0:1
CA1415-7110	14.0 - 15.0	30	5.0 MAX, 4.0 TYP	+30 MIN	+40 dBm	2.0:1
CA1722-4110	17.0 - 22.0	25	3.5 MAX, 2.8 TYP	+21 MIN	+31 dBm	2.0:1

ULTRA-BROADBAND & MULTI-OCTAVE BAND AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1dB	3rd Order ICP	VSWR
CA0102-3111	0.1-2.0	28	1.6 Max, 1.2 TYP	+10 MIN	+20 dBm	2.0:1
CA0106-3111	0.1-6.0	28	1.9 Max, 1.5 TYP	+10 MIN	+20 dBm	2.0:1
CA0108-3110	0.1-8.0	26	2.2 Max, 1.8 TYP	+10 MIN	+20 dBm	2.0:1
CA0108-4112	0.1-8.0	32	3.0 MAX, 1.8 TYP	+22 MIN	+32 dBm	2.0:1
CA02-3112	0.5-2.0	36	4.5 MAX, 2.5 TYP	+30 MIN	+40 dBm	2.0:1
CA26-3110	2.0-6.0	26	2.0 MAX, 1.5 TYP	+10 MIN	+20 dBm	2.0:1
CA26-4114	2.0-6.0	22	5.0 MAX, 3.5 TYP	+30 MIN	+40 dBm	2.0:1
CA618-4112	6.0-18.0	25	5.0 MAX, 3.5 TYP	+23 MIN	+33 dBm	2.0:1
CA618-6114	6.0-18.0	35	5.0 MAX, 3.5 TYP	+30 MIN	+40 dBm	2.0:1
CA218-4116	2.0-18.0	30	3.5 MAX, 2.8 TYP	+10 MIN	+20 dBm	2.0:1
CA218-4110	2.0-18.0	30	5.0 MAX, 3.5 TYP	+20 MIN	+30 dBm	2.0:1
CA218-4112	2.0-18.0	29	5.0 MAX, 3.5 TYP	+24 MIN	+34 dBm	2.0:1

LIMITING AMPLIFIERS

Model No.	Freq (GHz)	Input Dynamic Range	Output Power Range Psat	Power Flatness dB	VSWR
CLA24-4001	2.0 - 4.0	-28 to +10 dBm	+7 to +11 dBm	+/- 1.5 MAX	2.0:1
CLA26-8001	2.0 - 6.0	-50 to +20 dBm	+14 to +18 dBm	+/- 1.5 MAX	2.0:1
CLA712-5001	7.0 - 12.4	-21 to +10 dBm	+14 to +19 dBm	+/- 1.5 MAX	2.0:1
CLA618-1201	6.0 - 18.0	-50 to +20 dBm	+14 to +19 dBm	+/- 1.5 MAX	2.0:1

AMPLIFIERS WITH INTEGRATED GAIN ATTENUATION

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure (dB)	Power-out @ P1dB	Gain Attenuation Range	VSWR
CA001-2511A	0.025-0.150	21	5.0 MAX, 3.5 TYP	+12 MIN	30 dB MIN	2.0:1
CA05-3110A	0.5-5.5	23	2.5 MAX, 1.5 TYP	+18 MIN	20 dB MIN	2.0:1
CA56-3110A	5.85-6.425	28	2.5 MAX, 1.5 TYP	+16 MIN	22 dB MIN	1.8:1
CA612-4110A	6.0-12.0	24	2.5 MAX, 1.5 TYP	+12 MIN	15 dB MIN	1.9:1
CA1315-4110A	13.75-15.4	25	2.2 MAX, 1.6 TYP	+16 MIN	20 dB MIN	1.8:1
CA1518-4110A	15.0-18.0	30	3.0 MAX, 2.0 TYP	+18 MIN	20 dB MIN	1.85:1

LOW FREQUENCY AMPLIFIERS

Model No.	Freq (GHz)	Gain (dB) MIN	Noise Figure dB	Power-out @ P1dB	3rd Order ICP	VSWR
CA001-2110	0.01-0.10	18	4.0 MAX, 2.2 TYP	+10 MIN	+20 dBm	2.0:1
CA001-2211	0.04-0.15	24	3.5 MAX, 2.2 TYP	+13 MIN	+23 dBm	2.0:1
CA001-2215	0.04-0.15	23	4.0 MAX, 2.2 TYP	+23 MIN	+33 dBm	2.0:1
CA001-3113	0.01-1.0	28	4.0 MAX, 2.8 TYP	+17 MIN	+27 dBm	2.0:1
CA002-3114	0.01-2.0	27	4.0 MAX, 2.8 TYP	+20 MIN	+30 dBm	2.0:1
CA003-3116	0.01-3.0	18	4.0 MAX, 2.8 TYP	+25 MIN	+35 dBm	2.0:1
CA004-3112	0.01-4.0	32	4.0 MAX, 2.8 TYP	+15 MIN	+25 dBm	2.0:1

CIAO Wireless can easily modify any of its standard models to meet your "exact" requirements at the Catalog Pricing.

Visit our web site at www.ciaowireless.com for our complete product offering.

Ciao Wireless, Inc. 4000 Via Pescador, Camarillo, CA 93012

Tel (805) 389-3224 Fax (805) 389-3629 sales@ciaowireless.com



MICROSTRIP AND STRIPLINE: A DEEPER DIVE?

I thought your article “*What’s the Difference Between Microstrip and Stripline?*” (September 2016) was a decent overview, but I would have expected a bit more on the practical application differences, especially regarding filters, amplifiers, and directional couplers.

Because of the radiation problems of microstrip, it is necessary to take special precautions in the design of filters and amplifiers. It is unfortunately easy for the input signal to jump right over the filter or amplifier layout through the air-space above the microstrip, thus leading to the complications of undesired feedback in amplifiers, leading to instability, and insufficient rejection in filter structures. This may be a job for stripline, even though active devices may present a mechanical problem.

Another special circumstance arises

due to the non-uniform dielectric structure (substrate and air) in which microstrip propagation occurs, as you mentioned in the article. As a result of this non-uniform dielectric, coupled structures do not exhibit good directivity: the odd-mode and even-mode in coupled lines are of different electrical length. A typical directional coupler in microstrip may only provide directivity of 13 dB or so, whereas a number like 30 dB is reasonably achievable in stripline.

However, there is a major advantage to microstrip where it can be used: you can mount components—even large components like power devices, right on the surface. In addition, as the product is in development, it is possible to tweak the design a bit by adding bits of copper foil in judicious locations in order to improve matching of active devices, or frequency response of filters. The manufactured component then can

incorporate these modifications by adding them to the artwork.

The engineer desiring to utilize the advantages of microstrip may find that a judicious application of microwave-absorbing material to the cover of the housing will provide considerable improvement to the output-to-input coupling problem.

DOUG MCGARRETT

EDITOR’S NOTE

Thanks for taking the time to write, as well as for your thoughts. I think you are seeing what we editors face when trying to tackle a large topic like this in a short article. You definitely make me realize that there is a need for a follow-up story (or stories). Thanks again for reading and for your interest.

JACK BROWNE

TECHNICAL CONTRIBUTOR

CUSTOMIZED DESIGN QUOTES IN 24 HOURS
www.pulsarmicrowave.com

DC-85 GHz

PULSAR
MICROWAVE CORPORATION





Power Dividers, DC-70 GHz
2-32 Way



Directional Couplers
Single and Dual, to 60 GHz
High Power, to 2500 watts



Hybrids, to 40 GHz
90° & 180°



Attenuators, to 18 GHz
Digital, Analog, Linearized



Bias Tees, to 85 GHz
30 KHz to 85 GHz



Switches, to 18 GHz
SP1T-SP16T



High Power Combiners
to 500 watts

Also Available
Phase Shifters, DC Blocks, Mixers,
Modulators, and Image Reject Mixers

48 Industrial West, Clifton, NJ 07012 | Tel: 973-779-6262 | Fax: 973-779-2727 | sales@pulsarmicrowave.com


RoHS Compliant
6060 Solder Available
Specify your requirements
ISO 9001:2000 Certified





Upgrade Your Mixer

2GHz–14GHz, 0dBm LO Drive




The LTC5549 microwave mixer upgrades your transmitter and receiver performance with a +22.8dBm IIP3 at 12GHz. Its 0dBm LO drive and an on-chip frequency doubler eliminate the need for an external LO power amplifier and allow use of commonly available low frequency PLL/synthesizers, reducing power consumption and solution costs — all in a tiny 3mm x 2mm package that keeps your solution size small.

▼ Features

- +22.8dBm IIP3 at 12GHz
- 0dBm LO Drive
- Upconversion or Downconversion
- –30dBm LO Leakage
- Tiny 3mm x 2mm Package

Demo Board



▼ Info & Free Samples

www.linear.com/product/LTC5549

1-800-4-LINEAR

LT, LT, LTC, LTM, Linear Technology and the Linear logo are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners.

News

MAKERS OF CHIPS, CARS, AND RADIO EQUIPMENT

Join Forces to Connect Cars with 5G



(Image courtesy of BMW)

Germany's largest automakers are preparing to upgrade their cars with a new generation of wireless technology, and they have enlisted partners in radio infrastructure and semiconductors to help.

Audi, BMW, and Daimler said that they were partnering with two major chipmakers and telecommunications equipment makers Ericsson, Huawei, and Nokia to develop and test the fifth generation of wireless technology, or 5G. They will also aim to build consensus around issues like protecting cars from hackers and the privacy of drivers.

The organization, which also includes American chip giants Qualcomm and Intel, has been created at a time of significant upheaval in the automotive industry. Car manufacturers are working on vehicles that not only collect data from sensors and cameras but also using wireless technology to broadcast and receive location data from other cars—data that could

help alert drivers about other vehicles on the road or even automatically avoid collisions.

The organization will focus on the tricky task of connecting cars to infrastructure, and other cars. Many wireless companies are experimenting with this technology—also known as Vehicle-to-X or V2X communications—and not without reason. In the United States, the Department of Transportation is considering rules that would require cars to broadcast their location to others on the road.

But enabling cars to share data with other vehicles requires cellular networks that are faster and more reliable than what smartphone users are familiar with. That is where 5G networks enter the picture. These networks, industry executives say, will connect to cars almost instantaneously and be reliable enough to meet the strict standards of highway regulators.

(continued on page 22)

SCIENTISTS STEER RADAR BEAMS with Slight Change of Perspective

THE IDEA OF METAMATERIALS brings to mind comic book elements like Captain America's vibranium shield or Wolverine's adamantium claws. But metamaterials are not fictional. They are synthetic materials that bend things like radio waves in ways that don't occur naturally.

One of the earliest applications for the technology is in radar systems. By applying voltages to an antenna built out of metamaterials, engineers can actively control the direction of the radar beam. That makes the radar system cheaper and smaller than ones steered by mechanical parts or other electronics.

But many engineers are not ready to stop using conventional materials to achieve similar results.

Last month, for example, scientists reported that they had built a new type of electronically-steered radar antenna. Writing in the *Journal of Applied Physics*, a team from the University of Wisconsin-Madison said that they had used a reflective antenna to bend radar beams in different directions.

The new technology brings together mechanical and electronic steering. A transmitter sends radio waves through an array of reflective antennas, which directs the radar beam depending on how the transmitter is tilted. The scientists are calling it a macro-electromechanical system (M²EMS)—a play on micro-electromechanical systems, or MEMS, which are widely used in sensors that react to tiny alterations in pressure or radio waves.

The team stressed that it will not use bulky mechanical rigs or specialized circuitry. "Our approach doesn't depend on exotic materials that bend the laws of physics," Nader Behdad, the electrical engineering professor who led the research, said in a news release.

"We've found a practical way to achieve beam steering that the antennas field has largely overlooked," he added.

Radar systems locate and track objects by emitting radio waves and measuring the reflected signals. Some of the most advanced systems use electronics to direct radio waves without having to mechanically point the antenna in different directions. But these antennas normally use expensive and bulky electronics, known as phase shifters, to steer the radar beams.


The phase shifter's bulkiness and cost have largely kept electronically-steered antennas out of commercial applications, like drones or automated driving systems. They are mostly reserved for defense applications, like fighter jets. Raytheon, for example, has developed an active electronically scanning array (AESA) system, which can track multiple objects, like ballistic missiles, at the same time. Lockheed Martin and Boeing are two other companies that make AESA radars.

What sets the M²EMS technology apart is that it doesn't need solid-state devices or phase shifters integrated into the aperture of the antenna. The result, according to the scientists, is a radar system that can detect objects faster than mechanical radars used on airplanes and ships.

"In defense situations, you need to detect incoming objects where you are going very quickly," said John Booske, another electrical engineering professor that worked on the project, which received \$1.1 million in funding from the United States Office of Naval Research.

"The ability of a mechanical rig to move a big, heavy parabolic dish back and forth limits how quickly you can respond to potential threats," Booske added.

(continued on page 24)



A team from the University of Wisconsin-Madison said that they had used a reflective antenna to bend radar beams in different directions.

(continued from page 20)

The 3G Partnership Project, an industry group that maintains cellular standards, has already completed a V2X standard, which will be released as part of a larger standard in 2017. 5G, industry analysts say, will likely appear in 2020.

But there are other technologies for connecting cars in the works. While 5G will have to share the airwaves with smartphones and other devices, a technology known as dedicated short range communications, or DSRC, has been developed specifically for cars. Several Silicon Valley startups like Autotalks and Savari spe-

cialize in making hardware and software based on the standard.

By sharing location data with other cars on the road, for instance, Savari's software can warn drivers of a possible collision or when other vehicles creep into blind spots. Paul Sakamoto, chief operating officer at Savari, said in an interview earlier this year that hardware in smartphones can be programmed to share the short-range data, so that drivers can avoid pedestrians with a phone in their pockets.

Rapidly and reliably sharing data is at the heart of automakers' big data projects. Last week, the three German automakers said that they would use a new service from digital mapmaker Here. It will warn drivers about accidents and locate parking spaces by pooling data from cameras and sensors inside hundreds of thousands of cars. That data will be sent wirelessly into the cloud and redistributed in real-time.

The new partnership will also examine privacy and security regulations, in response to rising concerns about how data from vehicles will be used. In August, U.S. lawmakers sent a letter urging the Federal Communications Commission to create privacy rules for connected cars. The letter expressed fears that data could be misused for targeted advertising – like what Google and Facebook are doing on the internet – which could appear on dashboard displays and billboards.

To help address these concerns, industry executives say that companies need input from multiple industries. It is necessary to “work closely together with the car industry to jointly develop solutions as well as provide input to regulation, certification, and standardization,” said Ulf Ewaldsson, Ericsson's chief technology officer, in announcing the new organization.

Audi's Christoph Voigt will serve as the chairman of the 5GAA's board. The 3GPP's Dino Fiore will be the director general of the organization, according to a statement. ■



INVENTORY TRENDING

Now on

sourceesb

View inventory trends over a
 1, 3 or 6 month time period.

Learn more at
sourceesb.com/whatsnew

MULTIPLY UP TO 20 GHz



Frequency Multipliers from **\$5⁹⁵**

qty. 10-49

For your leading-edge synthesizers, local oscillators, and satellite up/down converters, Mini-Circuits offers a large selection of **broadband doublers, triplers, quadruplers, x5, x7 and x12 frequency multipliers.**

Now generate output frequencies from 100 kHz to 20 GHz with excellent suppression of fundamental frequency and undesired harmonics, as well as spurious signals. All models feature low conversion loss and are designed into a wide array of off-the-shelf, rugged coaxial and surface-mount packages to meet your requirements. Our new MMIC doubler, CY2-143+ generates output signals from 4 to 14 GHz in a tiny 4x4mm QFN package!

Visit our website to view comprehensive performance curves, data sheets, PCB layouts, and environmental specifications. Order direct from our web store and have a unit in your hands as early as tomorrow!



Broadest Selection of In-Stock RF Switches



PIN Diode




Waveguide



USB Controlled



Electromechanical



Surface Mount

- Coaxial, Waveguide and Surface Mount options available
- SPST thru SP12T and Transfer configurations
- Frequencies from 10 MHz to 110 GHz
- All in-stock and ship same-day



Fairview Microwave
RF COMPONENTS ON DEMAND. *Done!*

News

(continued from page 21)

The new antenna works by focusing microwave signals through an array of reflective patch antennas. To focus the signal into a beam, it alters the electronic properties of the individual elements in the array. In addition, the individual elements can be tuned to act like a phase shifter and direct the radar beam.

The approach is similar to phase-varied array antennas, the team said. These systems are made up of miniature transmitters that each emit a fraction of a signal, which adds up to a single beam. By altering the electronic properties of each individual part, the antenna can steer the radio beam.

The MÆMS array is also built out of many individual elements. The difference, according to the scientists, is that it uses a single transmitter instead of many partial ones. There is a drawback to this design: it is more difficult to tune the antenna and shape the radar beam.

The scientists found the solution in the mechanical motion that they had originally tried to eliminate. They discovered that tilting the ground plane underneath the antenna array would tune all the elements simultaneously, directing the radar beam.

Though the MÆMS device is mechanical, the small tilting movement requires less time and force than turning a large reflector dish.

A prototype based on the research showed that slight tilts (around 0.05λ) in the ground plane could steer the beam +/- 10 degrees in two dimensions. Another prototype with the ground plane segmented into multiple parts was shown to steer beams +/- 30 degrees.

"Luckily for us, in order to do beam-steering, we really don't need to individually tune each element," said Behdad. "All we need to do is create a gradient and we can do that by simply tilting the ground plane." ■

TUNABLE ANTENNA CIRCUITS May Adapt to Environment Prepare for Launch

IN 1944, THE United States Army Signal Corps started paying scientists to study materials that could be used in radio equipment. The first substance under investigation was known as barium strontium titanite (a powdered ceramic) which is capable of being altered when shocked with an electric current.


The researchers gave the material a lukewarm review. It could be made into delay lines and filters operating at microwave frequencies, they wrote in a report, but fabricating the

material to jump between frequencies posed a significant challenge. Fast forward sixty years and engineers are still struggling with it.

Now, researchers from the University of California, Santa Barbara, recently announced a new method for shaping the barium compound into circuits – ones that can be reconfigured to access multiple frequencies. By reducing the amount of heat radiated from the material, the researchers were able to create smaller and more efficient circuits.

The work, which was based out of the UCSB Materials Research Lab, and which appeared in the journal *Applied Physics Letters*, breathes life into a material considered

(continued on page 26)



(Image courtesy of University of California, Santa Barbara, and *Applied Physics Letters*)

The Right RF Parts. Right Away.

The image shows a hand holding a silver stopwatch in the foreground, partially obscuring a laptop screen. The laptop screen displays the Fairview Microwave website. The website has a red header with the company logo and tagline 'RF COMPONENTS ON DEMAND. Done!'. Below the header is a navigation bar with 'Live Chat' and a phone number '1-800-715-4396'. The main content area is a grid of product categories, each with an image and a label: 'New Products', 'Adapters', 'Connectors', 'Amplifiers', 'Attenuators', 'Cable Assemblies', 'Terminations', 'Isolators', 'Circulators', 'Power Dividers', 'Antennas', 'Bias Tees', 'Shorts & RF Caps', and 'Couplers'. The stopwatch is held by a hand, and its face is clearly visible, showing the time.

We're RF On Demand, with over one million RF and microwave components in stock and ready to ship. You can count on us to stock the RF parts you need and reliably ship them when you need them. Add Fairview Microwave to your team and consider it done.

fairviewmicrowave.com
1.800.715.4396

Fairview Microwave
RF COMPONENTS ON DEMAND. *Done!*

(continued on page 24)

defective by chip industry standards. The material is only used in a small number of wireless capacitors, which are paired with antennas to tune into different frequencies.

But the barium compound has potential. It could be used “to create tunable antennas for cellular communications, which allows a small antenna to be tuned over a wide frequency range or enables a phone to adapt to different surroundings for improved efficiency and

battery life,” said Robert York, an electrical engineering professor, in an article published with the research.

He also suggested the material could be used to create phase-shifters for phased-array antennas in satellite communications.

Materials like barium strontium titanate are known for having high dielectric constants, meaning that they can be adjusted with a pulse of high voltage electricity. The National Institute of Standards and Technology, which sponsored the research in 1944, is studying

dielectrics to enable satellites and smart-phones to tune into precise frequencies. Many chipmakers like Intel and Samsung are eyeing the materials to shrink computer circuits toward the atomic level.

These qualities have been both a blessing and a curse. The material's large dielectric constants “present fabrication challenges because the inherently high capacitance density of the films requires smaller electrode dimensions and finer lithography than many typical integrated capacitor structures,” said York.

To manufacture the circuits, the researchers tweaked a widespread process for making compound semiconductors called molecular beam epitaxy (MBE). They were able to recalibrate the process to reduce current leakage, while keeping the circuits clean of contaminants.

The researchers also discovered that barium strontium titanite was weirdly susceptible to contamination, and that was probably a reason why engineers had struggled to increase quality over the years. Imperfections are also caused by high temperatures and oxygen involved in traditional manufacturing.

Once the researchers adjusted the fabrication process, the capacitors operated over a wide frequency range. When a prototype was embedded in a metal waveguide, the researchers found that it scattered radio signals from 100 MHz to 40 GHz.

If the material is to be used practically, the process and circuit design will need improvements, York said. But “the infrastructure for deposition and fabrication already exists within most semiconductor foundries,” he said, “so the timeline for exploiting this advance could be relatively short compared to the typical timeline for a materials advance.” ■

FASTER, QUIETER, SMALLER SIGNAL SOURCES QUICKSYN SYNTHESIZERS

Design smaller and more efficiently with National Instruments QuickSyn synthesizers. The revolutionary phase-refining technology used in QuickSyn synthesizers enables blazing fast switching speeds, very low spurious and phase noise performance, wide frequency range, and small footprint.

ni-microwavecomponents.com/quicksyn



QuickSyn Lite Synthesizer



© 2016 National Instruments. All rights reserved.

Inside TRACK

with
Jeff Shamblin,

Chief Scientist, Ethertronics


Interview by CHRIS DeMARTINO, Technology Editor

JEFF SHAMBLIN, Chief Scientist at Ethertronics, is responsible for overseeing all research and development projects for the corporation. Prior to joining Ethertronics, Shamblin worked for two RFID startup companies: SCS Corp. and Claridy Solutions. He has also served as an antenna consultant, providing design and analysis services to several wireless startups in the Southern California area. On top of that, Shamblin spent more than 20 years in antenna design and development in the aerospace industry at Lockheed Martin and Northrop Grumman. He holds seven patents related to antenna technology. Shamblin earned his bachelor's degree in physics from California State University, Northridge.

How has the approach to developing antenna solutions changed in the last five or 10 years?

Shamblin: Antenna design for consumer and commercial applications has undergone a few significant changes. One has been to put more emphasis on a system-level approach for the antenna system, where the antenna is designed for optimal RF system operation and for operation in conjunction with the many sensors that now populate a consumer mobile device, such as proximity sensors. A system-level approach is important to optimize the four to six antennas that now populate a smartphone, where isolation and correlation between the multiple antennas will, to a large extent, dictate the data rate that can be achieved, the quality of a voice call, or the accuracy of an embedded GPS receiver.

A second change involves designing the antenna system for the specific use cases that will likely be applied to the mobile device. For example, antenna performance can be optimized for a hand-loading condition for a smartphone, or a body-loading condition for a wearable fitness tracker.



“Interference mitigation will become more important as a larger number of RF-enabled devices are installed in homes and businesses.”

What are some of the challenges in terms of developing antennas for cellular communications?

Shamblin: The increased number of cellular bands dedicated to LTE systems along with carrier aggregation, where two or more frequencies are aggregated to improve communication-system throughput, have added complexity to the multiple-input, multiple-output (MIMO) antenna system in a smartphone. Also, the trend to bring 2×2 MIMO at Wi-Fi frequencies to the smartphone requires the integration of additional antennas into a small, compact volume.

Looking for just
the right part,
at just the right price...

Connect with over 200 distributors on the NEW SourceESB!



Find electronic parts fast -
from the only database
that verifies
part authorization.



Part Lists Tool

- ✓ Send multi-part RFQs
- ✓ Save your part lists to work on later
- ✓ Filter by authorized distributor

www.SourceESB.com

Wi-Fi has advanced significantly over the years, and it continues to transform. How will that affect antenna design—both now and in the future?

Shamblin: The main affect will be an added requirement to integrate a larger number of antennas into a device as higher orders of MIMO are brought to bear to increase data rates. Wi-Fi routers today will typically have three or four antennas installed to provide 3×3 or 4×4 MIMO capability—and 8×8 MIMO will soon be available for the Wi-Fi market.

Tell us a little bit about Active Steering technology.

Shamblin: Ethertronics has developed a technique to generate multiple radiation patterns from a single antenna structure. A small-form-factor antenna, along with a four-port switch and algorithm, comprise an Active Steering antenna system. The radiation pattern of the single antenna can be dynamically changed. The proprietary algorithm accesses a metric from the baseband processor—for example, SINR or RSSI. This metric is used to determine the radiation mode for optimal throughput. The end result is improved throughput and a more reliable communication link for cellular and Wi-Fi applications.

How have antenna testing requirements changed throughout the years?

Shamblin: In the cellular industry, handset antenna requirements have progressed from tracking radiation patterns and efficiency for 2G/3G systems to tracking total radiated power (TRP) and total isotropic sensitivity (TIS) performance for 3G systems. Requirements now include isolation and envelope correlation coefficient for 4G MIMO antenna systems. Another

change has been to measure and use system-level performance metrics, such as throughput in Wi-Fi systems, to optimize the antennas during the antenna integration process.

What challenges will the Internet of Things (IoT) bring to antennas?


Shamblin: Interference mitigation will become more important as a larger number of RF-enabled devices are installed in homes and businesses. Reliability of the communication link will also be important for this plurality of IoT devices to allow for continuous and seamless monitoring of a wide variety of devices. Ethertronics' Active Steering technology will be able to assist in decreasing interference, as well as making the RF communication links more reliable by bringing antenna diversity to each antenna port.

What impact do you think 5G will have on antenna development?

Shamblin: Some 5G implementations will require millimeter-wave antenna systems integrated into handheld and mobile devices, and these millimeter-wave antennas will require different manufacturing techniques to maintain tolerances and allow for better material selection. Millimeter-wave applications will require better control of the radiation pattern in comparison to 3G and 4G systems.

Another impact that will affect 5G systems at both sub-10-GHz and millimeter-wave frequencies will be the use of higher orders of MIMO to drive higher data rates. The need to integrate a larger number of antennas in a device where isolation and envelope correlation must be designed will create more difficulties in antenna-system design. Good antenna-system design practices will be required for optimized 5G communication systems. **mw**

STM (SPUR TAMER) WIDEBAND MIXER SERIES



Features

- | Low Spurs
- | High Isolation
- | Good Linearity
- | Small Size

Up to
**18.0
GHz**



Talk To Us About Your Custom Requirements.




Phone: (973) 881-8800 | Fax: (973) 881-8361

E-mail: sales@synergymw.com

Web: WWW.SYNERGYMWAVE.COM

Mail: 201 McLean Boulevard, Paterson, NJ 07504





POWER SPLITTERS/ COMBINERS

from **2 kHz to 26.5 GHz** as low as **94¢** ea. (qty. 1000)

NEW!

**THE WIDEST BANDWIDTH IN THE INDUSTRY
IN A SINGLE MODEL!**

EP2K1+ 2 to 26.5 GHz

EP2W1+ 0.5 to 9.5 GHz

EP2C+ 1.8 to 12.5 GHz


*The industry's largest selection includes **THOUSANDS** of models from 2 kHz to 26.5 GHz, with up to 300 W power handling, in coaxial, flat-pack, surface mount and rack mount housings for 50 and 75 Ω systems.*

From 2-way through 48-way designs, with 0°, 90°, or 180° phase configurations, Mini-Circuits' power splitter/combiners offer a vast selection of features and capabilities to meet your needs from high power and low insertion loss to ultra-tiny LTCC units and much more.

Need to find the right models fast? Visit minicircuits.com and use Yoni2®!

It's our patented search engine that searches actual test data for the models that meet your specific requirements! You'll find test data, S-parameters, PCB layouts, pricing, real-time availability, and everything you need to make a smart decision fast!

All Mini-Circuits' catalog models are available off the shelf for immediate shipment, so check out our website today for delivery as soon as tomorrow!

 **RoHS Compliant**
Product availability is listed on our website.

 **Mini-Circuits®**

INNOVATIVE MODEL LEADS TO NOVEL BEAMFORMING TECHNIQUE

COMMUNICATIONS SYSTEMS AND other high-frequency electronic systems are now leveraging multiple-element antenna arrays rather than single antennas and advanced computer-modeling techniques to fine-tune physical designs. On that front, a group of researchers from China's Wuhan University applied mathematical modeling and modern sensing and sampling methods to optimize beamforming under various array element conditions. Beamforming is an important part of array signal processing in many applications, including radar, sonar, and satellite-communications (satcom) systems.

The researchers employed convex constrained optimization and compressed-sensing beamforming (CCOB-CS) models and an orthogonal matching pursuit (OMP) approach to achieve high mainlobe gain and low sidelobes with the aid of MATLAB mathematical-based computer modeling software from MathWorks (www.mathworks.com).

Conventional beamforming (CBF) methods provide good directional resolution and rejection of interference under stationary conditions. When spatial signals are constantly changing, however, the steering vector of the desired signal will deviate, leading to signal error problems. Some of the limitations of CBF methods have been confronted by adaptive beamforming methods using neural networks to dynamically steer the main beam towards the desired signal. But the approach is relatively slow and requires a large amount of processing power, with compromises in beamforming gain.

The new beamforming optimization approach involves using an analog-to-digital converter (ADC) in the direction of moving signals to take a few samples for analysis. By using a small number of low-dimensional snapshots to accurately reconstruct the original signal, the approach can provide suitable gain without requiring a large amount of digital processing power.

In a scenario with little change, an ADC can capture a statistically valid number of samples to construct a good covariance matrix. But when changes become more frequent, the number of samples required to reconstruct the sampled signals increases dramatically, requiring gigasample-per-second sampling rates. For an array assumed to be a linear array, the direction of arrival (DOA) will change when the linear array is moving in a circular fashion as well as changing in angular velocity.

The research team focused their beamforming improvements on satellite signals, specifically on the Global Navigation Satellite System (GNSS), hoping to protect desired signals from loss and interference. To overcome estimated errors in the DOA of the satellite signals, the steering vector is estimated by the multiple-signal-classification (MUSIC) principle. Using an optimization equation, it is possible to obtain the best estimated value of the steering vector for the desired signal.

For further details, see "A Novel Beamforming Technique," *IEEE Antennas & Propagation Magazine*, Vol. 58, No. 4, August 2016, p. 48.

CIRCULARLY POLARIZED REFLECTARRAY SERVES KA-BAND SYSTEMS

A BROADBAND, CIRCULARLY polarized reflectarray (RA) has been developed for Ka-band radar and satellite-communications (satcom) applications. The printed-circuit reflectarray, which measures 25×25 RA with physical size of 90×90 mm², consists of two dielectric substrate layers attached by adhesive. The lower substrate is Duroid 5880 circuit material with dielectric constant (Dk) of 2.2, and the upper is Duroid 6010 circuit with Dk of 10.2, both from Rogers Corp. (www.rogerscorp.com). An international team of researchers from Egypt, France, China, and the University of Mississippi, Oxford, coordinated their efforts on the compact array's development by creating a unit cell and then optimizing it for best radiation pattern performance throughout the array.

The RA and its unit cell were simulated with the aid of the Microwave Studio wcomputer-aided-engineering (CAE) software from Computer Simulation Technology (CST). It predicted the effects of signal-incidence angle on the RA's performance as well as the effects of air holes and metallic plated viaholes on the multiple-circuit-board RA structure.

The software was also used to design a dual-mode, circularly polarized feed horn for the RA. The dual-mode feed horn uses separate coaxial connectors for left-handed circular polarization (LHCP) and right-handed circular polarization (RHCP). The RA was designed as a broadside radiator with a design frequency of 30 GHz. Simulations of radiation patterns agreed closely with measurements at microwave and millimeter-wave frequencies (from 27 to 35 GHz) made on commercial test equipment.

See "Ka-Band Circularly Polarized Reflectarray," *IEEE Antennas & Propagation Magazine*, Vol. 58, No. 4, August 2016, p. 60.

Directional / Bi-Directional COUPLERS



5 kHz to 18 GHz up to 250W from **95¢** ea. (qty. 1000)

Now! 475¢ Looking for couplers or power taps? Mini-Circuits has ~~326~~ models in stock, and we're adding even more! Our versatile, low-cost solutions include surface-mount models down to 1 MHz, and highly evolved LTCC designs as small as 0.12 x 0.06", with minimal insertion loss and high directivity. Other SMT models are designed for up to 100W RF power, and selected core-and-wire models feature our exclusive Top Hat™ for faster, more accurate pick-and-place.

At the other end of the scale, our new connectorized air-line couplers can handle up to 250W RF input power, with low insertion loss and exceptional coupling flatness! All of our couplers are RoHS compliant. So if you need a 50 or 75Ω, directional or bi-directional, DC pass or DC block coupler, for military, industrial, or commercial applications, you can probably find it at minicircuits.com, and have it shipped today!



www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com

495 rev E

Waveguide Components

Same-Day Shipping

**RF Solutions
From RF Engineers**

RF Solutions From RF Engineers

866.727.8376
visit pasternack.com today!





All Quiet on the Compensation Front

Although concerns and challenges exist, the RF/microwave industry is continuing to provide stable salaries along with high job satisfaction.

What's the good news in this year's *Microwaves & RF* Annual Salary & Career Report? For one thing, 90% of those who responded report being satisfied in their current position. This high number seems to indicate that the RF/microwave industry is a good one to be a part of. The same number (90%) also said they would recommend engineering as a career path to a young person. As one respondent explained, "The field is wide open. The possibilities are only limited by a person's interest in advancing." Another noted, "You can work on new technology and influence the future in a positive way. You can continue to learn and grow—and often achieve fulfillment doing worthwhile things."

ON THE OTHER HAND....

Not all the respondents were so optimistic. Despite the high level of job satisfaction, work environment concerns were voiced. One respondent said, "There is constant pressure from management to force cookie-cutter solutions where they clearly don't fit." And another bemoaned "the lack of good design discipline and commitment to good products."

This year's survey—the third for *Microwaves & RF*—consisted of a total of 1,393 respondents. Job titles varied among those surveyed, allowing insight to be provided from a range of perspectives.

In terms of compensation, the average base salary was reported to be \$110,844, and 68.2% of respondents said they felt adequately compensated for what they do. Furthermore, the average bonus came out to \$4,182.

The survey responses also demonstrated the need to bring young engineers into the industry. Just over 40% of respondents are age 60 or older, with an average age of about 53. With many engineers approaching retirement, the industry clearly needs a next generation of engineers who will continue to drive RF/microwave technology in the future.

INFORMATION EVERYWHERE

Keeping up with the latest technology is another common theme, proving that an engineering career involves lifelong learning. Many of those surveyed continue to educate themselves in various ways. White papers, publications, webcasts, and seminars were the most commonly used forms of education. Other methods include engineering videos, textbooks, and more.

One prevalent challenge among respondents is finding the time to stay current with engineering information. Moreover, some expressed dissatisfaction regarding the quality of published information.


One respondent stated, "There is too much information on the web. Often times, this information is vague, not detailed, or is inaccurate. The challenge is to verify and validate the information." Another noted, "Much of the information is veiled advertising. Products are often made to seem better—or easier to use—than they turn out to be." Yet another respondent offered, "It takes work to recognize value when there are also many 'fluff' articles and emails."

Overall, the *Microwaves & RF* Annual Salary & Career Report results present the RF/microwave industry in a positive light. While not everything is perfect, engineers seem to be both well compensated and satisfied at the same time. With that being said, the industry appears to be in good shape. **mw**


—Chris DeMartino, Technical Editor

THE TYPICAL ENGINEER

YoY - Years in the Profession




YoY - Age




In 2016

77%

of engineers have
20+ years of experience



Top Work Locations in 2016





TEST CABLES *up to 40 GHz!*

Reliability You Can Trust... from **\$68⁹⁵** ea. (qty.1-9)

Why do 10,000 customers trust Mini-Circuits test cables? Because they simply don't fail! Our test cables have been performance qualified to 20,000 flexures* and come backed by our 6-month product guarantee**, so you can be confident you're getting rugged construction, reliability, and repeatable performance you can depend on. Whether you're performing production

test, burn-in, over-temperature testing, hi-rel testing – you name it – chances are there's a Mini-Circuits test cable for your application in stock, ready for immediate shipment. Order some for your test setup at minicircuits.com today, and you'll quickly find that consistent long-term performance, less retesting and fewer false rejects really add up to bottom-line savings, test after test!

Model Family	Capabilities	Freq. (GHz)	Connectors†
KBL	Precision measurement, including phase, through 40 GHz	DC-40	2.92mm
CBL- 75+	Precision 75Ω measurement for CATV and DOCSIS® 3.1	DC-18	N, F
CBL	All-purpose workhorse cables for highly-reliable, precision 50Ω measurement through 18 GHz	DC-18	SMA, N
APC	Crush resistant armored cable construction for production floors where heavy machinery is used	DC-18	N
ULC	Ultra-flexible construction, highly popular for lab and production test where tight bends are needed	DC-18	SMA
FLC	Flexible construction and wideband coverage for point to point radios, SatCom Systems through K-Band, and more!	DC-26	SMA
NEW! VNAC	Precision VNA cables for test and measurement equipment through 40 GHz	DC-40	2.92mm (MtoF)

* All models except VNAC-2R1-K+

** Mini-Circuits will repair or replace your test cable at its option if the connector attachment fails within six months of shipment. This guarantee excludes cable or connector interface damage from misuse or abuse.

† Various connector options available upon request.

Contact apps@minicircuits.com to discuss your special requirements.



COMPENSATION

\$

Average Salary in 2016

\$110,844

\$4,182
Average Bonus

\$2705
Average
Stock
Options

\$2,458
Average Other Options


Salary Changes

33.6%
Salary stayed the same

11.6%
Saw salary decrease


54.7%
Saw salary increase

YOY Salary by Experience




JOB SATISFACTION

How Satisfied Are You?



Recommend Engineering



Average Hours per Week



55

Reasons Engineers Would Leave the Profession



33.5%
Try something different



27.1%
Pursue other opportunities



19.1%
Do something more fulfilling




26.4%
To make more money



23.7%
To do something less stressful

Feeling Challenged

Somewhat Challenged



Sufficiently Challenged

Most Important Factors in Job Satisfaction



Research

Researching potential design solutions

Challenges

The challenges that accompany the design of new products




Benefits Society

Opportunity to design products that can benefit society



EMPLOYMENT OUTLOOK

Actively Seeking a New Position





CONCERNS

Top Concerns at Work

Resources



Funding



Time




On a scale of 1-10, with 10 being most pressing, how pressing are each of the following problems in your work?

Insufficient human resources to get job done	6.9
Finding the optimal components for my designs	6.83
Insufficient funding for my design projects	6.71
Having to compromise my design approaches	6.54
Time-to-market pressures	6.4
Inability to adequately test product designs	6.14
Competitive market pressures	5.87
Shrinking product life cycles	5.87
Lack of design management direction	5.66
Politics at work	5.33
Second sourcing for the components specified	5.31
Management taking company in wrong direction	4.93
Seniority issues	4.3

OUTSOURCING

Reasons for Outsourcing




Work Being Outsourced

Manufacturing/assembly	46.6%
Software engineering/development	42.6%
Design	36%
PCB layout	32.7%
R&D	22.7%
CAD/CAE	22.3%
Software verification/test	21.4%
Design verification	15.5%
Final test	14.7%
Drafting	11%
Incoming inspection	3.4%

Currently Outsourcing?

48%
No



52%
Yes



With this team on your bench, the sky's the limit.

Visit us at
EuMW in London,
booth 3

Signal generation and analysis for demanding requirements

When working at the cutting edge of technology, you shouldn't waste your time with inferior tools. Rely on measuring instruments evolved in the spirit of innovation and based on industry-leading expertise. Instruments like the R&S® SMW200A vector signal generator and the R&S® FSW signal and spectrum analyzer. Each is at the crest of today's possibilities. As a team, they open up new horizons.

See for yourself at www.rohde-schwarz.com/ad/highend



2016

WHAT'S KEEPING ENGINEERS UP AT NIGHT?



Staying current

with new and emerging technologies

Looming Project Deadlines



18.6%

Nothing keeps me up at night

YOUR COMPLETE MILLIMETER WAVE **SOLUTION**

new
Low-Cost
VNA Extender



MANY ITEMS IN STOCK



MADE IN USA


www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505
T: 424-757-0168 | F: 424-757-0188 | sales@sagemillimeter.com




SAGE
Millimeter, Inc.

EDUCATION

How engineers are keeping up



Which forms of education does your company reimburse you for?





emerge™

November 2-4, 2016
McCormick Place, Chicago

Learn. Disrupt. Network.

Join us in Chicago this November for real-world IoT insights, strategic and technical sessions, and live demos in four tracks: Smart Cities, Industrial IoT, IoT Engineering, and IoT Security.

Discount Codes:


Free Expo Pass: **IOTEDEXPO**

15% OFF Conference Pass: **IOTE-DES16**


 iotemerge.com




EFFICIENT ENGINEERING




Have you seen growing demand for lower-power, more energy-efficient products from your customers?




Have you seen growing demand for miniaturization in your product designs?




Have these low-power requirements become stricter over the last year?




TEST & MEASUREMENT




Do you feel that your company invests sufficiently in test and measurement equipment to support your design needs?




Do you think testing is still a challenge for the design process in terms of time consumption?




Is there sufficient training and documentation for your test requirements?



Do you expect the Internet of Things to affect test methodologies at your company?



Say their company has replaced box test instruments with modular solutions like PXI.



Do you use design simulation software in your product design process?

DUAL or SINGLE LOOP SYNTHESIZER & PLO MODULES

Features:



- Proprietary digital Integer and Fractional PLL technology
- Lowest digital noise floor available -237 dBc/Hz figure of merit
- Output frequencies from 100 MHz locked crystal to 30 GHz
- Available with reference clean up dual loop, or single loop for very low noise reference
- Parallel fixed band stepping or SPI interface synthesized up to octave bandwidths
- Reference input range 1 MHz to 1.5 GHz
- Dual RF output or reference sample output available
- +12 dBm standard output power +16 dBm available
- Standard module size 2.25 X 2.25 X 0.5 Inches (LxWxH)
- Standard operating temperature -10 to 60 °C, -40 to +85 °C available

Up to
30 GHz*

Applications:

- SATCOM, RADAR, MICROWAVE RADIO

* 16 - 30 GHz with added x2 module < 1" in height.



Talk To Us About Your Custom Requirements.



Phone: (973) 881-8800 | Fax: (973) 881-8361
E-mail: sales@synergymicrowave.com
Web: WWW.SYNERGYMICROWAVE.COM
Mail: 201 McLean Boulevard, Paterson, NJ 07504

Differentiating BAW and SAW Technologies

BAW and SAW technologies both make use of acoustic waves—albeit in different ways and at different frequencies—as part of high-frequency filters, resonators, and delay lines.


ACOUSTIC WAVES ARE PART of the operating mechanisms of both surface-acoustic-wave (SAW) and bulk-acoustic-wave (BAW) components, although the two acoustic component types and technologies have essential differences. Both technologies can support a number of resonant-type components, including oscillators, filters, and delay lines. SAW components are limited in frequency compared to their BAW counterparts. However, both technologies provide effective circuits within their frequency ranges, and in small sizes that make them attractive for a wide number of applications in commercial, industrial, and military systems.

Both SAW and BAW components leverage the electromechanical properties of certain materials, notably anisotropic piezoelectric materials. Piezoelectric materials transform applied mechanical stress into electrical energy and can also convert electrical energy into mechanical stress.

SAW components make use of the electromechanical properties of these materials through the propagation of acoustic waves along the surface of the piezoelectric material. The acoustic waves travel through the interleaved metal “fingers” of interdigital transducers (IDTs) fabricated on the appropriate piezoelectric substrate.

Piezoelectric materials can produce electricity from applied mechanical stress, in addition to transforming applied electrical energy into mechanical energy, such as acoustic waves. This is accomplished by fabricating interdigital transducers (IDTs) on the surface of a piezoelectric substrate, such as lithium tantalite (LiTaO_3), lithium niobate (LiNbO_3), or quartz crystal.

Electrical RF/microwave energy at one end of the transducer is transformed into mechanical energy in the form of acoustic waves that travel along the interleaved metal fingers, and are transformed back to electrical RF/microwave energy at the other end of the transducer. With the slower velocity of these acoustic waves compared to the input RF/microwave waveforms, signal processing such as filtering and time delays can be performed in the acoustic frequency range, and then realized in the RF/microwave frequency range at the output of the SAW transducer.




1. Large circular and rectangular piezoelectric substrate wafers enable large volume manufacturing of SAW components. In this case, these wafers are used strictly for custom SAW components and modules for military applications. (Courtesy of Phonon Corp.)

Commercial SAW components can be fabricated on relatively large piezoelectric wafers (Fig. 1) compared to the smaller wafers used for fabricating semiconductor devices. Using larger wafers enables the production of relatively large volumes of SAW components for relatively low cost, with the opportunity to fabricate RF/microwave bandpass and other filters in much smaller sizes than ceramic filters for the same center frequency.

SAW components are typically manufactured at frequencies to about 2 GHz. Since the dimensions of the IDT structure shrink with increasing frequency, the challenges of producing SAW components with sufficiently small IDT dimensions to support those higher frequencies make it impractical at higher frequencies.

BAW components typically operate at higher frequencies that SAW components, almost starting where SAW components leave off—at about 1.5 GHz and higher. BAW components are also fabricated on piezoelectric materials, although typically using different substrate materials than their SAW counterparts.



TINY Wideband Transformers & Baluns!

NOW!
4 kHz - 18 GHz From **99¢** ea. (qty. 20)

To support an even wider range of applications, Mini-Circuits tiny surface-mount transformers and baluns now cover frequencies from 4 kHz up to 18 GHz! Our latest designs achieve consistent performance across very wide frequency bands, and our baluns have demonstrated great utility for use with chipsets. With over 250 trusted models in stock representing a wide selection of circuit topologies and impedance ratios, chances are, we have a solution for your needs!

Our Low Temperature Co-Fired Ceramic (LTCC) models provide reliable performance in tough operating conditions, tiny size – as small as 0805 – and very low cost. All core-and-wire models are available with our exclusive Top Hat® feature, improving pick-and-place accuracy and throughput. We even manufacture our own transmission wire under rigorous control and use all-welded connections to ensure reliability and repeatability you can count on.

Visit minicircuits.com and use **Yoni2®**, our patented search engine to search our entire model database by performance criteria and find the models that meet your requirements. Order today and have them in hand as soon as tomorrow! Cost-effective custom designs and simulations with fast turnarounds are just a phone call away!



TC
0.15" x 0.15"



NC
0.08 x 0.05"
Ceramic



NCR2
0.08 x 0.10"
Ceramic

 **RoHS compliant.**



“ At frequencies of about 2 GHz or below, SAW filters are capable of excellent rejection of unwanted, out-of-band signals while maintaining flat amplitude response across the passband frequency range. ”

In fact, one of the more popular piezoelectric substrate materials for BAW components is aluminum-nitride (AlN). BAW components also function differently than SAW components. In a BAW component, the acoustic waves travel and are stored in the piezoelectric material rather than across the top surface of the substrate.

Metallization for a BAW component is deposited on the top and bottom of the piezoelectric material, creating a form of acoustic channel for the waves. The acoustic waves essentially bounce between the metal layers and through the piezoelectric material, forming a standing acoustic wave. The resonant frequency of the standing wave is a function of the substrate thickness and the mass and type of metallization, with thinner substrates yielding higher operating frequencies.

Different types of metal films are used in BAW components than in SAW components—typically aluminum metallization for lower-power components and tungsten (W) for higher-power components. Although BAW components such as filters can be fabricated for use at frequencies below 1.5 GHz, and well into the frequency range of SAW components, the larger sizes of BAW components at those lower frequencies results in lower yields of components per piezoelectric wafer, making it difficult to be cost-competitive with SAW filters or even ceramic filters at those lower frequencies.

BAW components operate to higher frequencies than SAW components—about 15 GHz and higher compared to SAW components, which are available to about 2 GHz. The nature of BAW components, with high-density acoustic energy stored within the metal plates of a piezoelectric substrate, results in lower-loss components at higher frequencies than SAW components.

They are also capable of high-quality-factor (high-Q) reso-

nators in relatively small sizes for microwave filters with high rejection and sharp band edges. In general, BAW components (such as filters) can typically achieve lower passband insertion loss than SAW filters, although usually at higher frequencies.

At frequencies of about 2 GHz or below, SAW filters are capable of excellent rejection of unwanted, out-of-band signals

while maintaining flat amplitude response across the passband frequency range. In general, SAW components exhibit greater variations in performance with temperature than BAW components at their higher frequencies, although careful selection of SAW substrate materials can help limit these performance variations. In addition, some manufacturers offer temperature-compensated SAW (TC-SAW) components to minimize temperature variations without sacrificing the excellent electrical



2. Manufacturing of high-performance SAW components requires computer-controlled automated measurements of SAW component performance.

(Courtesy of Phonon Corp.)

performance of SAW technology.

Similarly, some suppliers offer BAW components, mainly filters, based on “low-drift” piezoelectric materials that minimize variations in frequency with temperature, usually characterized in parts per million per degrees Centigrade (ppm/°C). The temperature shifts for these components can be in terms of negative or positive values (changes in frequency with temperature), with an ideal component characterized by 0 ppm/°C. At least one manufacturer offers these low-drift BAW components at frequencies to 9 GHz and higher.

By applying consistent manufacturing practices, quality control, and computer-controlled test methods (*Fig. 2*), some manufacturers of SAW components—such as Phonon Corp. (www.phonon.com)—have succeeded in achieving some of the highest quality levels in SAW components like filters, delay lines, oscillators, and modules. These quality levels are sufficient for an exclusively military customer base. **mw**

Industry Trends

JOHN COONROD | Technical Marketing Manager

Rogers Corp., Advanced Connectivity Solutions, 100 South Roosevelt Ave., Chandler, AZ 85226-3416;
(480) 961-1382, www.rogerscorp.com

Materials Make the Difference in Low-PIM PCB Antennas

Certain characteristics of circuit materials can indicate whether a material will contribute to higher or lower levels of PIM for a printed-circuit RF/microwave antenna.

Antennas are the beginning and end components of many communications systems, and the performance of modern wireless communications networks depends on these antennas achieving low passive-intermodulation (PIM) levels. PIM is a complex phenomenon that results in the generation of spurious energy. It is not caused by circuit materials, but results from the design and mechanical structure of high-frequency circuits, from circuit-assembly practices, and/or from system-level effects.

Still, circuit materials can play a part in achieving low PIM in PIM-sensitive applications. For low-PIM printed-circuit-board (PCB) antennas, some of the PIM performance depends on the design, and some on the choice of PCB materials. Understanding how PCB characteristics influence PIM performance can ease the task of choosing circuit materials for low-PIM PCB antennas.

Maintaining low PIM in a communications system is a complex problem due to the large number of variables that contribute to PIM. A quick list of PIM-causing variables includes cables, connectors, passive components, solder joints, and even placement of hardware. It gets even more complex with inter-

actions among variables. The proper choice of circuit materials for a PCB antenna can at least shrink one list of variables.


RISE OF PIM

PIM has become more of a design issue in recent years with the growing number of wireless applications and their associated signals occupying a limited amount of available bandwidth. Two or more closely spaced signals within the same operating

band can produce intermodulation distortion due to the mixing of their lower-order harmonics and the mixing of those harmonics with the two fundamental signals (Fig. 1). The signals may come from the same wireless base station, or they could be signals reaching the antenna from additional, outside sources.

Such intermodulation was once only associated

with active devices, such as semiconductor mixers and amplifiers, but in recent years it has become evident that intermodulation can be caused by passive components, too, including antennas. It can affect applications with single antennas used for transmit and receive functions and multiple carrier frequencies, especially when those antennas exhibit the non-



1. This plot shows how intermodulation products result from the mixing of two fundamental-frequency signals and their harmonics.

linear behavior that could create PIM. When the amount of spurious energy produced as PIM falls within the operating frequency range of a receiver, it can qualify as interference.

At the system level, anything in the RF signal path between the transmitter and receiver can cause PIM, especially ferromagnetic materials or metals and any materials with ferromagnetic properties. Materials such as rust and metals like nickel and iron can be sources of PIM. Anything that interrupts the signal path of a transmission line, e.g., poorly fitted interconnections or debris in the mating area of connectors, can cause PIM. Even a rusty fence in the vicinity of a wireless transmitter could trigger PIM, with sufficiently high transmit power.

In a PCB-based antenna, such as a microstrip patch antenna, circuit cleanliness (or lack thereof) may also cause problems. For example, residue remaining on a PCB following fabrication and left behind by inadequate PCB cleaning procedures can be sufficient to induce nonlinear effects that result in PIM. A number of different kinds of plated finishes on PCBs can contribute to higher levels of PIM—electroless nickel, immersion gold (ENIG), and electroless nickel, immersion palladium, immersion gold (ENIPIG) are two such types.

MATERIAL CONSISTENCY

The choice of PCB material itself may also play a part in the PIM performance of a PCB antenna. Several circuit material parameters can be used to project how well a PCB antenna is expected to perform, including consistency of dielectric constant (Dk), stability of Dk with temperature, and mechanical stability with temperature. Ideally, the Dk of a circuit substrate material should be uniform throughout each board and consistent from board to board for good circuit-to-circuit repeatability.

Because Dk determines the circuit dimensions required for optimum antenna performance at a desired wavelength/frequency, any circuit material intended for PCB antenna design should feature dielectric constant within a tight tolerance. Although predicting PIM performance for any antenna design is difficult, using the optimum circuit material to achieve the best performance for a printed antenna will also generally deliver the best PIM performance.

The Dk determines the impedance of the patch pattern and the microstrip transmission lines feeding the patch. Consequently, excessive variations in a circuit material's Dk will result in changes in impedance and frequency throughout the printed antenna circuit and unwanted variations in antenna radiation pattern. A Dk tolerance of ± 0.05 is considered quite good for printed antennas, as well as for most other high-frequency circuit applications.

Consistent circuit material Dk is also desirable across a wide operating-temperature range. That's because printed antennas and their transceivers may be asked to perform flawlessly over

a wide range of operating conditions, from day to day or from season to season in outdoor base stations and cell sites.

The parameter that provides insight into the stability of a circuit material's Dk with temperature is the thermal coefficient of Dk (TCDk). For a given material, this parameter notes by how many parts per million (ppm) the Dk will change per change in temperature in degrees centigrade ($^{\circ}\text{C}$). If the TCDk value of a material is high, the Dk will change by a relatively large amount with temperature, and will change the antenna's resonant frequency as well as alter the radiation pattern for the desired frequency range.

A TCDk value can be positive or negative, depending upon the formulation of the circuit material. Considering the absolute value of a material's TCDk, a value of 50 ppm/ $^{\circ}\text{C}$ or less is quite good, or within the range of ± 50 ppm/ $^{\circ}\text{C}$.


In terms of real-world circuit materials used for PCB antennas, FR-4 typically represents a low-cost circuit-material solution. However, the tradeoff for low cost is a Dk that varies widely with temperature, characterized by a high value of TCDk. When room temperature (or $+25^{\circ}\text{C}$) is used as the starting point for normalized Dk, a circuit material's Dk may increase or decrease at other temperatures. When compared to other circuit materials, the changes for FR-4 can be dramatic, with significant decreases in Dk at temperatures below $+25^{\circ}\text{C}$ and large increases in Dk for temperatures above $+25^{\circ}\text{C}$.

Ideally, materials for PCB antennas should provide stable Dk with temperature, denoted by lower values of TCDk. Depending on formulation, commercial materials, such as RO3003 and RO4003 laminates from Rogers Corp. (www.rogerscorp.com) can have negative or positive TCDk values, describing how the material Dk changes with temperature.

For RO3003 laminates, which are polytetrafluoroethylene (PTFE) circuit materials reinforced with ceramic fillers, the TCDk is extremely low and negative, at only -3 ppm/ $^{\circ}\text{C}$, for very little change in Dk with temperature. This material has a Dk of 3.00 with tolerance of ± 0.04 . For RO4003 laminates, which also have quite low TCDk, the value is positive at 40 ppm/ $^{\circ}\text{C}$. This hydrocarbon circuit material, reinforced with ceramic filler, has a Dk value of 3.38 and tolerance of ± 0.05 .

Another circuit-material parameter for antennas related to temperature is coefficient of thermal expansion (CTE). Though also given in units of ppm/ $^{\circ}\text{C}$, it is a measure of the mechanical changes in a circuit material due to changes in temperature. Because a material will expand and contract according to changes in temperature in its x, y, and z axes, the CTE of candidate materials for an antenna design must be compared in all three axes.

In particular, these CTE values should be compared to the CTE values for other materials used on a PCB. This includes the copper used to form a patch antenna pattern and its microstrip



2. A PCB laminate's copper conductor roughness can impact the amount of PIM produced by circuits fabricated on that circuit material.

feed lines, in addition to copper plating used on plated through-holes (PTHs) that might connect an antenna to the different layers of a multilayer circuit. In the x and y dimensions, the circuit patterns and the dielectric material will expand and contract; in the z dimension, the metal of the PTHs and the thickness of the dielectric material will change with temperature.

Ideally, the CTE values for all materials of interest should be

fairly closely matched. This will prevent stresses at the interfaces of different materials caused by mechanical changes with temperature. Since the CTE of copper is about 17 ppm/°C, a CTE value for a PCB material that is within range of copper is considered good, such as 60 ppm/°C or less. The CTE is not just a factor to consider for printed-antenna performance and reliability. It is also an indicator of a circuit material's capability to withstand the high temperatures used when manufacturing a printed antenna, such as for lead-free solder-reflow processes.

PATROLLING ANTENNA PIM

When considering high-frequency circuit materials for printed antennas, metallic rather than dielectric materials are the main concern. Rough copper-laminated surfaces of PCB materials are a leading source of PIM in such antennas. Ideally, the surface of a PCB's copper laminate should be as smooth as possible to promote linear behavior. Specifically, the surface of concern is the copper-substrate interface of the laminate. As the roughness of the copper surface increases, the EM behavior of the copper as a conductor becomes increasingly nonlinear and more subject to generating higher levels of PIM as an antenna circuit (*Fig. 2*).

As noted earlier, treatments applied on the copper foil can raise a PCB antenna's level of PIM. Treatments are often performed to improve the adhesion of the copper layer to the

AUTOMATED RF TEST SYSTEMS

from

JFW

**Attenuator Assemblies
Transceiver Testing
RF Switch Assemblies
RF Matrix Switches
Handover Test Systems**



JFW Industries, Inc.

317-887-1340

877-887-4539

www.jfwindustries.com

sales@jfwindustries.com

“Although PIM is a type of distortion that affects system-level communications performance, it starts at the component level (i.e., connectors, antennas, etc.)”

dielectric layer. However, a copper treatment with ferromagnetic properties such as nickel-based treatments can be a source of higher PIM levels; therefore, it's a good idea to minimize use of such PIM-causing treatments.

In terms of a PCB's dielectric material, for low PIM levels, the guidelines provided earlier should be followed for consistent Dk held within a tight tolerance window. In addition, the dielectric material should exhibit low loss as evidenced by a low value of dissipation factor (Df).

Furthermore, as a simple rule of thumb, a thinner circuit laminate will yield worse PIM performance than a thicker circuit laminate, although this is not due to the dielectric properties. The amount of PIM is very much subject to the design of the printed circuit. In a thinner antenna circuit, greater power density is concentrated in a smaller area than a thicker antenna circuit with wider conductors. If any conditions for PIM are present, such as rough copper foil or residue from PCB fabrication, the higher power density will add to conditions favorable for generating higher levels of PIM.

Although PIM is a type of distortion that affects system-level communications performance, it starts at the component level (i.e., connectors, antennas, etc.). As wireless communications services extend throughout the world, with strong com-

petition for available frequency bands, PIM becomes more critical than ever. As a result, lower levels of PIM are required to maintain system-level performance and avoid symptoms such as dropped calls and diminished coverage areas.

PIM performance can be compared in terms of dBm (power relative to 1 W) or dBc (power relative to the carrier). A PIM level of -145 dBc was once considered satisfactory. But as the number of subscribers increased along with the number of cell sites to serve them, required PIM levels continued to drop. They initially fell to -150 dBc, and now -153 dBc is considered adequate.


To achieve printed antennas with the performance required for low PIM, the circuit materials must play their parts to help minimize intermodulation distortion. Although no industry-standard test methods exist for characterizing circuit materials for PIM, a technique was developed to characterize the latest generation of low-PIM circuit laminates, such as RO4730G3 circuit material from Rogers Corp. (see “*Laminates Lay Foundation for 5G Antenna Circuits*” on mwr.com).

Evaluation involved the fabrication of a 12-in.-long microstrip transmission-line circuit on 60.7-mil-thick RO4730G3 laminate. Since so many variables can impact PIM and its testing, a circuit's PIM performance may change dramatically over even the short period of time required for testing

(i.e., a few seconds). To reveal consistency in PIM performance, measurements should be performed for a time period much longer than just those few seconds. Thus, the microstrip circuit's PIM performance was measured for a total of 55 s, with 10 data points collected every second to produce a total of 550 plots of PIM versus time (Fig. 3).

The RO4730G3 material, which was engineered for printed antennas, is capable of PIM levels of -163 dBc or better. It is an example of a material with the characteristics—tight Dk tolerance, smooth copper foil, excellent CTE—that support low PIM levels for printed-circuit antennas. **IMW**

Editor's Note: To learn more about the test methods used to characterize circuit laminates for PIM, copies of “PIM and PCB Antennas: Your Guide to Circuit Materials for Low Passive Intermodulation (PIM) Antennas” are available for free download at www.rogerscorp.com.



3. PIM testing as a function of time was performed on RO4730G3 circuit laminates using a 12-in.-long microstrip transmission-line circuit on 60.7-mil-thick circuit material.



BIAS-TEES

100 kHz-12 GHz Now up to 40W RF Power

Whether your applications call for biasing amplifiers, laser diodes, or active antennas, DC blocking, DC return, satellite communications, test, or if you have custom requirements, just contact Mini-Circuits and let us fit your needs to a "TEE"! Mini-Circuits is your complete source for bias-tees, covering from 100 kHz to 12 GHz, handling up to 40W RF power and 4A DC current in a variety of coaxial and surface mount packages. All of our Bias-Tees provide low insertion loss and VSWR. Our patented TCBT series models are the smallest in the industry and are suitable for projects where low price, small size, and temperature stability are a must. Our ultra-wideband ZX85 bias-tees use our patented unibody construction affording small size and high repeatability.



RoHS compliant.

LTCC TECHNOLOGY

\$395 *IN STOCK*
from ea. Qty. 1000

TYPICAL SPECIFICATIONS

Model	Freq (MHz)	Insertion Loss (dB)	Isolation (dB)	Max Current mA	Price \$ea. Qty. 10
TCBT-2R5G+**	20-2500	0.35	44	200	6.95
TCBT-6G+**	50-6000	0.7	28	200	7.95*
TCBT-14+***	10-10000	0.35	33	200	8.45
TCBT-14R+***	10-10000	0.6	33	200	8.45

TCBT: LTCC, Actual Size .15" x .15"

U.S. Patent 7,012,486**

U.S. Patent 8,644,029***

					Qty. 1-9
JEBC-4R2G+	10-4200	0.6	40	500	39.95
JEBC-4R2GW+	0.1-4200	0.6	40	500	59.95
PBTC-1G+	10-1000	0.3	33	500	28.20
PBTC-3G+	10-3000	0.3	30	500	38.20
PBTC-1GW+	0.1-1000	0.3	33	500	38.20
PBTC-3GW+	0.1-3000	0.3	30	500	49.20
ZFBT-4R2G+	10-4200	0.6	40	500	59.95
ZFBT-6G+	10-6000	0.6	40	500	79.95
ZFBT-4R2GW+	0.1-4200	0.6	40	500	79.95
ZFBT-6GW+	0.1-6000	0.6	40	500	89.95
ZFBT-4R2G-FT+	10-4200	0.6	N/A	500	79.95
ZFBT-6G-FT+	10-6000	0.6	N/A	500	79.95
ZFBT-4R2GW-FT+	0.1-4200	0.6	N/A	500	79.95
ZFBT-6GW-FT+	0.1-6000	0.6	N/A	500	89.95
ZFBT-282-1.5A+	10-2800	0.6	45	1500	59.95
ZFBT-352-FT+	30-3500	0.4	23	4000	49.95
ZNBT-60-1W+	2.5-6000	0.6	45	500	82.95
ZX85-12G+	0.2-12000	0.6	N/A	400	99.95
ZX85-40W-63+	700-6000	0.5	33	1000	179.95

NEW!

ZX85: U.S. Patent 6,790,049.

Note: Isolation dB applies to DC to (RF) and DC to (RF+DC) ports.

*Price is for quantity of 20





Proven Performance



GORE-FLIGHT™ Microwave Assemblies, 6 Series are ruggedized, lightweight and vapor-sealed airframe assemblies that withstand the challenges of aerospace.

With GORE-FLIGHT™ Microwave Assemblies, 6 Series, a fit-and-forget philosophy is now a reality – providing the most cost-effective solution that ensures mission-critical system performance for military and civil aircraft operators.

Find out why at:
www.gore.com/GORE-FLIGHT



precision

lightweight

durability

GORE, GORE-FLIGHT, the purple cable and designs are trademarks of W. L. Gore & Associates.

Follow us on



defense electronics

Radar Embraces
Remote Control p158

German Security Relies
on R&S Scanner p160

Deciding on DSPs and
FPGAs for EW p168

A Special Section to PENTON'S DESIGN ENGINEERING & SOURCING GROUP OCTOBER 2016

JACK BROWNE | Technical Contributor

RADAR TECHNOLOGY CONTINUES TO ADVANCE

Military radar systems are moving away from vacuum tubes, embracing GaN semiconductors and solid-state amplification for improved power efficiency and long-term reliability.

RADAR TECHNOLOGY has been the backbone of the electronic military for many decades. Even as the technology continues to extend as the basis for numerous collision-avoidance systems in commercial automobile markets, it also expands into a growing number of military applications—specifically, as part of surveillance and tracking systems on the ground, at sea, in the air, and in outer space.

In the case of some airborne systems, such as in unmanned aerial vehicles (UAVs), an operator may be quite a distance from the radar system. In all cases, the feedback that these radar systems provide is invaluable.

(continued on p. 64)

1. The long evolution of synthetic-aperture-radar (SAR) technology has enabled the development of dependable, solid-state ground-based surveillance and early-warning systems.

(Photo courtesy of Lockheed Martin)



NAVY PICKS Lockheed Martin for Frigate Combat Management

THE U.S. Navy selected Lockheed Martin (www.lockheedmartin.com) and its COMBATSS-21 as the combat-management system for Navy frigates, awarding a contract worth as much as \$79.5 million for fiscal years 2016 through 2021. COMBATSS-21—the open-architecture combat-management system deployed on cruisers, destroyers, and littoral combat ships—will now also be deployed on Navy frigates.

COMBATSS-21, an abbreviation for COMPONENT-BASED Total-Ship System-21(st century), is built from Aegis Common Source Library (CSL) code. It has a framework similar to Aegis Baseline 9 software developed for the Aegis cruiser and destroyer ships, Littoral Combat Ships (LCS), and U.S. Coast Guard national security cutters.

Rich Calabrese, director of mission systems at Lockheed Martin, says that using the CSL code is both efficient and cost-effective: “Using the CSL enhances life-cycle affordability by reducing costs for integration, test, and certification—and delivers an open combat system architecture in line with the Navy’s objective architecture, driving affordability and increasing interoperability across the entire fleet.” This shared use of the CSL code makes it possible for combat ships to quickly integrate new capabilities, incorporating new sensors and weapons in response to new threats. ■

(continued on p. 60)



Radar Embraces Remote Control

RADAR HAS long been the “backbone” technology of military electronics. It is the means by which an adversary’s troops and their movements can be detected from a dis-

tance, and has served as a reliable early-warning system for decades.


Radar technology is ever-evolving and improving along with enhancements to RF/microwave components and developments in signal-processing components,

such as digital signal processors (DSPs) and field-programmable gate arrays (FPGAs). It is also teaming with another technology, unmanned aerial vehicles (UAVs), to provide remote vision for military surveillance.

Of course, creating a remote-controlled UAV with a radar system, or even an on-board camera system, is no trivial task. Radar systems have traditionally relied on high-power pulsed signals to illuminate targets, which makes generating signals of sufficient amplitude with batteries on a UAV a challenge. The weight of the radar system is also a concern, since it must juggle the tradeoff between weight and transmit power to make it a viable subsystem onboard a UAV, or even an unmanned ground vehicle (UGV).

Then there is the matter of transferring intelligence on the radar returns from the drone to a remote operator. Wireless radio links must be secure, and they must also contain sufficient bandwidth for communications and control signals—as well as video signals, if the UAV is equipped with a monitoring camera.

Military interest in radar-equipped UAVs is so strong that research efforts analyzing the design challenges of creating UAVs with remote-controlled radar systems are spreading. For example, work at the University of Denver’s Unmanned Systems Research Institute has included the development of a fully working prototype, with antenna, amplifier, processor, transmitter/receiver, and wireless data link. The prototype weighs 230 g and consumes only 4.5 W power.

This prototype system was initially developed to serve the Federal Aviation Administration (FAA) and air-traffic-control applications. Consumer and commercial interest in UAVs is so great that there is concern among FAA officials about excessive airborne congestion and in-flight accidents. Adding radar technology to commercial UAVs can prevent them from crashing into each other or, more importantly, into manned aircraft. 



VITA 67

Multicoaxial RF backplane connection

HUBER+SUHNER VITA 67 is the first true high performance 65 GHz SMPM cable assembly in the market. Thanks to the solderless Minibend bend-to-the-end technology tightest bending radii (0.06”/1.5 mm) are applicable right behind the connector.

The snap-in captivation method guarantees an easy and quick installation without any tools and loose parts. VITA 67 is designed for side-by-side implementation with VITA 46 and VITA 66 hardware.

» aerospacedefense.hubersuhner.com

HUBER+SUHNER AG 9100 Herisau/Switzerland
HUBER+SUHNER INC. Charlotte NC 28273/USA



CERAMIC FILTERS

LOW PASS BANDPASS HIGH PASS DIPLEXERS

99¢

Covering DC to 18.3 GHz from ea. qty. 3000

Over 195 models as small as 0.06 x 0.03"! These tiny, hermetically sealed filters utilize our advanced Low Temperature Co-fired Ceramic (LTCC) technology to offer superior thermal stability, high reliability, and very low cost. Supporting a wide range of applications with high stop band rejection and low pass band insertion loss in tiny packages, they're a perfect fit for your system requirements. Visit minicircuits.com for comprehensive data sheets, PCB layouts, free high-accuracy simulation models, and everything you need to choose the model for your needs. Order direct from our web store, and have them in your hands as soon as tomorrow!

Now available in small-quantity reels at no extra charge:

Standard counts of 20, 50, 100, 200, 500, 1000 or 3000.
Save time, money, and inventory space!

Wild Card Filter Kits, KWC-LHP, only \$98



- Choose any 8 LFCN or HFCN models
- Receive 5 of each model
- A total of 40 filters for a great value
- Order your KWC-LHP Filter Kit TODAY!

 **RoHS compliant** U.S. Patents 7,760,485 and 6,943,646

Free, High-Accuracy Simulation Models for ADS



www.modelithics.com/mvp/Mini-Circuits.asp



German Security Relies on R&S Scanner

SECURITY SCANNERS from Rohde & Schwarz (www.rohde-schwarz.com) will soon be essential tools for the German Federal Police Force, thanks to a major contract awarded to the firm by the German Federal Ministry of the Interior. The primary application for the 300 new R&S QPS200 security scanners will be for security at German airports. Terms of the contract will be fulfilled over a three-year period.

The scanners use millimeter-wave technology to automatically detect potentially dangerous objects hid-

den on a body or under clothing, whether they are rigid, flexible, fluid, metallic, or non-metallic. They operate at frequencies between 70 and 80 GHz and at extremely low, safe radiated power levels. The scan of a passenger or person is comfortable, requiring only milliseconds to complete. Privacy is maintained by means of a neutral graphical display. The scanners have been certified by the European Civil Aviation Conference (ECAC) and thoroughly tested for suitability by the German Federal Police. ■



Scanners operating between 70 and 80 GHz will be used for security purposes at German airports.

Sidewinder Missile Tests Hit the Mark

RAYTHEON CO. (www.raytheon.com) recently teamed with the U.S. Air Force and Navy on test firing three AIM-9X Block I ("Sidewinder") missiles from an F-35A aircraft, the first short-range, air-to-air missile to be used on

the F-35 Joint Strike Fighter. These tests demonstrated the effectiveness of numerous functions required for successful missile deployment, including loading, target acquisition by the aircraft, missile target acquisition and tracking, launch initiation, in-flight guidance, and impact/proximity fusing at the interception of the target.

"These tests validated the on-board communications and handoffs between the aircraft and the missile required to prosecute an aerial target," says Mark Justus, AIM-9X program director for Raytheon Missile Systems. "AIM-9X will help ensure our pilots and allies have the most reliable and effective weapons on the F-35." A fourth guided missile test of the AIM-9X Block I missiles is expected later this year.

An F-35 can carry two AIM-9X missiles on its wings, and four AIM-120 missiles internally, when properly configured. These test firings were intended to ensure integration of the advanced missile systems with their introduction across the F-35 fleet expected in 2017. ■



This file photo shows U.S. Navy aviation crewmen handling a Sidewinder missile, recently exercised through a series of tests. (Photo courtesy of the U.S. Navy)



\$139⁹⁵
from (qty. 1-9)
 Rugged connectorized package
 0.75 x 0.74 x 0.46"

\$11⁹⁵
from (qty. 20)
 3x3mm MMIC

0.5 to 8 GHz

LOW NOISE AMPLIFIERS

IN/OUT Termination Matched!

Low noise, high dynamic range, high output power, and flat gain from 0.5 to 8 GHz, all in a single amplifier! Mini-Circuits' popular ultra-wideband LNAs are now available in both a 3x3mm QFN for your PCB and a rugged connectorized package to facilitate your cable assemblies. Both models are matched over the 0.5 to 8 GHz range*, making them a snap to use for sensitive, high-dynamic-range receivers, instrumentation, defense systems, LTE, WiFi, S-Band and C-Band radar, SatCom and more! They're available off the shelf for a great value, so visit minicircuits.com and place your order today for delivery as soon as tomorrow!

*See datasheet for suggested application circuit for PMA3-83LN+

†Flatness specified over 0.5 to 7 GHz

FEATURES:

- **Low Noise Figure, 1.3 dB**
- **High Gain, 21 dB**
- **Excellent Gain Flatness, ± 0.7 dB[†]**
- **High IP3, +35 dBm**
- **High POUT, +23.2 dBm**



DESIGN WITH CONFIDENCE

Advanced Technology, Proven Heritage



AVIONICS | MIL-COTS | SPACE
POWER CONVERSION SOLUTIONS

- ✓ MIL-PRF-38534
Class H & Class K Qualified
- ✓ Efficient and Reliable
- ✓ Products Ship from Stock

VPT

Power Your Critical Mission Today

www.vptpower.com

NEWS SHORTS

Strong Growth Expected for Military Aerostat Markets

MILITARY AEROSTAT systems, including unmanned aerial vehicles (UAVs) and unmanned ground vehicles (UGVs), will be heavily enlisted both on the battlefield and as a means of preventing conflicts during the next decade. According to the 165-page study "Military Aerostats Market Report: 2016-2026," compiled by market researcher Visiongain (www.visiongainglobal.com), the continued growth of national threats worldwide will fuel the need for military aerostat systems. These include different types of radar, surveillance, and imaging systems for homeland secu-

rity, law enforcement, border patrols, and tactical applications.

The report notes an anticipated compound annual growth rate (CAGR) of 4.8% for the five-year period from 2016 through 2021. In addition, the market size of \$4.17 billion in 2016 is expected to grow to almost \$5.3 billion by the end of 2021. The detailed report, which references such companies as BAE Systems, the Boeing Co., Elbit Systems, Lockheed Martin Corp., Northrop Grumman Corp., and Raytheon Co., offers insights on how to compete in this lucrative and dynamic market. ■

ROCKWELL COLLINS Demonstrates Wideband HF from Airborne C-17


FOR THE first time, Rockwell Collins (www.rockwellcollins.com) completed a complex data transfer from an airborne C-17 aircraft to a ground station using a wideband high-frequency (WBHF) communications channel. The air-to-ground data link was accomplished in collaboration with the U.S. Air Force. It took place over the duration of a two-day flight, between Dover Air Force Base (AFB) Delaware and Joint Base Lewis-McChord, Washington, using a WBHF receiver-exciter configured for airborne operation.

The demonstration included transfers of streaming video, real-time chat, file transfers, and digital voice audio over distances of 1,500 miles and more. Compared to traditional HF communications, WBHF provides much higher data throughput. It is an effective complement to satellite-communications (satcom) links where satellite signals are limited

or unavailable. WBHF systems can perform transfers of large data files at speeds comparable to narrowband satcom systems. ■



An airborne C-17 aircraft was part of a test of examining the capabilities of performing air-to-ground communications using wideband high-frequency (WBHF) communications equipment. (Photo courtesy of the Boeing Co.)



GVA AMPLIFIERS

NOW DC* to 12 GHz up to 1W Output Power from **94¢** ea. (qty. 1000)

GVA amplifiers now offer more options and more capabilities to support your needs. The new **GVA-123+** provides ultra-wideband performance with flat gain from 0.01 to 12 GHz, and new model **GVA-91+** delivers output power up to 1W with power added efficiency up to 47%! These new MMIC amplifiers are perfect solutions for many applications from cellular to satellite and more! The GVA series now covers bands from DC to 12 GHz with

various combinations of gain, P1dB, IP3, and noise figure to fit your application. Based on high-performance InGaP HBT technology, these amplifiers are unconditionally stable and designed for a single 5V supply in tiny SOT-89 packages. All models are in stock for immediate delivery! Visit minicircuits.com for detailed specs, performance data, export info, **free X-parameters**, and everything you need to choose your GVA today!

US patent 6,943,629

*Low frequency cut-off determined by coupling cap.
For GVA-60+, GVA-62+, GVA-63+, and GVA-123+ low cut off at 10 MHz.
For GVA-91+, low cut off at 869 MHz.

NOTE: GVA-62+ may be used as a replacement for RFMD SBB-4089Z
GVA-63+ may be used as a replacement for RFMD SBB-5089Z
See model datasheets for details

**FREE X-Parameters-Based
Non-Linear Simulation Models for ADS**



<http://www.modelithics.com/mvp/Mini-Circuits.asp>



Over the course of six decades, radar supplier Lockheed Martin (www.lockheedmartin.com) has evolved its use of synthetic-aperture-radar (SAR) technology at lower frequencies, most recently expanding into highly efficient solid-state SAR systems. The firm's solid-state ground-based surveillance and early-warning systems (*Fig. 1*) are capable of providing intelligence at any time.

These systems are neither limited by weather nor the atmospheric attenuation of conventional radars and electro-optical imaging systems. In addition to being used for moving target indication (MTI), the VHF/UHF SAR sensors have been used for ocean spill monitoring, polar ice assessment, intelligence acquisition, and battlefield reconnaissance.

Military radar systems have traditionally been large electronic systems using vacuum-tube amplification to achieve megawatts of transmitted pulse-modulated output power at RF and microwave frequencies. The radar signal frequencies have always been dictated by the performance goals of a particular radar system. Lower frequencies and their longer wavelengths provide better surveillance of targets of interest at longer distances than higher-frequency signals and their shorter wavelengths, which offer more precise tracking at shorter distances.

A number of different signal-generation and -amplification electron-tube devices have been used in military radar systems, with magnetrons capable of producing output signals at megawatts of power and klystrons serving as effective amplifiers through kilowatts of output power. Traveling-wave tubes (TWTs) and TWT amplifiers (TWTAs) have also been utilized to amplify radar signals, as have crossed-field amplifiers (CFAs).

However, as has been true for frequencies from the audio range through microwave bands, designers have sought solid-state replacements for vacuum tubes. The basic tradeoff between the two technologies is that vacuum tubes provide



2. The Patriot radar system was recently upgraded to GaN-based T/R modules and AESA technology for full 360-deg. scanning capability.

(Photo courtesy of Raytheon Co.)

3. The AN/TPS-80 Ground/Air Task-Oriented Radar (GATOR) is now being assembled with solid-state GaN modules. (Photo courtesy of Northrop Grumman)



enormous output-power levels compared to solid-state devices, but with much higher bias requirements and much shorter operating lifetimes. Thus, the key to using solid-state devices in applications such as radar systems that require high output signal levels is to combine the individual outputs of multiple transistors in parallel to achieve higher output-power levels.

Gallium nitride (GaN) is a high-power semiconductor technology that has proven its worth in lower-microwave-frequency commercial applications such as Fourth-Generation (4G) wireless communications systems, and is gaining ground as an amplification solution for military radar systems. Earlier this year, one of the leaders in military radar technology, Raytheon Co. (www.raytheon.com), upgraded the main array of the Patriot Air and Missile Defense System with 360 deg. of coverage, along with GaN-based active electronically scanned array (AESA) technology.


"A GaN-based AESA radar benefits netted sensors, and gives Patriot greater capability and reliability while significantly reducing operations and sustainment cost," explains Ralph Acaba, vice president of Integrated Air and Missile Defense at Raytheon's Integrated Defense Systems business. "Raytheon recognizes how important this capability is for the warfighter, and is investing in its own resources to bring Patriot's GaN-based AESA radar to the point where it can enter engineering and manufacturing development with low risk."

The main AESA array measures about 13×9 ft. and is a bolt-on forward-facing replacement antenna. Earlier in the year, Raytheon built a GaN-based rear-panel array for the Patriot system (*Fig. 2*) as part of the efforts to enable a full 360-deg. view for the system. Raytheon also uses solid-state GaN technology for a U.S. Navy radar and jammer, and is exploring the use of the technology for the compact version of the Pentagon's pain ray. Known as the Active Denial System, the pain ray uses a beam of RF/microwave energy to repel a living target by heating the skin.

Recently, Northrop Grumman Corp. (www.northropgrumman.com) received an award from the U.S. Marine Corps for nine AN/TPS-80 Ground/Air Task-Oriented Radar (GATOR)

RF SWITCH MATRICES

DC to 18GHz



USB & Ethernet Control Options models from **\$385** ea.

- 0.25 dB Insertion Loss
- 85 dB Isolation
- 1.2 VSWR
- up to 10W Power Handling
- Extra-Long Switch Life
Up to 100 Million Cycles*
- Switch Cycle Counting Feature
with Automatic Calibration Alerts
- User-Friendly GUI and DLLs Included
- Compatible with Most Third Party Lab Software†
- Small size fits in your Laptop Case!
- Available from Stock

Visit minicircuits.com for detailed model specs, application notes, and more!
Place your order today for delivery as soon as tomorrow!

* Switches protected by US patents 5,272,458; 6,650,210; 6,414,577; 7,843,289; and additional patents pending.
† See data sheet for a full list of compatible software.



low-rate initial production (LRIP) systems (Fig. 3). The systems support air surveillance, weapon cueing, counter-fire target acquisition, and air-traffic control.

Northrop Grumman was previously contracted to supply six of the G/ATOR LRIP systems to the Marines, the first

of which is scheduled for delivery by February 2017. By designing these latest nine systems around solid-state GaN technology for microwave amplification, the defense contractor has provided the Marine Corps with nearly \$2 million in lifecycle cost savings per system.

"There are no other GaN ground-based AESA radars in production today," says Roshan Roeder, director of mission solutions for Northrop Grumman. "G/ATOR is the first DoD ground-based AESA system to incorporate GaN in a production program. We proposed this technology as a cost-savings measure for the government and funded risk reduction internally to ensure a seamless insertion into the G/ATOR system. We are continuing to look at future technology insertions to continue providing the best capability out there to our warfighters at an affordable cost."

GaN is a wide-bandgap semiconductor technology, with low parasitic capacitance and high breakdown voltage. It has wider bandgap than silicon-bipolar, silicon-carbide (SiC), and gallium-arsenide (GaAs) transistor technologies, and amplifier designers have succeeded in using GaN devices in high-efficiency Class E and Class F amplifier designs, with efficiency levels theoretically approaching 100%.

GaN material has excellent thermal-conductivity properties for low self-heating effects at high power levels. It also exhibits higher breakdown voltage, but lower carrier mobility, than GaAs, which will limit the upper frequency limits of GaN devices compared to GaAs transistors.

GaN-based power amplifiers for radar and other applications are available from a growing number of suppliers, including GaN-on-silicon-carbide (GaN-on-SiC) substrates for high-power amplifiers. For example, component supplier Aethercomm (www.aethercomm.com) recently delivered an L-band amplifier with Class-F efficiency to a major defense contractor. The amplifier was based on off-the-shelf, packaged, GaN high-electron-mobility-transistor (HEMT) devices. The amplifier was capable of more than 50 W output power with efficiency of 60% or more.

The same company's model SSPA 0.1-1.0-300 is a wideband amplifier that offers evidence of the capabilities of

Cover your bases with KRYTAR



KRYTAR, Inc., founded in 1975, specializes in the design and manufacturing of ultra-broadband microwave components and test equipment for both commercial and military applications.

Products cover the DC to 67 GHz frequency range and are designed for a wide range of applications including:

- ☐ Test Equipment
- ☐ Simulation Systems
- ☐ SATCOM & SOTM
- ☐ Jammers for Radar & IEDs
- ☐ Radar Systems
- ☐ EW: ECM, ECCM & ESM

KRYTAR has a commitment to technical excellence and customer satisfaction.

These principles form the basis for the steady growth that has earned KRYTAR an enviable reputation in the microwave community.

Cover your bases. Contact KRYTAR today for more information.

MIL-Qualified RF, Microwave & mmW Components

- ☐ Directional Couplers to 67 GHz
- ☐ 3 dB 90° Hybrid Couplers to 40 GHz
- ☐ **NEW! 3 dB 180° Hybrid Couplers to 45 GHz**
- ☐ Beamforming Networks to 18 GHz
- ☐ Power Dividers to 45 GHz
- ☐ Detectors to 40 GHz
- ☐ Custom Applications



KRYTAR

www.krytar.com

1288 Anvilwood Avenue • Sunnyvale, CA 94089

Toll FREE: +1.877.734.5999 • FAX: +1.408.734.3017 • E-mail: sales@krytar.com



GaN technology. Designed for military and commercial applications, the GaN amplifier measures $5.25 \times 10.15 \times 1.97$ in., weighs 8.5 lb., and is capable of 250 to 300 W average power from 10 to 1,000 MHz. It provides high efficiency and operates from a MIL-STD-461 aircraft power supply or an input voltage from +18 to +36 V dc.

In terms of radar market size, a number of market research forecasts agree that steady growth is expected for military radar markets around the world. British researcher Business Reports Updates (www.vgdefence.com) offers "Military Radar Systems Market Outlook 2016-2026," a 329-page report that looks at 211 specific contracts by countries and breaks down markets into land-based, airborne, and maritime radar systems. It also provides profiles of the leading 13 military radar companies based on 2016 sales. The company also compiled the "Military Simulation, Modeling, and Virtual Training Market Report: 2016-2026," a report on markets for military simulation.

According to a report from Market Research Media (www.marketresearch-media.com), "U.S. Military Unmanned Aerial Vehicles (UAV) Market Forecast 2013-2018," the use of radar technology is expected to increase dramatically in UAVs for the next several years. UAVs equipped with low-power radar systems are viewed as attractive tools for performing remote surveillance.

The report projects the market for UAV radar systems to grow to \$86.5 billion by 2018, rising at a compound annual growth rate (CAGR) of 12%. The use of solid-state GaN-based amplification can form the basis for lower-voltage radar systems that are practical, portable, and light in weight for realistic use in military and even government-sponsored UAVs, such as for weather radar UAVs.

In commercial markets, radar technology is being adopted widely in automotive safety systems for forward- and rear-looking, radar-based collision-avoidance

systems. These are much higher-frequency radar emitters than in most military radar systems, operating at millimeter-wave frequencies up to 77 GHz and at frequencies well beyond the limits of GaN semiconductor technology—they typically use lower-power GaAs and

silicon-germanium (SiGe) devices.

Whether for military, industrial, or commercial automotive applications, the spread of radar technology is almost relentless. Device technologies will continue to be developed or adapted to meet the different requirements. **ce**

Enabling wideband frequency agility

GaN and GaAs Solid-State Power Amplifiers for Multi-Function, Radar, and EW System Design






Whether your application is narrowband, wideband or ultra-wideband, operating in pulsed or CW mode, CTT's power amplifiers are an especially attractive choice for new multi-function frequency-agile systems that effectively conserve weight, space and power consumption.

The characteristics of the portion of the electromagnetic spectrum selected for any of these particular system designs are undoubtedly the most important to the end user, as it has the greatest impact on the type of information required and received.

Engineered specifically to meet the stringent requirements imposed by many modern system designs, CTT's family of GaN and GaAs-based solid-state power amplifiers excel in a wide range of applications.

CTT has delivered production quantities of amplifiers with power levels from 10 through 400 Watts – and higher – for a variety of multi-function, radar and EW applications.

- AMDR • Shipboard Radar • AESA Radar
- VLO/FLO Threats • New Land Radar • EW • UAVs

More than thirty years ago CTT, Inc. made a strong commitment to serve the defense electronics market with a simple goal: quality, performance, reliability, service and on-time delivery of our products.

Give us a call to find out how our commitment can support your success.

It's that simple.



Microwave Technology Leadership

- ❖ **Power Amplifiers**
- NEW GaN and GaAs Models**
- Radar Bands up to 1kW
- EW Bands up to 400W
- Pulse and CW
- Solid-State Microwave Power Modules
- Rack-Mount Configurations
- ❖ **Low-Noise Amplifiers**
- ❖ **Up and Downconverters**
- ❖ **Subsystems**
- ❖ **Custom Engineered Options**



USA-based thin-film microwave production facility



NSAI
ISO 9001:2008



241 East Java Drive • Sunnyvale • California 94089

Phone: 408-541-0596 • Fax: 408-541-0794 • www.cttinc.com • E-mail: sales@cttinc.com

Deciding on DSPs and FPGAs for EW

Digital components like DSPs and FPGAs can provide the signal processing needed in modern radar and electronic-warfare systems, all the while helping to save size, weight, and power.

SIGNAL PROCESSING is often the difference between missing and identifying a radar target, delivering an effective electronic-warfare (EW) response, or maintaining secure communications. A number of digital components perform signal processing in military electronic systems, with digital signal processors (DSPs) and field-programmable gate arrays (FPGAs) often used separately or together. Finding the right component match for an application can be a challenge, although understanding key performance parameters and how they relate to different military electronic applications can help ease the process.


DSPs are essentially types of microprocessors aimed at performing math-intensive operations. The processing power of a DSP can be determined by its clock rate and the number of operations it can perform per clock cycle, such as how many additions or multiplications per second. Its processing capabilities are typically characterized in terms of millions of instructions per second (MIPS).

A DSP must be preconditioned or programmed to perform a particular function, usually by “C” programming code or

some other assembly language. DSPs are designed to work with external memory on a printed-circuit board (PCB) or within a system, and can work with large amounts of available data for handling large processing operations. As a tradeoff, accounting is necessary for transferring data between a DSP and the memory locations, plus any required transfer times.

An FPGA, on the other hand, is a collection of transistor gates that are able to change functions in the field. The array of gates can be connected together to achieve different functions, such as addition or multiplication, without the prior programming required for a DSP. In some ways, an FPGA can be thought of as multiple DSPs or processors, each with its own dedicated memory, so that multiple functions can be performed.


In addition to performing very-high-level operations—like finite-impulse-response (FIR) filters, infinite-impulse-response filters (IIR), or fast-Fourier-transform (FFT) functions—FPGAs can perform DSP functions (e.g., the aforementioned addition and multiplication) at very high clock rates. Again, with an FPGA, comparing performance is a



1. A line of FPGAs includes different radiation-hardened models that offer long, reliable operating lifetimes in outer space. (Photo courtesy of Atmel)

MMIC AMPLIFIERS

50 MHz to 26.5 GHz



PHA-1+ \$**1**⁹⁹
0.05-6 GHz ea. (qty. 20)
Gain 13.5 dB
P_{out} 22 dBm

AVA-183A+ \$**7**⁹⁵
5-18 GHz ea. (qty. 20)
Gain 14.0 dB
P_{out} 19 dBm

AVM-273HPK+ \$**36**⁹⁰
13-26.5 GHz ea. (qty. 10)
Gain 13.0 dB
P_{out} 27 dBm



We've got you covered!

3 MMIC amplifiers support the whole gamut of applications from 50 MHz all the way up to 26.5 GHz!

Mini-Circuits' AVM-273HPK+ wideband microwave MMIC amplifier supports applications from 13 to 26.5 GHz with up to 0.5W output power, 13 dB gain, ± 1 dB gain flatness and 58 dB reverse isolation. The amplifier comes supplied with a voltage sequencing and DC control module providing reverse voltage protection in one tiny package to simplify your circuit design. This model is an ideal buffer amplifier for P2P radios, military EW and radar, DBS, VSAT and more!

The AVA-183A+ delivers 14 dB gain with excellent gain flatness (± 1.0 dB) from 5 to 18 GHz, 38 dB isolation, and 19 dBm power handling. It is unconditionally stable and an ideal LO driver amplifier. Internal DC blocks, bias tee, and microwave coupling capacitor simplify external circuits, minimizing your design time.

The PHA-1+ uses E-PHEMT technology to offer ultra-high dynamic range, low noise, and excellent IP3 performance, making it ideal for LTE, and TD-SCDMA. Good input and output return loss across almost 7 octaves extend its use to CATV, wireless LANs, and base station infrastructure.

Visit minicircuits.com for full specs, performance curves, and free data! These models are in stock and ready to ship today!

FREE X-Parameters-Based
Non-Linear Simulation Models for ADS



<http://www.modelithics.com/mvp/Mini-Circuits.asp>



2. Stratix 10 FPGAs can operate at clock rates to 1 GHz, and with power efficiency to 80 GFLOPS/W.

(Photo courtesy of Altera)

matter of determining how many useful functions can be performed per clock cycle, or how many total operations can be performed per second.

In contrast to DSPs, FPGAs are


designed and fabricated with internal memory. This enables functioning without any memory-transfer delays, with fast data input/output (I/O) rates. As a tradeoff, the amount of memory and



the size of the data sets processed are limited compared to a DSP. Of course, when an FPGA must handle large, complex data sets, it can be designed into a PCB or module with dedicated external memory to increase its processing capabilities with minimum data I/O delays.

One way to think of the difference between an FPGA and DSP for a military system is to imagine how a block diagram of part of the system (a receiver, for instance) might be handled by each component. In an FPGA, equivalent receiver components (e.g., frequency mixers, filters, and amplifiers) are defined as specific functions within the FPGA. Once those functions are defined, the FPGA provides fairly efficient operation. However, the functions cannot be easily changed, since the gates within the device have been set for the desired signal processing.

In a DSP, though, the block diagram is defined by programming code in terms of its functionality. If necessary, a DSP programmed as a receiver could be reprogrammed as a transmitter, with the signal branching and complex decision making determined as responses to the programming code.

In many military electronic systems (portable systems, in particular), power efficiency is important in maintaining military design goals for size, weight, and power (SWaP). The power efficiency of signal processing as performed by multicore processors, DSPs, or FPGAs is usually compared in terms of millions of floating-point operations per watt (MFLOPS/W) and billions of floating-point operations per watt (GFLOPS/W). FPGAs typically excel in this area compared to DSPs. 



MicroScan® Miniature, Ruggedized SDR Transceiver For Cyber-EW, COMMS, Surveillance, SIGINT, and DF



- **SWaP:** Size: 2.2 x 1.4 x 0.9 inches; Weight: 0.2 lbs.; Powered by USB 3.0/2.0
- **Frequency Range:** 70-6000 MHz, 56 MHz IBW, dual-channel coherent RX
- **TX Power:** +20 dBm, with in-built capability to key external PA's for higher power
- **In-Built RF Filters:** Essential for high RF performance including 9 tracking suboctave bandpass filters for RX, and 9 fixed suboctave lowpass filters for TX
- **Integration:** Inside antennas, manpacks, UAV's, networked sensor nets, etc.
- **Locking:** Optional GPS time and frequency locking with 9 axis gyro/compass sensor
- **Development Kit:** Available with FPGA DSP blocks, examples in source code, and Technical Support so Primes can get missions going quickly
- **Software Support:** GNURadio, Redhawk, Windows, Linux, Android

MicroScan® Mission Applications




Soldier Worn & Handheld For Dismount SIGINT



Inside DF Arrays For Mounted DF



Disposable Jammers For Remote EW



Multi-point Transceivers For Dismount COMMS



Inside Small UAV Pods For Aerial Cyber-EW



Networked Sensors For Remote SIGINT

Spectranetix, Inc.
sales3@spectranetix.com +1-408-982-9057 www.spectranetix.com/products

ULTRA-REL™ CERAMIC MMIC AMPLIFIERS

10 MHz to 7 GHz



Low NF from 0.5 dB High IP3 up to +42 dBm Low DC current 65 mA **\$7⁴⁵**
from ea. (qty 20)

When failure is not an option! Our CMA family of ceramic MMIC amplifiers is expanding to meet your needs for more critical applications. Designed into a nitrogen-filled, hermetic LTCC package just 0.045" high, these rugged models have been qualified and are capable of meeting MIL standards for a whole battery of harsh environmental conditions:

Qualified for: (see website for complete list and details)

Gross and Fine Leak	HTOL (1700 hours @ +105°C)
Mechanical Shock	Steam Aging
Vibration	Solder Heat Resistance
Acceleration	Autoclave
PIND	And More!

*Gross leak only

Robust performance across wide bandwidths makes them ideal for military and defense applications, hi-rel instrumentation, and anywhere long-term reliability adds bottom-line value. Go to minicircuits.com for all the details today, and have them in your hands as soon as tomorrow!

Electrical Specifications (-55 to +105°C)



Model	Freq. (GHz)	Gain (dB)	P _{out} (dBm)	IP3 (dBm)	NF (dB)	DC (V)	Price \$ ea. (qty 20)
CMA-81+	DC-6	10	19.5	38	7.5	5	8.95
CMA-82+	DC-7	15	20	42	6.8	5	8.95
CMA-84+	DC-7	24	21	38	5.5	5	8.95
CMA-62+	0.01-6	15	19	33	5	5	7.45
CMA-63+	0.01-6	20	18	32	4	5	7.45
CMA-545+	0.05-6	15	20	37	1	3	7.45
CMA-5043+	0.05-4	18	20	33	0.8	5	7.45
CMA-545G1+	0.4-2.2	32	23	36	0.9	5	7.95
CMA-162LN+	0.7-1.6	23	19	30	0.5	4	7.45
CMA-252LN+	1.5-2.5	17	18	30	1	4	7.45

RoHS compliant



Integrated Microwave Assemblies for Military Radar Applications

Performance Advantages:

- L, S, C, X, Ku, Ka Bands
- High spurious rejection
- Adjustable Filter Bandwidth
- Gain Control
- RF Gating Capacity

Features:

- Designed to minimize spurious emissions while maintaining the transmitted waveform integrity
- Hermetic package
- Wide Operating temperature range



**Upconverters
And Digital
Attenuators**



**Contact us about
integrating
your designs today.**



Receivers



Performance Advantages:

- L, S, C, X, Ku, Ka Bands
- Low Noise Figures
- Digital Gain Control
- Linearized RF Attenuation
- Very high Dynamic Range
- Fast Recovery Time
- Switched IF Filter

Features:

- Dual-conversion radar receivers
- High dynamic range to operate in a multiple system environment
- Hermetic package
- Wide Operating temperature range

REAL-WORLD SOLUTIONS

AS EXAMPLES OF the processing capabilities available from high-speed DSPs, models C6654 and CC6652 are (respectively) fixed- and floating-point DSPs recently introduced by Texas Instruments (www.ti.com). Based on the firm's KeyStone multi-processor core architecture, and incorporating the new C66x DSP core, these DSP devices run at clock speeds to 850 MHz (C6654) and 600 MHz (C6652). With an extended operating temperature range of -40 to +100°C, the devices are suitable for avionics and other defense applications as well as for ruggedized commercial applications.

Each DSP features two on-chip phase-locked loops (PLLs), two channels of 8- or 16-b processing, 8 GB of addressable memory space, and I2C and SPI interfaces. The model TMS320C6652 DSP provides a cycle time of 1.167 ns at 600 MHz, delivering 19.2 GMACS and 9.6 GFLOPS at 600 MHz. The model TMS320C6654 has a cycle time of 1.175 ns at 850 MHz, providing 27.2 GMACS and 13.6 GFLOPS at 800 MHz.

Additional suppliers of DSPs include Analog Devices (www.analog.com), Infineon Technologies (www.infineon.com), Intersil (www.intersil.com), Microchip Technology (www.microchip.com), NXP Semiconductors (www.nxp.com), ON Semiconductor (www.onsemi.com), STMicroelectronics (www.st.com), and Zilog (www.zilog.com).

As an example of a military-grade FPGA, the Virtex-7 X980T FPGA from Xilinx (www.xilinx.com), has been used in a 24-channel portable radar beamformer and demonstrated as much as 987 GFLOPS capability with lower power consumption. Fabricated on a 28-nm silicon semiconductor process, the FPGA achieves as much as 2.8- Tb/s total serial bandwidth with as many as two million logic cells.

Atmel (www.atmel.com) has been a longtime supplier of both radiation-tolerant and radiation-hardened (rad-hard) FPGAs for space-based applications (Fig. 1). As an example, model AT40KEL040 is a rad-hard FPGA dedicated for space use. It is based on a static-random-access-memory (SRAM) architecture with 46,000 application-specific-integrated-circuit



(ASIC) gates and fabricated in a 0.35- μm silicon CMOS semiconductor process. The FPGA, which operates at internal clock rate of 60 MHz, provides 18-ns memory access speed over an operating temperature range of -55 to $+125^{\circ}\text{C}$.

Altera (www.altera.com), now part of Intel Co. (www.intel.com), offers high-performance Stratix 10 FPGAs that support advanced beam-forming functions in many stationary and portable military radar systems (Fig. 2). Capable of operating at clock rates to 1 GHz, these FPGAs can perform at rates to 10 TFLOPS with power efficiency to 80 GFLOPS/W.

In addition, Microsemi Corp. (www.microsemi.com) supplies high-performance, low-power and radiation-tolerance FPGAs and systems-on-a-chips (SoCs) for commercial, industrial, and military applications. Earlier this year, the company acknowledged its support of defense contractor Lockheed Martin during the U.S. Navy's successful 158th, 159th, and 160th test launches of the Trident II D5 Fleet Ballistic Missile (FBM). Lockheed Martin has been the U.S. Navy's strategic missile prime contractor, and Microsemi has played a strong part in achieving the signal-processing goals of these missile guidance systems with its FPGAs and SoCs.

In many defense systems, signal processing is not accomplished solely by DSPs or FPGAs, but through a combination of the two, along with multiple-core microprocessors and various other digital components. Suppliers of DSPs and FPGAs typically offer sample boards for different applications, such as secure communications systems and portable radar systems, to help users through their own system-design process. System designs employing both DSPs and FPGAs offer a great deal of flexibility, since different types of functions, such as fixed-point and floating-point operations, can be directed to the different types of processors.

In addition to sample boards, many component suppliers also support their devices with model libraries that can speed the design process, such as models for FIR filters, FFTs, and IIR filters. Design support should be a consideration in addition to component performance when selecting and specifying a DSP or FPGA. ■


NI AWR DESIGN ENVIRONMENT

SIMPLY SMARTER

RADAR DESIGN

NI AWR Design Environment is one platform — integrating system, circuit, and electromagnetic analysis — for the design of today's radar systems spanning EW to transportation, weather monitoring, and biomedical applications. The software's intuitive use model, proven simulation technologies, and open architecture supporting third-party solutions translates to zero barriers for your radar system design success. Simply smarter design.

Learn more at ni.com/awr



Microwave Office | Visual System Simulator™ | Analog Office | AXIEM | Analyst™


©2016 National Instruments. All rights reserved. Analog Office, AWR, AWR Design Environment, AXIEM, Microwave Office, National Instruments, NI, and ni.com are trademarks of National Instruments. Other product and company names listed are trademarks or trade names of their respective companies.

Coupler Passes DC, Power Levels to 200W

CAPABLE OF PASSING dc and handling high-frequency power levels to 200 W for signals from 225 to 450 MHz, the model MBDA-30-451HP 50- Ω bidirectional coupler offers low loss and high directivity. This compact 30-dB coupler features mainline insertion loss of only 0.15 dB and directivity of 28 dB. Typical input and output return loss is 30 dB. Typical coupling flatness is ± 0.85 dB, with worst-case coupling flatness of ± 1 dB. Well-suited for use in VHF and UHF radios for antenna feeds and with high-power amplifiers, the miniature coupler operates over a temperature range of -55 to $+105^{\circ}\text{C}$. It measures just $1.0 \times 1.0 \times 0.051$ in.

MINI-CIRCUITS

P.O. Box 350166, Brooklyn, NY 11235-003; (718) 934-4500, www.minicircuits.com



Frequency Dividers Tackle 0.5 to 18.0 GHz

HIGH-RELIABILITY (HI-REL) frequency dividers have been developed in bands from 0.5 to 18.0 GHz. Available in divide-by-two, four, five, eight, and 10 configurations, the frequency-divider modules are well-suited for use with phase-locked loops (PLLs) in frequency synthesizers. Based on GaAs heterojunction-bipolar-transistor (HBT) monolithic-microwave-integrated-circuit (MMIC) technology, the frequency dividers operate on a single $+5\text{-V}$ dc supply and can achieve typical additive phase noise of -155 dBc/Hz offset 100 kHz from the carrier. They provide output-power levels from -1 to -4 dBm and are qualified to EAR99 requirements. All models come with field-replaceable SMA connectors in Kovar packages and meet MIL-STD-883 requirements. They have an operating temperature range of -55 to $+85^{\circ}\text{C}$.

PASTERNAK ENTERPRISES INC.

17802 Fitch, Irvine, CA 92614; (949) 261-1920, (866) 727-8376, www.pasternack.com

Amplifier Boosts Forward and Backward

MODEL TTRM1010 is a bidirectional solid-state amplifier capable of 3 W output power from 30 to 3,000 MHz. Well-suited for small- to medium-sized unmanned-aerial-system (UAS) applications, the amplifier incorporates power-supply circuitry for operating from power sources from $+9$ to $+36$ V dc. Typical gain is 23 dB, while typical noise figure is 3 dB. The amplifier measures $3.25 \times 2.00 \times 0.993$ in.

TRIAD RF SYSTEMS

11 Harts Lane, Ste. I, E. Brunswick, NJ 08816; (855) 558-1001, e-mail: sales@triadrf.com, www.triadrf.com



Frequency Synthesizer Tunes 3 to 6 GHz

LOW NOISE frequency synthesizer model KMTS2500-300600-10 combines the best in direct-digital-synthesis (DDS) and voltage-controlled-oscillator (VCO) technologies for excellent spectral purity from 3 to 6 GHz. The synthesizer achieves 1-Hz tuning resolution with less than 2-W power consumption and is ideal for use in radar systems, unmanned aerial vehicles (UAVs), communications systems, and test equipment. It provides at least $+4$ dBm output power across the tuning range. Typical phase noise is -87 dBc/Hz offset 1 kHz from the carrier and -93 dBc/Hz offset 100 kHz from the carrier. Typical harmonic level is -18 dBc, with typical spurious of -50 dBc. The synthesizer operates on $+12\text{-V}$ dc supplies and has an operating temperature range of -20 to $+70^{\circ}\text{C}$.

SYNERGY MICROWAVE CORP.

201 McLean Blvd., Paterson, NJ 07504; (973) 881-8800, www.synergymicrowave.com

Bandpass Filter Screens 0.7 to 6.0 GHz

MODEL DTRA-00014 is a digitally tunable filter with continuously adjustable bandwidth from 700 MHz to 6 GHz. Since different passbands of bandpass filters are often required to suppress signals in commercial, industrial, and military electronic applications, this single bandpass filter can be set for typical passbands of 5, 10, 15, 20, and 40 MHz to eliminate unwanted interference within a particular passband and center frequency. The rack-mount filter, which includes Ethernet and General Purpose Interface Bus (GPIB) interfaces, is also well-suited for use in automatic-test-equipment (ATE) systems.

K&L MICROWAVE

2250 Northwood Dr., Salisbury, MD 21801; (410) 749-2424, www.klmicrowave.com



Design Feature

XIA XINLIN | Master

YU LIU | Doctor, Associate Professor

YANG TAO | Doctor, Associate Professor

University of Electronic Science and Technology of China, School of Electronic Engineering,
Chengdu, Sichuan 611731, People's Republic of China; e-mail (for Xia Xinlin): xx10702@sina.cn

UWB Bandpass Filter Includes Notched Band

Leveraging two interdigital coupled three-line structures with bandpass characteristics, this compact ultrawideband filter incorporates a notched band with 25-dB rejection.

Development of ultrawideband (UWB) communications systems requires the design of many different component functions, including bandpass filters (BPFs) with acceptable selectivity. To serve UWB communications applications, a compact UWB BPF with reasonable selectivity and an integral notched band was fabricated with two interdigital, coupled, three-line structures. Selectivity was improved by adding another signal path loaded by two short-circuit stubs. The filter exhibits sharp rolloff to its rejection bands with a wide fractional bandwidth of 116%, with 25-dB rejection in the notched band.

The UWB spectrum from 3.1 to 10.6 GHz has attracted lots of attention in recent years due to its excellent energy efficiency—it supports short-range transmission of very high data rates while only requiring very low power levels. This spectrum was authorized for commercial radio use at low transmit levels in 2002.¹


A great deal of research has been reported on efforts to develop BPFs with high selectivity for UWB use while achieving wide stopband, low insertion loss, and compact size.²⁻¹² One approach, with three coupled interdigital transmission lines, has proven popular in recent UWB BPF designs.^{2,3}

Other UWB BPF design approaches involve the use of transitions between different microwave transmission lines, such as microstrip and coplanar waveguide (CPW). These UWB BPFs have incorporated both CPW-to-microstrip transitions⁴ and microstrip-to-CPW transitions.⁵ In ref. 6, a new approach involving a bandpass defected microstrip resonator was used to implement an UWB BPF.


Because UWB signals are used at such low levels over such wide bandwidths, interfering signals are inevitable, leading to the development of various methods to create a notched band within the passband of an UWB BPF.⁷⁻¹² For example, an L-shaped open-end slot was inserted in a trisection-stepped-

impedance-resonator (TSSIR) to generate a notched band at 5.5 GHz.⁷ In ref. 8, a parasitic coupled line was added to achieve an UWB BPF with a notched band. In ref. 9, a microstrip-to-stripline transition was used in the UWB BPF, and a microstrip stub located at the feedlines helped to reject wireless-local-area-network (WLAN) signals within the UWB frequency range.

In ref. 10, a slow-wave, half-mode, substrate-integrated-waveguide (SW-HMSIW) UWB BPF design achieved a notched band through the use of an L-type resonator. More recently, several novel structures were reported to implement a notch band, such as the via-loaded ring resonators¹¹ and a spiral defected ground structure.¹²



1. These diagrams show the basic BPF configuration with (a) Path 1 and Path 2 and (b) an equivalent transmission-line model of the filter.



2. These plots show simulations of (a) the filter's Path 1 and Path 2 transmission paths and (b) the equipment circuit representation of the filter of Fig. 3.

DESIGN DETAILS

To achieve good selectivity over the wide UWB frequency range, a BPF with a novel structure based on three interdigital coupled lines was developed (Fig. 1). To facilitate the design process, an equivalent-circuit transmission-line model was constructed using the Advanced Design System 2009 (ADS 2009) computer-aided-engineering (CAE) simulation software from Agilent Technologies (now Keysight Technologies).

Compared with traditional UWB BPFs based on the interdigital coupled three-line structures, the proposed filter offers improvements in terms of selectivity, small size, and low insertion loss. The filter also achieves a notched band at 7.3 GHz with a maximum rejection loss of 25 dB. A prototype was fabricated and measured using commercial test equipment, with test results matching closely with the computer simulations.


Figure 1 shows the basic structure of the UWB BPF and its equivalent-circuit transmission-line model. Input signals travel through two different signal paths. The filter's main transmission path consists of two interdigital coupled three-line structures. The other signal path is a transmission line loaded with two short-circuited stubs.

As the simulations of paths 1 and 2 show in Fig. 2a, the interdigital coupled three-line structures of path 1 exhibit bandpass characteristics. These characteristics are not directly usable for UWB filtering because of unsatisfactory out-of-band characteristics like poor selectivity and narrow upper stopband. Additional filtering is provided by the transmission line loaded by the two short-circuited stubs (path 2), which functions as a narrow bandpass filter.

To simplify analysis, as detailed in ref. 13, the three interdigital coupled lines can be converted to an asymmetric parallel coupled-line structure. For convenience's sake with respect to the filter design, its equivalent circuits (Fig. 3) are analyzed by ADS 2009. The simulated results of the equivalent circuits with different coupling

coefficients are shown in Fig. 2b. In this work, its coupling coefficient of coupled lines is 0.64 due to limitations of manufacturing technology and the requirement of UWB. The optimized parameters for the proposed filter using ADS software were as follows:

$$\begin{aligned} Z_1 &= 143 \, \Omega; \\ Z_2 &= 93 \, \Omega; \\ Z_3 &= 93 \, \Omega; \\ \theta_1 &= 26 \, \text{deg}; \\ \theta_2 &= 90 \, \text{deg}; \\ \theta_3 &= 90 \, \text{deg}; \\ Z_{00} &= 62 \, \Omega; \\ Z_{0e} &= 278 \, \Omega; \text{ and} \\ \theta_4 &= 90 \, \text{deg}. \end{aligned}$$



3. This simplified equivalent circuit represents the UWB BPF.



4. The UWB BPF was fabricated on 0.787-mm-thick RT/duroid 5880 circuit-board material (from Rogers Corp.) with relative permittivity of 2.2.



MODULAR TEST SYSTEMS

Built Your Way and Delivered within 2 Weeks!

Signal Routing & Attenuation Control for Production Test, R&D and More!

Mini-Circuits' new ZTM-Series RF test systems dramatically accelerate custom solutions for a wide range of applications in test environments. Choose from our lineup of extra-long-life SPDT, SP4T, SP6T and transfer switches, and programmable attenuators with attenuation ranges of 0 to 30, 60, or 90, 110 or 120 dB. We'll build and ship a solution tailored to your exact requirements *within just 2 weeks!*

It's that simple! Give us a call and talk to our engineers about how Mini-Circuits' ZTM-Series custom rack mount test solutions can improve efficiency, increase throughput, and save cost in your business!

Features

- Rugged 19" Rack Mountable Chassis
- Customizable Front Panel Layout
- Light Weight
- USB and Ethernet Control
- User-friendly GUI and DLLs Included
- Qualified to 100 Million Switch Cycles
- Affordable Cost
- **Delivery within 2 Weeks!**

Choose from hundreds of possible configurations!



SPDT Switches
DC – 18 GHz



SP4T Switches
DC – 18 GHz



SP6T Switches
DC – 12 GHz



Transfer Switches
DC – 18 GHz




0 – 30, 60, 90, 110 or 120 dB
Programmable Attenuators
1 MHz – 6 GHz



Configure your
system online now
for a fast quote!





5. These plots show simulated and measured results for (a) transmission loss and (b) group delay behavior.

Introducing the transmission line with two stubs generates two transmission zeros around the passband edges, significantly improving the UWB BPF selectivity. Moreover, a notched band at the passband center frequency is obtained.

Finally, according to parameters provided by ADS 2009, an UWB BPF was fabricated on RT/duroid 5880 from Rogers Corp. (www.rogerscorp.com) for experimental analysis. The circuit material has a dielectric constant (relative permittivity) of 2.2 measured at 10 GHz in the z-axis (thickness); circuit materials with 0.787-mm thickness were used for the filter.

Figure 4 presents a photograph of the fabricated UWB BPF. The filter was assembled according to the following parameters, developed with the aid of the ANSYS High Frequency Structure Simulator (HFSS) electromagnetic (EM) simulation software (V 13) from ANSYS (www.ansys.com):

- $w0 = 2.4$ mm;
- $l0 = 4$ mm;
- $s = 0.1$ mm;
- $d2 = 0.425$ mm;
- $g2 = 0.35$ mm;
- $d0 = 0.45$ mm;
- $w1 = 0.1$ mm;
- $w2 = 0.25$ mm;
- $g0 = 0.15$ mm;
- $g1 = 0.35$ mm;
- $w3 = 0.8$ mm;
- $d1 = 0.7$ mm;
- $l1 = 7.03$ mm;
- $w4 = 0.8$ mm;

COMPARING THE PROPOSED FILTER DESIGN WITH OTHER FILTERS						
Reference	SF	3-dB FBW	S_{11} (dB)	S_{21} (dB)	F_c (GHz)	Size ($\lambda_g \times \lambda_g$)
2	0.88	108%	>10	NG	12.6	1.12×0.84
3	0.82	103%	>15.1	<0.6	15.1	0.94×0.63
4	0.50	95%	>11	<1.83	16	1.07×0.35
5	0.80	116%	>14	<0.68	12.4	1.10×0.55
6	0.65	110%	>10	<1	13.5	1.67×0.08
7	0.80	118%	>11.5	<1	13.6	0.98×0.35
8	0.54	103%	>12.5	<0.45	NG	0.75×0.40
9	0.8	114%	>10	<0.83	14.5	1.14×0.90
10	NG	113%	>14.9	<1.77	NG	0.87×0.66
11	0.74	109%	>10	<1.5	27.6	0.82×0.50
12	0.72	110%	>11	<0.6	15.6	0.68×0.50
Current work	0.91	116%	>15	<0.6	17.5	0.51×0.11

Notes: The selectivity factor (SF) = $\Delta f(3 \text{ dB})/\Delta f(20 \text{ dB})$; F_c = the upper stopband frequency for 20-dB insertion loss; NG means not given; λ_g = the guided wavelength at 6.85 GHz.

TEST RESULTS

The S-parameters of the fabricated filter were obtained through measurements with a model E8383B vector network analyzer (VNA) from Agilent Technologies (again, now Keysight Technologies). As shown in Fig. 5, good consistency between the simulation and experiment results is observed except for the tiny frequency shift mainly caused by the machining and assemblage errors.

The measured results reveal that this filter achieves a very wide fractional bandwidth of 116% (3.05 to 11.4 GHz) with good return loss. Besides, this filter has a low insertion loss (>0.6 dB) within the passband. Obviously, it achieved sharp selectivity due to the transmission zeros at the lower and upper passband edges, respectively. Moreover, a notched band with a maximum rejection loss of 25 dB at 7.3 GHz was obtained. The group delay is relatively flat across the full UWB passband, with 0.25 ns or less variation (not including the notched band).

The *table* compares the performance of this UWB BPF with notched band to other UWB filters reported in the technical literature. Looking at the table, this novel UWB BPF has lower insertion loss, more compact size, wider passband bandwidth, and somewhat sharper selectivity.

The compact UWB filter shows measured performance that compares favorably with the best published results for UWB BPFs, including good selectivity, low insertion loss (>0.6 dB), compact size ($0.51\lambda_g \times 0.11\lambda_g$), good return loss (<15 dB), and wide bandwidth (3.05 to 11.4 GHz). Such performance levels make it a likely candidate for UWB communications systems, especially when the notched band can be applied to diminish the effects of troublesome interference within the UWB frequency range. **mmv**

ACKNOWLEDGMENTS

This work was supported by the National Natural Science Foundation of China under Grant 61471093 and the China Postdoctoral Science Foundation under Grant 2014M552337.

REFERENCES

1. Federal Communications Commission, "Revision of part 15 of the commission's rules regarding ultra-wideband transmission systems," First Report and Order, FCC 02. V48, April 2002.
2. X. Chen, L. Zhang, and Y. Peng, "UWB band-pass filter with sharp rejection and narrow notched band," *Electronic Letters*, Vol. 50, No. 15, 2014, pp. 1,079-1,080.
3. X. Lu, B. Wei, Z. Xu, B. Cao, X. Guo, X. Zhang, R. Wang, and F. Song, "Superconducting Ultra-Wideband (UWB) Bandpass Filter Design Based on Quintuple/Quadruple/Triple-Mode Resonator," *IEEE Transactions on Microwave Theory & Techniques*, Vol. 63, No. 4, 2015, pp. 1281-1293.
4. H. Hu, X. Huang, and C. Cheng, "Ultra-wideband bandpass filter using CPW-to-microstrip coupling structure," *Electronic Letters*, Vol. 42, No. 10, 2006, pp. 586-587.
5. A. Ghazali, M. Sazid, and S. Pal, "Compact broadband balun-based UWB-BPF with minimum insertion loss and sharp selectivity," *Electronic Letters*, Vol. 51, No. 15, 2015, pp. 1,174-1,175.
6. S. Fallahzadeh and M. Tayarani, "A New Microstrip UWB Bandpass Filter Using Defected Microstrip Structures," *Journal of Electromagnetic Waves and Applications*, Vol. 24, No. 7, 2010, pp. 893-902.
7. C.-H. Lee, C.-I. G. Hsu, and L.-H. Chen, "Band-notched ultra-wideband bandpass filter design using combined modified quarter-wavelength tri-section stepped-impedance resonator," *IET Microwave Antennas & Propagation*, Vol. 3, No. 8, 2009, pp. 1,232-1,236.
8. S. Pirani, J. Nourinia, and C. Ghobadi, "Band-Notched UWB BPF Design Using Parasitic Coupled Line," *IEEE Microwave & Wireless Component Letters*, Vol. 20, No. 8, 2010, pp. 444-446.
9. C.-H. Lee, C.-I. G. Hsu, and C.-J. Chen, "Band-Notched Balanced UWB BPF With Stepped-Impedance Slotline Multi-Mode Resonator," *IEEE Microwave & Wireless Component Letters*, Vol. 22, No. 4, 2012, pp. 182-184.
10. J. Li, C. Ding, F. Wei, and X. Shi, "Compact UWB

BPF with notch band based on SW-HMSIW," *Electronic Letters*, Vol. 51, No. 17, 2015, pp. 1,338-1,339.

11. H. Zhu and Q.-X. Chu, "Ultra-Wideband Bandpass Filter With a Notch-Band Using Stub-Loaded Ring Resonator," *IEEE Microwave & Wireless Component Letters*, Vol. 23, No. 7, 2013, pp. 341-343.

12. G. Karimi, K.-H. Farnaz, and H. Siahkamari, "Compact UWB BPF using slotted resonator with an independently controllable notched band," *International Journal of Microwave & Wireless Technology*, Vol. 8, No. 1, 2016, pp. 25-31.

13. M.-H. Weng, C.-T. Liauh, H.-W. Wu, and S. Vargas, "An Ultra-Wideband Bandpass Filter With an Embedded Open-Circuited Stub Structure to Improve In-Band Performance," *IEEE Microwave & Wireless Component Letters*, Vol. 19, No. 3, 2009, pp. 146-148.

Powerful Multipath/Link Emulator



Multipath Rayleigh & Rician Fading
Unmanned Aerial Vehicle (UAV) testing
Sophisticated Satellite link emulation
Mobile Comm's on the move testing


**250 MHz
bandwidth**

Test solutions for

WIN-T
MUOS
JTRS
IRIS

- warfare information networks, tactical
- mobile user objective system
- Joint Tactical Radio System
- Internet routing in space

Software showing mobile link setup



RF Test Equipment for Wireless Communications

dbm Corp, Inc

32A Spruce Street ♦ Oakland, NJ 07436
 Tel (201) 677-0008 ♦ Fax (201) 677-9444

www.dbmcorp.com

Design Feature

DR. BENMOSTEFA NAIMA | Researcher

STIC Laboratory, Department of Electrical Engineering, Faculty of Technology, University of Tlemcen,
Post Box 230, Pole of Chetouane, 13000 Tlemcen, Algeria; benmostefanaima@yahoo.fr

Split-Ring Resonators Add to SIW Bandpass Filter

Complementary split-ring resonators etched into substrate-integrated-waveguide circuits can form the basis of broadband PCB bandpass filters at microwave frequencies.

Waveguide has long been a reliable, low-loss transmission line technology capable of handling high power levels and forming high-quality-factor (high-Q) resonators. But it is large and heavy compared to transmission-line technologies constructed on printed-circuit-board (PCB) materials. Substrate-integrated-waveguide (SIW) transmission-line technology brings some of the features of rectangular waveguide to the miniature size of PCB circuits.

In addition, SIW transmission lines are easy to fabricate. By using SIW transmission lines to fabricate complementary split-ring resonator (CSRR) structures, it is possible to achieve waveguide-like filter performance from a planar PCB.

As with metallic waveguides, SIW circuits with CSRR elements are capable of achieving high-quality-factor (high-Q) performance. By combining SIW technology with CSRR circuit elements, it is possible to build a low-profile planar bandpass filter on a single substrate with high-Q performance for radio front ends in broadband communication systems (Fig. 1).

CSRRs etched in the ground plane or conductor strip of a planar transmission media, such as microstrip or coplanar waveguide (CPW), provide a negative effective permittivity to the structure. In doing so, they preclude signal propagation and provide stopband behavior at the resonant frequency of the CSRR structure.¹


CSRRs have been proposed for the synthesis of negative permittivity and left-handed (LH) metamaterials in planar configurations.¹⁻³ CSRRs are the dual counterparts² of the split-ring resonators (SRRs) proposed by Pendry.⁴ CSRRs have been applied to the design of compact bandpass filters with high performance and controllable characteristics.^{5,6}

By forming them with SIW technology, it is possible to achieve excellent filter performance from small planar circuits. SIW transmission lines are created by forming two rows of metallized viaholes in a PCB substrate. The field distribution in a SIW transmission line is similar to that in a conventional rectangular waveguide.


Figure 2 shows the basic structure of an SIW transmission line. It has two rows of metallized viaholes on both sides of the substrate. The key design parameters for achieving a desired level of performance include the diameter of the viaholes, the separation between two successive viaholes, and the separation between the rows of viaholes. Such parameters are



1. This is the basic structure of a CSRR, with inner and outer rings and the dark areas representing metallization of the rings.



2. A simplified view of a SIW transmission line (left) is shown next to a cross-sectional view of a dielectric-loaded rectangular waveguide (right).



3. The top view of a PCB substrate shows an SIW circuit with etched CSRR.

essential for designing low-loss SIW circuitry. To design an SIW circuit with low radiation loss, several conditions should also be met:

$$D < \lambda_g/5$$

and

$$b = 2D$$

where

a = the center-to-center distance between two parallel metallized viaholes;

b = the height of the substrate;

c = the speed of light in a vacuum;

d = the diameter of the metallized viaholes;

D = the periodic distance between two viaholes;

λ_g = the wavelength of the waveguide;

a_{RWG} = the width of a dielectric filled metallic waveguide equivalent to the SIW


Parameter b should be as small as possible to minimize radiation losses. Parameter D , which also impacts the loss performance of an SIW circuit, will change according to b . The ratio of b to D is more critical in maintaining low radiation loss than the individual values of b and D .

When designing SIW transmission lines for a particular frequency range, the cutoff frequency, f_c , is determined as a function of the width and length of the SIW structure. An SIW structure has highpass characteristics. It exhibits a transverse electromagnetic (TE) TE₁₀ mode with dispersion characteristics—characteristics that are almost identical with the same mode of a dielectric filled rectangular waveguide with an equivalent width.

The effective width of an SIW structure is given by:

$$a_{\text{RWG}} = a - (D^2/0.95b)$$

while f_c can be found from




4. The bottom view of a PCB substrate shows the bottom of the CSRR etched in the substrate.


$$f_c = C/[2(\epsilon_r)^{0.5} a_{\text{RWG}}]$$

Figure 3 shows the layout of an SIW circuit with CSRRs etched in the top layer of a PCB substrate. Figure 4 depicts the layout of an SIW circuit with CSRRs etched in the bottom layer of the substrate. Since CSRRs are etched in the center of the top or bottom layers of the substrate—and they are mainly excited by the electric field induced by the SIW (as for TE₁₀ mode)—this coupling can be modeled by connecting the capacitance of the SIW transmission lines to the CSRRs. Using this strategy, the lumped-element equivalent circuit for an CSRR-loaded SIW circuit is shown in Fig. 5.


As long as the electrical size of the CSRRs is small, the structures can be described by means of lumped elements. In these models, L is the SIW inductance and C is the coupling capacitance



5. This equivalent-circuit model represents the CSRR-loaded SIW circuit shown in Figs. 3 and 4.



6. These simulated responses show the insertion loss (S_{21}) and return loss (S_{11}) for the basic CSRR cell depicted in Fig. 3.




7. These simulated responses show the insertion loss (S_{21}) and return loss (S_{11}) for the basic CSRR cell depicted in Fig. 4.

between the SIW and the CSRR. The resonator is described by means of a parallel tank,^{7,8} with L_c and C_c being the reactive circuit elements and R accounting for loss.

Using this model, the transmission-zero frequency which nulls the shunt impedance was determined through simulations and measurements. To demonstrate the viability of the proposed technique, it was applied to the determination of the electrical parameters of a single-cell CSRR-loaded SIW circuit.

The structures of Figs. 3 and 4 were simulated for fabrica-




8. A compact SIW bandpass filter was formed with three cascaded CSRR cells and tapered lines for interconnection with microstrip input and output transmission lines.


tion on RT/duroid 5880 circuit laminate material from Rogers Corp. (www.rogerscorp.com). The PCB material has a relative dielectric constant, ϵ_r , of 2.22 at 10 GHz in the z axis (thickness) of the material. The material's thickness, h , is 0.254 mm, and dissipation factor (loss), δ , is 0.002. The width of the access lines is 0.76 mm.

Figures 6 and 7 show the simulated scattering (S) parameters for the circuits depicted in Figs. 3 and 4, respectively. The circuit structures show similar characteristics, except that the circuit of Fig. 3 achieves higher stopband attenuation.

The single SIW CSRR cell shown in Fig. 4 was designed using a cell with outer-circle radius of 1.8 mm and inner-circle radius of



9. These simulated responses show the insertion loss (S_{21}) and return loss (S_{11}) for the SIW bandpass filter of Fig. 8.



10. This is an SIW transmission line with single CSRR cell etched in the top layer.



The best Solution for RF Technology!

LOWEST PRICE & HIGHEST QUALITY

SRTechnology Corporate

TERMINATION

MALE 2WATT
18GHz
VSWR 1.18:1



- TERMINATIONS
- ATTENUATORS
- CONNECTORS
- CABLE ASSEMBLYS
- ADAPTORS

- Frequency Range : DC~18GHz
- Impedance : 50 Ohm
- Power Rating : 2 Watt
- V.S.W.R.
- DC~4GHz : 1.05:1
- 4~8GHz : 1.10:1
- 8~18GHz : 1.18:1


Warranty 3 years
Payment Term
Within 30 days from B/L date.

sale@srtechnology.com **+82-2-866-9003**

srtechnology.com

NOW! Revolutionary **ABSORPTIVE/REFLECTIONLESS FILTERS**

DC to 21 GHz!



Stop Signal Reflections Dead in Their Tracks!

\$6⁹⁵_{ea.(qty.1000)}

Mini-Circuits is proud to bring the industry a revolutionary breakthrough in the longstanding problem of signal reflections when embedding filters in RF systems. Whereas conventional filters are fully reflective in the stopband, our new X-series reflectionless filters are matched to 50Ω in the passband, stopband and transition band, eliminating intermods, ripples and other problems caused by reflections in the signal chain. They're perfect for pairing with non-linear devices such as mixers and multipliers, significantly reducing unwanted signals generated due to non-linearity and increasing system dynamic range by eliminating matching attenuators². They'll change the way you think about using filters in your design!

Jump on the bandwagon, and place your order online today for delivery as soon as tomorrow. Need a custom design? Call us to talk to our engineers about a reflectionless filter for your system requirements.



X-Series

- ✓ High pass, low pass and band pass models
- ✓ Patented design eliminates in-band spurs
- ✓ Absorbs stopband signal power rather than reflecting it
- ✓ Good impedance match in passband stopband and transition
- ✓ Intrinsically Cascadable³
- ✓ Passbands from DC – to 21 GHz⁴
- ✓ Stopbands up to 35 GHz

 ***Tiny 3x3mm QFN***

¹ Small quantity samples available, \$9.95 ea. (qty. 20)

² See application note AN-75-007 on our website

³ See application note AN-75-008 on our website

⁴ Defined to 3 dB cutoff point


Protected by U.S. Patent No. 8,392,495 and Chinese Patent No. ZL201080014266.1. Patent applications 14/724976 (U.S.) and PCT/USIS/33118 (PCT) pending.



Split-Ring Resonators

1.0 mm. To minimize losses, a microstrip feed was used to obtain maximum coupling between the SIW filter and the external feed line. By reducing the dimensions of the CSRR cell, the resonant frequency will increase.

The CSRR cell was loaded periodically onto the face of the SIW circuitry, but its edges were adjusted in size to achieve adequate bandwidth. As a result, their size has been slightly adjusted—to 1.7 mm for the outer-circle radius and 0.9 mm for the



11. These simulated responses show the insertion loss (S_{21}) and return loss (S_{11}) for the SIW circuit with single CSRR cell of Fig. 10.

inner-circle radius—using the RT/duroid 5880 PCB substrate material.

Following simulation via the High Frequency Structure Simulator (HFSS) EM simulation software from ANSYS (www.ansys.com), the single cell CSRR was found to resonate at around 6.5 GHz, yielding negative effective permittivity at that frequency. Figures 6 and 7 show simulated results for the CSRR-loaded SIW structures of Figs. 3 and 4, respectively, from 4 to 10 GHz.

When CSRR cells are cascaded, as shown in Fig. 8, the SIW circuit exhibits bandpass behavior from 7.2 to 10.0 GHz with very low return and insertion losses. When two CSRR cells are added and aligned with the central CSRR structure, the resulting structure achieves wide bandwidth from 4 to 12 GHz as part of a bandpass response (Fig. 9).

A SIW circuit with square CSRR cell was designed using a width of 3.6 mm for the outer ring and 2.0 mm for the inner ring (Fig. 10). A taper was employed to minimize losses by maximizing coupling between the SIW filter and the external line. Otherwise, the SIW circuit dimensions were the same as those for the SIW circuits with circular CSRR cells. The SIW circuit with square CSRR cell was simulated with HFSS software, with minimal reflections found around 7.4 GHz, when the effective permittivity of the CSRR cell is negative (Fig. 11). **mw**

Editor's Note: To read the full version of this article, visit mwr.com.

KOAXIS, Inc. Coaxial RF Cable Assemblies

VITA 67 Cable Assemblies



**Build It
See It
Buy It**

**visually build a cable assembly
get a specification instantly
online using eCommerce**

online at koaxis.com




Made in the USA

+1 (610) 222-0154

**USB &
Ethernet**

POWER SENSORS

Turn Smart Power Sensors into Low-Cost RF Power Meters!



1 to 8000 MHz -45 to +20 dBm

\$695 from ea. qty. (1-4)

Mini-Circuits' smart RF power sensors turn almost any Windows® or Linux® based computer into a low-cost testing platform for all kinds of RF components and systems. To give you even more capabilities, our lineup now features models for high-sensitivity measurement of CW, multi-tone and modulated signals at levels as low as -45 dBm!

With 8 different models in stock offering USB and Ethernet control options, measurement speeds as fast as 10 ms*, dynamic range options from -45 to +20 dBm, and measurement capability for continuous wave and modulated signals, chances are, we have a power sensor to meet your needs and fit your budget!

Our user-friendly GUI provides a full range of measurement tools including measurement averaging, time-scheduled measurements, multi-sensor support, and measurement applications supporting RF testing of couplers, filters, amplifiers and more! View data and graphs on-screen or export to Excel® for reporting and data analysis.

All Mini-Circuits power sensors fit in your pocket and come supplied with all the accessories you need for immediate use right out of the box. Visit minicircuits.com and place your order today for delivery as soon as tomorrow.

RoHS compliant

Model	Power Measurement	Frequency MHz	Dynamic Range (dBm)	Control Interface	Price \$ ea. (Qty1-4)
NEW! PWR-6LRMS-RC	True RMS	50 to 6000	-45 to +10	USB & Ethernet	1595.00
NEW! PWR-6LGHS	CW	50 to 6000	-45 to +10	USB	895.00
NEW! PWR-6RMS-RC	True RMS	50 to 6000	-35 to +20	USB & Ethernet	1595.00
PWR-4RMS	True RMS	50 to 4000	-35 to +20	USB	1169.00
PWR-2.5GHS-75 (75Ω)	CW	0.1 to 2500	-30 to +20	USB	795.00
PWR-4GHS	CW	0.009 to 4000	-30 to +20	USB	795.00
PWR-6GHS	CW	1 to 6000	-30 to +20	USB	695.00
PWR-8GHS	CW	1 to 8000	-30 to +20	USB	869.00
PWR-8GHS-RC	CW	1 to 8000	-30 to +20	USB & Ethernet	969.00
PWR-8FS	CW	1 to 8000	-30 to +20	USB	969.00

*Measurement speed as fast as 10 ms for model PWR-8-FS. All other models as fast as 30 ms.

Excel is a registered trademark of Microsoft Corporation in the US and other countries.

Neither Mini-Circuits nor Mini-Circuits Power Sensors are affiliated with or endorsed by the owners of the above-referenced trademarks.

Mini-Circuits®

Deciphering Between MIMO and MMICs

These abbreviations stand for two completely different things—antennas and semiconductors—although surprisingly some similarities exist between the two.

Modern wireless systems have long depended on monolithic microwave integrated circuits (MMICs) and are increasingly relying on the use of multiple-input, multiple-output (MIMO) antenna techniques. As much as these abbreviations seem similar, what exactly is each technology and what roles do each play in a wireless system? Knowing the differences between MMICs and MIMO systems can help avoid confusion when assembling the components for a modern wireless communications system..

MMICs are integrated circuits (ICs), designed for use at microwave frequencies and, occasionally, as high as millimeter-wave frequencies. They were originally fabricated solely on gallium-arsenide (GaAs) semiconductor wafers. Now, though they are based on a wide range of semiconductor materials, including silicon (Si), indium phosphide (InP), silicon germanium (SiGe), and, increasingly, gallium nitride (GaN) for its capabilities of operating at high voltages and high power levels at microwave frequencies (as a basis for microwave amplification and for transmitter and transceiver circuits).


MMICs comprise a number of different high-frequency components on the same chip, supplied in semiconductor die form or in a package, such as a surface-mount-technology (SMT) package for ease of mounting on a printed circuit board. A MMIC can be a passive component, such as a filter, or an active component, such as an amplifier, rather than a transistor in a similarly small package.

As an example, the model CMD233C4 from Custom MMIC (www.custommmic.com) is a distributed amplifier in a low-profile package (*Fig. 1*) fabricated on GaAs semiconductor substrate material. It is extremely broadband, operating from 2 to 18 GHz with more than 9-dB small-signal gain, 4.5-dB noise figure, and +20.5-dBm output power at 1-dB compression. The MMIC is impedance-matched to 50 Ω and powered by a single bias supply of +3 to +6 V dc.

RF/microwave MMICs are available from a large number of suppliers, in die and packaged formats, which simplifies the task of adding component functions while shrinking the overall size of a system design. MMICs can be mass-produced from large semiconductor wafers (*Fig. 2*) and screened through automated testing to maintain proportionally lower cost for each component than the equivalent cost of each of the discrete component functions they replace.

While GaAs was once the semiconductor wafer material of choice for microwave MMICs, more work at present is being done at high frequencies on GaN wafers (at least for power amplifiers) because of the material's enhanced power capabilities compared to GaAs. Many military contractors, such as Northrop Grumman Corp. (www.northropgrumman.com), maintain their own GaN and GaAs wafer/semiconductor foundries as a source of high-frequency semiconductors.

In addition, commercial semiconductor foundries offer wafers and fabrication services that enable customers to submit design files




1. By using large semiconductor wafers, great numbers of MMIC devices can be fabricated and produced with high yields. (Courtesy of MACOM.)


HIGH DYNAMIC RANGE MMIC AMPLIFIERS



NF as low as 0.8 dB IP3 to +44.6 dBm P1dB up to +23.8 dBm from **\$123** ea. (qty. 1000)

Broadband high dynamic range for high-performance applications. Mini-Circuits' PGA-series of MMIC amplifiers features ten unique models, all with outstanding combinations of low noise and high linearity to meet your needs for sensitive systems in dense signal environments. Choose from 50 Ω and 75 Ω models with a selection of bandwidth, gain, output power, IP3, noise figure and DC operating power. They all achieve low current consumption and excellent input/output return loss with no external matching required. They're even available in unpackaged die form for integration into your hybrids where minimizing size and weight is critical. From CATV and broadband to LTE, WiFi and more, there's a PGA model to improve your system performance. In stock, ready to ship, at a budget-friendly price.



- 50 and 75 Ω models
- Wideband performance
- Input/output VSWR from 1.2:1
- Choose operating voltage from +3V to +9V
- Current consumption as low as 57mA
- Tiny  SOT-89 package
- Available in unpackaged die form

 RoHS compliant

Visit minicircuits.com for detailed performance specs, test data, S-parameters, small quantity pricing and more! Place your order today, and have them in hand as soon as tomorrow!



What's the Difference?

in software to fabricate MMICs or discrete devices within the limits of a particular commercial semiconductor foundry's design guidelines. GaN is currently a widely accepted starting material for high-frequency MMICs, with many device designers in quest of filling one major gap between GaN and GaAs, and that is for a truly low-noise amplifier (LNA) based on GaN material.

BOOSTING CAPACITY WITH MIMO

MIMO antennas are similar to MMICs in that they integrate a number of antennas into a single package (*Fig. 2*). These antennas take advantage of multipath propagation to improve the performance and capacity of a wireless communications system. Prior to the use of MIMO techniques, multipath effects were never considered a good thing. Signal multipath is caused by transmitted signals bouncing off objects between a transmit antenna and a receive antenna, such as buildings, towers, bridges, and any object with sufficient mass and material type to deflect electromagnetic (EM) energy.

Legacy wireless communications systems have used what are known as single-input, single-output (SISO) antenna configurations. MIMO approaches employ multiple transmit and receive antennas or antenna elements to send signals along a number of different propagation paths (*Fig. 2*) rather than a

single signal path and, in the process, enable increased data rates for a given frequency and bandwidth.

MIMO methods can increase channel capacity as a function of the increasing number of antenna elements or boost performance in terms of signal-to-noise ratio (SNR) of a transmitter-receiver combination. Quite simply, more antennas in a MIMO system, such as a 4×4 MIMO system, with four transmit and four receive antennas, versus a 2×2 MIMO system, with two transmit and two receive antennas, means faster data rates and greater capacity.

MIMO techniques were developed in response to the ever-increasing number of wireless communications subscribers and limited amount of available bandwidth. MIMO is employed in a number of mobile communications standards, including IEEE 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), Third-Generation (3G) wireless systems, and Fourth-Generation (4G) wireless systems, including Long Term Evolution (LTE) systems.

MIMO may be implemented in the form of polarization diversity systems, where antennas use adjustable feed systems to achieve dual polarization, such as vertical and horizontal polarization or X-polarization (with -45° and $+45^\circ$ polarization). Different diversity modes may also be used with MIMO antennas.



Tickets & Registration: electronica.de/en/tickets



Messe München
Connecting Global Competence

Planet e: Where the future begins.

Automotive electronics of tomorrow. Today.

Automotive exhibition sector:	November 8–11, 2016
electronica Automotive Forum:	November 8–11, 2016
electronica Automotive Conference:	November 7, 2016
All about electronica Automotive:	electronica.de/en/automotive

World's Leading Trade Fair for Electronic Components, Systems and Applications

Messe München | November 8–11, 2016 | electronica.de




electronica 2016
inside tomorrow

Diversity modes typically used in MIMO systems include time diversity, space diversity, and frequency diversity. In time diversity, data is transmitted at different times, using different time slots and different channel coding. In space diversity, antennas are positioned in different physical positions in

order to make use of terrestrial characteristics and different radio paths available in a particular location. A reference signal (RS) is used in many MIMO configurations to allow for measurements of the spatial channel properties and facilitate coherent demodulation at the terminal. It can be an RS for a specific terminal or a common RS (CRS) that is shared among a group of terminals.

Spatial multiplexing may also be used in MIMO systems to increase system capacity. With spatial multiplexing, multiple spatial streams are sent through multiple transmit antennas; the spatial streams are separated at the receiver's multiple antennas by means of spatial signal processing.

In frequency diversity, information is communicated using different frequencies, such as the different channels on a commercial broadcast radio. It may also be implemented by means of frequency-agility techniques, such as frequency hopping or spread-spectrum communications, to divide transmitted data among available frequencies and bandwidth, as well as minimize the effects of interference and enhance communications security. **ITW**



2. MIMO technology uses multiple antennas and multiple signal paths to boost the performance and/or data capacity of a wireless communications system, optimizing use of multipath propagation effects.

IWCE's CRITICAL LTE COMMUNICATIONS FORUM

November 2-3, 2016 • McCormick Place • Chicago, IL

Mapping the Transition from LMR to LTE

IWCE's Critical LTE Communications Forum is the first event of its kind in North America. The CLC Forum will examine the network solutions, applications and opportunities for Critical Communications organizations to transition to secure, reliable networks for voice and data within an LTE framework. To learn more, visit criticalLTEforum.com.

Use promo code MP2 to save \$200!

REGISTER TODAY!

DEFEAT INTERFERENCE PROBLEMS WITH REAL-TIME SPECTRUM ANALYSIS

AS THE NUMBER of wireless technologies in communications networks expands, overcoming RF/microwave interference has become more of a challenge. Quality of service is determined by the extent of interference management. Real-time spectrum analysis (RTSA) enables users to detect challenging signals and solve network problems, making RTSA essential for field testing. In the application note, “Overcoming RF & MW Interference Challenges in the Field,” Keysight Technologies discusses interference in various networks before delving into RTSA technology and its key performance indicators.

The note begins with a description of interference in commercial wireless networks, explaining both internal and external interference. LTE networks, which must

have a sophisticated and efficient interference management scheme, are examined in detail. Microwave backhaul is then discussed, with the application note stating that approximately 50% of the world’s base stations are connected to backhaul with a microwave radio. Microwave-radio network interference can be produced by reflection and refraction, as well as the usage of unlicensed frequency bands. The challenges associated with aerospace and defense communication systems and public safety systems are explained as well.

Some of the shortcomings of traditional interference analysis are examined, too. Traditional swept-tuned and FFT spectrum analyzers can effectively de-

tect a relatively constant signal. However, these analyzers are less effective when measuring random bursty signals, nar-

row pulses, or signals with duration based on network traffic conditions. Detecting such challenging signals can be achieved by utilizing RTSA, which is able to detect transient signals, dynamic signals, and RF pulses within a specific bandwidth.

The note mentions several important RTSA performance indicators, such as real-time bandwidth, minimum signal duration for 100% probability of intercept (POI), and dynamic range. Moreover, two types of challenging interference in the field—co-channel and uplink interference—are touched upon, along with an explanation of how RTSA can help detect both types. The application note also states that component failures lead to many instances of interference, with further discussion of how component-based problems can be prevented. The document concludes with a description of Keysight’s FieldFox handheld analyzers.

**Keysight Technologies,
1400 Fountaingrove Pkwy.,
Santa Rosa, CA 95403;
(707) 577-2663;
www.keysight.com**

DELIVER 125 W OF POWER USING A GAN TRANSISTOR

GALLIUM-NITRIDE (GAN) DISCRETE transistors have steadily improved in terms of performance, with manufacturers now offering devices with impressive gain, RF output power, and efficiency. In the white paper, “The Design of a 125W L-band GaN Power Amplifier,” Plextek RFI demonstrates the design of a single-stage, 125-W power amplifier (PA). The PA, which is optimized for a frequency range of 960 to 1,215 MHz, is designed with a commercially available GaN transistor housed in a metal-based ceramic package.

The PA is designed using a 32-mil-thick Rogers 4360G2 laminate with 1-oz. metallization. By using this relatively thick substrate, the trace widths of the required characteristic impedance are wide enough to handle high RF power and dc current under large-signal drive conditions. The transistor operates with 260-mA quiescent current at a drain voltage of +50 V dc.

Large-signal load-pull data demonstrated the device is able to provide +51 dBm of output power at the 3-dB compression point at 1.1 GHz. The complete PA schematic is presented, with passive components carefully selected to handle high dc

voltages and RF power levels alike. Both the gate and drain bias networks utilize printed transmission lines along with shunt surface-mount-technology (SMT) capacitors. Furthermore, the input and output matching networks are lowpass structures that transform the 50-Ω system impedance to the lower source and load impedances needed to achieve optimum power transfer.

Utilizing a SHaaS ecosystem can reduce redundancy and maintenance. For example, a single sensor can be used for a range of applications. A motion sensor could be used to control lighting, manage the home environment, and more.

The final assembly is mounted onto an aluminum alloy carrier that acts as a heat spreader. This carrier can also be attached to a heatsink. Small-signal S-parameters were measured at package-base temperatures of -40, +25, and +85°C. These measurements demonstrate a small-signal gain of approximately 19 dB across the frequency range, which varies by less than 2 dB over temperature. Large-signal measurements were performed over the same temperature range. Those results prove the PA can deliver 125 W of output power at the 3-dB compression point at midband. The document also details the PA’s efficiency performance.

**Plextek RFI, London Rd.,
Great Chesterford,
Saffron Walden, CB10 1NY,
UK; +44 (0) 1799 533200;
www.plextekrfi.com**

Tiny

TOUGHEST MIXERS UNDER THE SUN

NOW
UP TO **20 GHz!**



\$4⁹⁵

from 1 ea. qty. 1000

Mini-Circuits' rugged, tiny ceramic SIM mixers

offer ultra-wideband, high-frequency performance for applications ranging from 100 kHz to 20 GHz, while maintaining low conversion loss, high isolation and high IP3. They're available in 25 models with LO levels of +7, +10, +13, & +17 dBm, so regardless of your bandwidth requirements or application environment, whether industrial, military or commercial, there's a tiny SIM mixer that will meet your needs.



All models stand up to the toughest operating conditions, including high ESD levels, and they're available from stock for a very competitive price.

Visit our website to view comprehensive performance data, curves, data sheets, PCB layouts, environmental specifications and more. You can even order direct from our web store and have your order in your hands as early as tomorrow!

Mini-Circuits...we're redefining what VALUE is all about!

U.S. Patent # 7,027,795  RoHS compliant



PORTABLE TESTERS

Add Real-Time Spectrum Analysis to 50 GHz

Covering a total frequency range from 9 kHz to 50 GHz, these portable, handheld test instruments now offer a 10-MHz real-time bandwidth to capture short-duration signals.

ON-SITE SPECTRUM ANALYSIS ONCE implied the use of a “portable” instrument with a battery almost large enough to start an automobile. But portable RF/microwave test instruments have come a long way, and lightweight units such as the FieldFox analyzers from Keysight Technologies (www.keysight.com) provide a number of measurement functions from a battery-powered package weighing just 7.1 lb. (3.2 kg).


Just added as an option to 16 models in the FieldFox line is real-time spectrum-analysis (RTSA) capability. Available over a total frequency range of 9 kHz to 50 GHz, it captures the most elusive signals—including multiple pulses, interference, and other signals occupying a band of interest. With outstanding efficiency, these portable analyzers can run for nearly four hours on a single battery charge for thorough, on-site RTSA measurements.

The FieldFox analyzers (*Fig. 1*) are compact and light in weight, yet quite rugged and lacking none of the power and accuracy of much larger, laboratory benchtop analyzers. They show captured signals on a bright 6.5-in. diagonal thin-film-transistor (TFT) display and are available with a variety of measurement functions, including as combination instruments with cable and antenna tester (CAT), spectrum analyzer, and vector network analyzer (VNA).

The 16 models available with RTSA option 350 (*see table*) include spectrum analyzers and combination analyzers with built-in power meters, frequency counters (with 1-Hz resolution), and a Global Positioning System (GPS) receiver for precise location of detected signals. The internal GPS receiver,

THE FIELDFOX ANALYZERS WITH OPTION 350 RTSA, AT A GLANCE			
Model	Instrument type	Frequency range	RTSA range
N9913A	Combination	30 kHz to 4 GHz	100 kHz to 4 GHz
N9914A	Combination	30 kHz to 6.5 GHz	100 kHz to 6.5 GHz
N9915A	Combination	30 kHz to 9 GHz	100 kHz to 9 GHz
N9916A	Combination	30 kHz to 14 GHz	100 kHz to 14 GHz
N9917A	Combination	30 kHz to 18 GHz	100 kHz to 18 GHz
N9918A	Combination	30 kHz to 26.5 GHz	100 kHz to 26.5 GHz
N9935A	Spectrum analyzer	30 kHz to 9 GHz	100 kHz to 9 GHz
N9936A	Spectrum analyzer	30 kHz to 14 GHz	100 kHz to 14 GHz
N9937A	Spectrum analyzer	30 kHz to 18 GHz	100 kHz to 18 GHz
N9938A	Spectrum analyzer	30 kHz to 26.5 GHz	100 kHz to 26.5 GHz
N9950A	Combination	300 kHz to 32 GHz	9 kHz to 32 GHz
N9951A	Combination	300 kHz to 44 GHz	9 kHz to 44 GHz
N9952A	Combination	300 kHz to 50 GHz	9 kHz to 50 GHz
N9960A	Spectrum analyzer	300 kHz to 32 GHz	9 kHz to 32 GHz
N9961A	Spectrum analyzer	300 kHz to 44 GHz	9 kHz to 44 GHz
N9962A	Spectrum analyzer	300 kHz to 50 GHz	9 kHz to 50 GHz
Note: Combination analyzers include cable and antenna tester (CAT), vector network analyzer (VNA), and spectrum analyzer.			

Ultra-Wideband MMIC SPLITTER/COMBINERS



Single Unit Coverage as Wide as **2 to 26.5 GHz**

\$5⁵⁶
Models from ea. (qty. 1000)

THE WIDEST BANDWIDTH IN THE INDUSTRY IN A SINGLE MODEL!

Our new EP-series ultra-wideband MMIC splitter/combiners are perfect for wide-band systems like defense, instrumentation, and all cellular bands through LTE and WiFi. These models deliver consistent performance across the whole range, so you can reduce component counts on your bill of materials by using one part instead of many! They utilize GaAs IPD technology to achieve industry-leading performance, high power handling capability and efficient heat dissipation in a tiny device size, giving you a new level of capability and the flexibility to use them almost anywhere on your PCB! They're available off the shelf, so place your order on minicircuits.com today, and have them in hand as soon as tomorrow!

- Series coverage from 0.5 to 26.5 GHz
- Power handling up to 2.5W
- Insertion loss, 1.1 dB typ.
- Isolation, 20 dB typ.
- Low phase and amplitude unbalance
- DC passing up to 1.2A

 EP2K-Series, 4x4x1mm

 EP2W-Series, 5x5x1mm



which has a female SMA connector for attachment of a GPS antenna, can also be used as a frequency reference.

Although battery powered, these analyzers perform very much like larger benchtop instruments, with frequency resolution of 1 Hz for signals to 5 GHz, 1.34 Hz for signals to 10 GHz, 2.68 Hz for signals to 20 GHz, 5.36 Hz for signals to 40 GHz, and 8.04 Hz for signals to 50 GHz. The dedicated reference oscillator is accurate to ± 0.7 ppm plus the aging rate, which is ± 1 ppm/year for 20 years.

When locked to a GPS signal, the frequency accuracy improves to ± 0.010 ppm. The nominal zero-span sweep time can be set from 1 μ s to 1000 s, with 100-ns resolution. The

zero-span 3-dB RBW is settable from 10 Hz to 5 MHz in a 1-3-10 sequence. Video bandwidth range is 1 Hz to 5 MHz. The amplitude accuracy at center frequency ranges from ± 0.8 to ± 1.4 dB depending on frequency.

AN RTSA EXAMPLE

One of the widest-frequency analyzers, model N9952A, has a real-time bandwidth of 10 MHz that can be

swept across a total frequency range of 9 kHz to 50 GHz. It features a wide dynamic range of 105 dB and spurious-free dynamic range (SFDR) of 63 dB. It can capture and display as many as four separate signal traces with a total of 561 points, using density spectrum, spectrogram, and real-time-spectrum displays. The N9952A FieldFox with RTSA capability can detect pulses as narrow as 22 ns even amidst surrounding signals and noise.

The analyzer achieves 100% probability of intercept (POI) with full amplitude accuracy for pulses as narrow as 12 μ s. As with the other analyzers featuring the RTSA option, the N9952A provides flexible triggering, with free-run, external, video, and RF burst triggers using positive- or negative-edge trigger slopes. Trigger delay times can be set from 150 ms to 10 s with 100-ns resolution. The built-in power meter in the N9952A covers a frequency range of 300 kHz to 50 GHz.

For a given frequency range, these FieldFox portable analyzers with RTSA option can capture multiple simultaneous pulses or short-duration signal events within a channel of interest. The two pulses shown in Fig. 2 were acquired within a 20-ms acquisition time for a center frequency of 1 GHz, using a spectrum-analyzer resolution bandwidth (RBW) of 35.7 kHz and real-time bandwidth of 10 MHz. The pulse traces are formed from 561 points with display persistence set at 1 s.

When working with the firm's new RTSA software, one of these FieldFox analyzers can capture and identify multiple simultaneous pulses within the capture bandwidth; work with a directional antenna to identify interference signals; and even verify wireless communications network operations, such as Long-Term-Evolution (LTE) uplink control and traffic signals (Fig. 3).

These portable analyzers with optional RTSA capability are compliant to MIL Class 2 requirements and are as home in



1. The FieldFox portable, battery-powered RF/microwave signal and spectrum analyzers are now available with optional real-time-spectrum-analyzer (RTSA) capability across bandwidths as wide as 9 kHz to 50 GHz.

C to Ka-Band Corechips for AESA



C-band integrated Corechip




6-bit X-band Corechip


6-bit Ka-band Corechip

CGY2175AHV/C1

CGY2170YHV/C1

CGY2351UH/C1






2. The portable FieldFox analyzers with optional RTSA capability can capture two simultaneous pulses and show traces on a bright, 6.5-in. diagonal TFT display screen.

commercial and industrial applications as they are in military test situations. They are well-suited for monitoring interference on two-way radio links, checking signals at satellite-communications (satcom) ground stations, capturing frequency-hopped signals, and verifying pulse sequences in military radar systems.

With their multiple display modes, such as spectrogram and real-time-spectrum displays, these FieldFox analyzers with optional RTSA capability can show small signals “hiding” within or in the presence of larger signals. They can serve as effective tools for checking on wireless communications signal carrier quality or for detecting the small signals emitted by improvised explosive devices (IEDs), even in the presence of much larger signals at airports.

The FieldFox microwave and spectrum analyzers with optional RTSA capability measure just 11.5 × 7.4 × 2.8 in. (292 ×




3. When using available software, the portable FieldFox analyzers with optional RTSA capability can measure and display LTE commercial communications control signals.

188 × 72 mm). They are software-enabled and field-upgradable for keeping pace with changing measurement requirements. In addition to the many integral measurement functions already mentioned, these portable instruments also feature a built-in interference analyzer for the frequency range of the instrument, with included record and playback capability for analyzing captured interference.

Finally, the analyzers offer a number of different options, including for characterizing pulses found in radar and electronic-warfare (EW) systems, use of an external Universal Serial Bus (USB) power sensor, and remote control of the analyzer using smartphones or other wireless devices. **mw**


KEYSIGHT TECHNOLOGIES, Inc., 1400 Fountaingrove Pkwy., Santa Rosa, CA 95403; (707) 577-2663, www.keysight.com/find/fieldfox



ECLIPSEmdi
sales@eclipsemdi.com | www.eclipsemdi.com

Maximum power.

Minimal noise.

 4mm Actual Size

Introducing the ultra small, super powerful low noise amplifier EMD1725D, DC-40 GHz.

Broadband performance ahead of its time.

Product Trends

ADAM SMITH | Director of Marketing

LitePoint, www.litepoint.com

Wi-Fi's Future Up in the Air

As competing technologies emerge, Wi-Fi must adapt over the next few years to maintain its position in the wireless arena.

IN MANY WAYS, WI-FI is a victim of its own success. Some 12 billion Wi-Fi products have been shipped and another 3 billion will be shipped in 2016, according to the Wi-Fi Alliance. Wi-Fi will continue to be one of the most prolific technologies around the world, with 38 billion products touching nearly all aspects of our lives by 2020.

As device makers and consumers see Wi-Fi as a key technology in everyday life, the wireless spectrum is becoming more congested and impacting performance. This is especially true in dense urban areas, where dozens of access points can overlap. Another factor is the growth of high-bandwidth applications, such as video streaming and multi-user gaming. To keep up with demand, Wi-Fi and the equipment used to test Wi-Fi devices must continue to evolve.

WI-FI EVOLUTION

Modern Wi-Fi took root when the IEEE formed the 802.11 working group back in 1990 to promote the standard. The initial release, 802.11 Wireless LAN, was approved in 1997. Since then, several advances to the Wi-Fi standard have occurred, perhaps the most significant being 802.11n. Released in 2009, 802.11n is considered a fourth-generation wireless-LAN technology standard, operating in both the 2.4- and 5.0-GHz bands.

Users had already begun migrating to 802.11n, based on the Wi-Fi Alliance's certification of products conforming to a 2007 draft of the 802.11n proposal. This version of the standard improved Wi-Fi in two major ways:

- It opened up the 5-GHz band. Although support for 5 GHz is optional under 802.11n, many users found this feature desirable because it relieved the congestion that users were experiencing on the 2.4 GHz band.
- It offered better throughput, as the maximum net data rate increased from 54 to 600 Mb/s. This was accomplished by increasing the channel width from 20 MHz to 40 MHz. Incorporation of multiple-input-multiple-output (MIMO) technology also enhanced performance. MIMO is made possible by devices utilizing multiple antennas. The antennas enable data to be transmitted over multiple streams, which significantly increases and accelerates overall data throughput.

Through the years, the evolution of 802.11 continued with the publishing of the 802.11ac standard in December 2013. Compared to 802.11n, it features wider channels (80 or 160 MHz versus 40 MHz) in the 5-GHz band, more spatial streams (up to eight versus four), higher-order modulation (up to 256-QAM versus 64-QAM), and the addition of multi-user MIMO (MU-MIMO). Generally, 802.11ac's rollout is distinguished by two "waves":

- "Wave 1" implementations support 80-MHz channels, three spatial streams, and 256-QAM, yielding a data rate of up to 433.3 Mb/s per spatial stream, 1,300 Mb/s total, in 80-MHz channels in the 5-GHz band.
- "Wave 2" devices include support for 160-MHz channels, four spatial streams, and MU-MIMO. Device makers began shipping Wave 1 devices in late 2013 and are starting to ship Wave 2 devices this year.

Today, 802.11ax is touted as the next-generation Wi-Fi standard. It promises to deliver even higher throughput than 802.11ac by using a more-efficient modulation scheme called orthogonal frequency division multiple access (OFDMA). OFDMA is a huge benefit of the 802.11ax standard. The primary goal is to increase the data rate per user by a factor of 4 and enable 10X more capacity over 802.11ac.

The current official release date of the 802.11ax standard is sometime in 2019. Like the rollout of 802.11n, though, we should begin to see devices that support the draft standard





Ultra Small 2x2mm

2W ATTENUATORS DC-20 GHz **\$1⁹⁹** from ea. (qty. 1000)


Save PC board space with our new tiny 2W fixed value absorptive attenuators, available in molded plastic or high-rel hermetic nitrogen-filled ceramic packages. They are perfect building blocks, reducing effects of mismatches, harmonics, and intermodulation, improving isolation, and meeting other circuit level requirements. These units will deliver the precise attenuation you need, and are stocked in 1-dB steps from 0 to 10 dB, and 12, 15, 20 and 30 dB.


The ceramic hermetic **RCAT** family is built to deliver reliable, repeatable performance from DC-20GHz under the harshest conditions. With prices starting at only

\$4.95 ea. (qty. 20), these units are qualified to meet MIL requirements including vibration, PIND, thermal shock, gross and fine leak and more, at up to 125°C!

The molded plastic **YAT** family uses an industry proven, high thermal conductivity case and has excellent electrical performance over the frequency range of DC to 18 GHz, for prices starting at \$2.99 ea. (qty. 20).

For more details, just go to minicircuits.com – place your order today, and you can have these products in your hands as soon as tomorrow!

 RoHS compliant



Plastic

Ceramic

FREE Simulation Models! 

<http://www.modelithics.com/mvp/Mini-Circuits/>



before then. It is absolutely essential for 802.11ax to keep progressing, considering that another technology is beginning to compete for bandwidth.

ON YOUR MARK

Wi-Fi is in a horse race with two Long Term Evolution (LTE) technologies: LTE in Unlicensed Bands (LTE-U) and LTE Licensed-Assisted Access (LTE-LAA). LTE-U is quietly emerging in 4G/LTE wireless networks specific to North America that use unlicensed spectrum—the same unlicensed 5-GHz spectrum currently being used by Wi-Fi.

Some studies have shown that LTE technology—originally used in cellular phones in licensed bands—offers performance advantages over Wi-Fi when operating in unlicensed bands, such as:

- Better link performance
- Medium access control
- Mobility management
- Excellent coverage

These benefits, combined with the vast amount of available spectrum (>400 MHz) in the 5-GHz band, make LTE-U a promising radio access technology in the unlicensed arena. Mobile operators are hot to implement this technology, as it will enable them to offload data traffic onto unlicensed frequencies and reduce the load on their wireless networks that use licensed spectrum. Devices that employ LTE-U are being field tested now, and commercial devices will be available to consumers starting this year.

Some of the industry's biggest players are behind LTE-U. In 2014, Verizon, in cooperation with Alcatel-Lucent, Ericsson, Qualcomm Technologies Inc. (a subsidiary of Qualcomm Inc.), and Samsung, formed the LTE-U Forum. The LTE-U Forum is a consortium, much like the Wi-Fi Alliance. In March 2015, the group published technical specifications, including minimum performance specifications for operating LTE-U base stations and consumer devices on unlicensed frequencies in the 5-GHz band as well as coexistence specifications.

The coexistence specifications are meant to address concerns that LTE-U devices will interfere with Wi-Fi networks. The FCC requires that devices using unlicensed spectrum do not interfere with the operation of other devices using those frequencies, but that's easier said than done.

The LTE-U Forum has conducted tests and published a report that shows that LTE-U will not cause interference to Wi-Fi. The study concludes that, "With a set of well-designed coexistence algorithms, the level of protection that LTE-U nodes provide to nearby Wi-Fi deployment can be better than what Wi-Fi itself provides."

Not surprisingly, Wi-Fi companies aren't quite so optimistic. Google issued a report that LTE-U would seriously interfere with Wi-Fi. Fortunately, we're at a point where these issues

can be worked out before the widespread sale and implementation of devices that could cause harmful interference to one another. Consumers will benefit greatly if the Wi-Fi Alliance and the LTE Forum work out these issues.

One possible scenario is that devices support both 802.11ax and LTE-U. This is certainly possible because the 802.11ax spec describes some of the same mechanisms found in LTE-U. For this to happen, chipset manufacturers will have to make chipsets that support both standards. Another scenario is that the IEEE 802.11ax committee will continue to improve the Wi-Fi specification, so that when it is released, it will be competitive with LTE-U.

INCREASED TESTING CHALLENGES

Of course, new technologies mean new testing challenges. Range and battery life will continue to be a concern. Higher data rates can reduce range and battery life, and manufacturers will have to make sure that their new designs don't fall short in these two areas. Comprehensive testing during the design phase is important to ensure that the customer experience isn't degraded.

Chipset calibration is another issue. As opposed to cellular, many device manufacturers do not perform Wi-Fi calibration in order to minimize test time and reduce cost. However, failing to do so can adversely affect range and battery life.

Another test challenge is that consumer devices are supporting more cellular and connectivity technologies. For example, smartphone manufacturers need to support 2G, 3G, and 4G cellular technologies today to ensure worldwide operation. Manufacturers need test equipment that can cover all of the communications protocols supported by a particular device.

More standards, in general, means increased test times. More test time in turn impacts the test process, and often becomes a financial quandary. Balancing new test methodologies and managing reasonable test times, while ensuring a high level of quality, deserves a fresh look. Test methodologies or test strategies should be periodically reevaluated, keeping mindful of the impact on the economies of test.

CONCLUSION

Without a doubt, Wi-Fi technology and the equipment needed to test it must adapt over the next few years. On the one hand, consumers are demanding more from their Wi-Fi in terms of more devices, users, and bandwidth. On the other hand, competing technologies, such as LTE-U, are looking to grab a share of the market, if not dominate it.

The next two years are crucial. The longer it takes manufacturers to develop and test LTE-U consumer devices, the better for 802.11ax, as it gives the standards committee time to make the standard more competitive. And, chances are that the groups supporting Wi-Fi and LTE-U will make concessions to allow for coexistence. **mw**

Multiport VNA Tests to 20 GHz

With outstanding measurement speed, accuracy, and 16 test ports, this RF/microwave vector network analyzer supports high-throughput production testing to 20 GHz.

VECTOR NETWORK ANALYZERS (VNAs) are so essential for higher-frequency testing of transmission characteristics that they might be thought of as “microwave voltmeters.” Most commercial VNAs are equipped with two or four ports for measuring the forward and reverse transmission characteristics of RF/microwave devices and components one at a time.

In production testing, however, more ports are needed, and the R&S ZNBT20 VNA from Rohde & Schwarz is designed for that purpose, with 16 integrated test ports and a frequency range of 100 kHz to 20 GHz. Each of the 16 ports provides high performance, allowing for high-volume S-parameter measurements under high-speed production conditions. The multiport analyzer can drive all of its test ports in parallel without compromising performance, for simultaneous testing of multiple devices under test (DUTs).

The R&S ZNBT20 (*see figure*) provides generous test port power through 20 GHz, with -30 to +6 dBm to 1 MHz, -30 to +8 dBm to 10 MHz, -30 to +10 dBm to 1 GHz, -30 to +8 dBm to 10 GHz, and -30 to +5 dBm to 20 GHz. The source power accuracy is better than 2 dB to 10 GHz and better than 3 dB to 20 GHz, with power resolution of 0.01 dB.

The multiport analyzer tunes frequency with 1-Hz resolution and can perform measurements on as few as 2 and as many as 100,001 points. The measurement bandwidth can be set from 12 Hz to 1 MHz in standard models and from 1 Hz to 10 MHz in instruments with an increased bandwidth option. The typical dynamic range at all ports is high, as good as 115 dB to 1 MHz, 130 dB to 2 GHz, 125 dB to 10 GHz, and 120 dB to 20 GHz.

The measurement accuracy is a function of frequency and test-port power, with amplitude accuracy at the lowest frequencies ranging from 0.30 dB for test-port power of -50 to -60 dBm to 0.06 dB for test port power from -35 to +5 dBm. From 1 MHz to 10 GHz, the amplitude accuracy is 0.10 dB for test port power from -50 to -60 dBm, improving to 0.06 dB for more robust test-port power from -35 to +5 dBm. At the highest test frequencies, from 10 to 20 GHz, the amplitude accuracy is 0.20 dB at the lowest test-port powers, improving to 0.06 dB for test-port power of -50 to -35 dBm and topping out at 0.05 dB for test-port power from -35 to +5 dBm.

The phase measurement accuracy is similarly well controlled, falling as low as 2 deg. at the lowest frequencies (100 kHz to 1 MHz) and power levels but typically 0.8 deg. or better for all



This multiport RF/microwave vector network analyzer (VNA) provides 16 parallel test ports for production S-parameter testing to 20 GHz.

power levels and for all frequencies above 1 MHz. Test signal harmonics are well controlled for the R&S ZNBT20. When tested for a 0-dBm test output level, harmonics are typically -20 dBc from 100 kHz to 10 MHz, -30 dBc from 10 to 100 MHz, -35 dBc from 100 MHz to 8 GHz, and -25 dBc from 8 to 15 GHz.

The R&S ZNBT20 20-GHz multiport VNA can achieve fast sweep times in support of production testing. Data transfers and measurement times were evaluated with a PC running 64-b copy of the Windows 7 operating system (OS) from Microsoft Corp. For a 900-MHz center frequency, the sweep time is less than 2.5 ms with a full test cycle time of less than 5 ms. For a 5.1-GHz center frequency, the sweep time is less than 2.0 ms and the full cycle time is less than 5 ms. The compact VNA is supplied with 3.5-mm male connectors on its RF/microwave ports and includes two USB 2.0 ports on front panel and two more on the rear panel to help with data transfers.

The analyzer is available with a sizable list of options, including extended bandwidth. An additional option, the R&S ZNBT-K20 option for extended time-domain analysis, makes it possible to perform signal-integrity tests on high-speed transmission standards, allowing displays of plots useful for such analysis, including eye diagrams, rise time, and skew. The R&S ZNBT20 is supported by a number of different ATE test programs to speed and simplify setup of production test systems. **mw**

ROHDE & Schwarz GmbH & Co., P.O. Box 80 14 69, 81614 Munich, Germany; 888-TEST-RSA (1-888-837-8772); www.rohde-schwarz.com.

Board Packs Pair of Superhet Channels

This low-power, wideband receiver module provides as much as 80 MHz for each of two superheterodyne channels with wide dynamic range from 10 MHz to 6 GHz.


MODULARITY OFTEN IS SYNONYMOUS with flexibility—a trait exemplified in the TwinRX daughterboard for the USRP X Series of software-defined radios (SDRs) from Ettus Research, a National Instruments company (www.ettus.com). Two of the TwinRX daughterboards fit within a model USRP X300 or USRP X310 SDR, each measuring just $27.7 \times 21.8 \times 3.9$ cm and weighing a mere 1.7 kg.

The TwinRX boards deliver 80-MHz bandwidth per receiver channel across a total frequency range of 10 MHz to 6 GHz. Each compact daughterboard (*Fig. 1*) is actually a full-fledged dual-channel receiver. They are capable of local-oscillator (LO) sharing with other receiver daughterboards in a system to create multichannel receiver systems or even massive MIMO system solutions. Each TwinRX is a low-power subsystem, with stable preselection filters (*Fig. 2*), attenuators, and two frequency mixer stages with tightly controlled phase synchronization.

BROAD FUNCTIONALITY

The TwinRX achieves a 110-dB dynamic range at 2.4 GHz, 5.5-dB minimum noise figure at the same frequency, and only 10-W power dissipation. Each of the daughterboard's receiver channels has instantaneous bandwidth of 80 MHz that can be tuned independently across the full frequency range from 10 MHz to 6 GHz to capture and analyze signals in multiple-frequency bands of interest.

As an example, a single TwinRX daughterboard can simultaneously monitor uplink and downlink communications signals across a combined bandwidth of $80 + 80 = 160$ MHz. By sharing LO signals across multiple TwinRX daughterboards, it is possible to achieve the phase-aligned operation needed for multichannel phased-array systems. In addition to the tight phase control, the dual-channel receiver is also capable of high-speed frequency-hopped tuning to detect frequency-agile emitters.




1. Each TwinRX daughterboard contains two independently tunable superheterodyne receiver channels for use from 10 MHz to 6 GHz.

The TwinRX exhibits noise figure of better than 5 dB from 10 MHz to 3 GHz, better than 4 dB from 3 to 5 GHz, and better than 8 dB from 5 to 6 GHz. Image rejection is -70 dBc from 0.5 to 6.0 GHz. Phase noise is -88 dBc/Hz offset 10 kHz from a 900-MHz carrier, -86 dBc/Hz offset 10 kHz from a 2.4-GHz carrier, and -82 dBc/Hz offset 10 kHz from a 5.8-GHz carrier. And phase noise is -105 dBc/Hz offset 100 kHz from a 900-MHz carrier, -107 dBc/Hz offset 100 kHz from a 2.4-GHz carrier, and -103 dBc/Hz offset 100 kHz from a 5.8-GHz carrier.

In addition, non-input-related spurious levels are -95 dBc from 10 MHz to 3 GHz, -92 dBc at 3.2 GHz, -98 dBc at 4.8 GHz, and -98 dBc at 5.4 GHz. The third-order-intercept point is -8 dBm for a full scale of -45 dBm from 10 MHz to 1.8 GHz, -2 dBm for a full scale of -30 dBm from 10 MHz to 1.8 GHz, and $+16$ dBm for a full scale of -20 dBm from 10 MHz to 1.8 GHz, with similar readings at higher frequencies. **mw**

ETTUS RESEARCH, a National Instruments Co., 4600 Patrick Henry Dr., Santa Clara, CA 95054; (480) 610-6399, e-mail: sales@ettus.com, www.ettus.com.



2. Powerful preselector filter capability within each TwinRX dual-channel receiver allows for detection and isolation of signals from interference from 10 MHz to 6 GHz.

YIG Oscillators Offer 20-MHz FM Bandwidth

YIG-based RF/microwave oscillators have been enhanced with 3-dB frequency modulation capabilities of 20 MHz or more.

MICROWAVE OSCILLATORS BASED ON yttrium-iron-garnet (YIG) resonators have long been prized for their low phase noise and linear tuning capabilities. The performance has always come at the cost of limited frequency-modulation (FM) 3-dB bandwidth—typically just a few MHz—which challenged synthesizer designers attempting to stabilize these sources with a phase-locked loop (PLL).

But those limits are no more: Micro Lambda Wireless has introduced YIG oscillator technology with FM 3-dB bandwidths of 20 MHz and higher, applicable to both electromagnetic and permanent-magnet (PM) type YIG oscillators. The firm designs and manufactures PM YIG sources from 2 to 20 GHz (Fig. 1) and electromagnetic YIG oscillators (Fig. 2) from 0.5 to 40.0 GHzs.

Smaller YIG oscillators, such as the TO-8-packaged MLS-MO series of PM YIG oscillators and the mini and PCB lines of sources, are currently available with the wideband FM to 16 GHz. Larger oscillators, such as 1-in. and 1.25-in. cubes and 1.75-in. cylinders, will be available shortly with the wideband FM capabilities. These exceptional FM capabilities are available as options meeting specific customer requirements.

The firm's various YIG oscillators are available for narrow-band and wideband frequency tuning ranges. The MLSMO series, for example (see "YIG Oscillators Fit Surface-Mount Packs" at mwrf.com), covers a variety of frequency bands, including 3.0 to 6.0 GHz, 4.0 to 9.0 GHz, and 6.5 to 13.0 GHz. The output power for all models is +8 dBm across each frequency range, with phase noise as good as -128 dBc/Hz offset 100 kHz from carriers to 9 GHz.

The electromagnetic and PM YIG oscillators differ in their approaches to the resonant magnetic structure within each oscillator, as well as with their resulting performance levels. While both approaches are capable of linear tuning low noise, electromagnet YIG oscillators offer extended frequency coverage with wider tuning ranges than PM YIG oscillators based on a magnet tuned at the factory according to a customer's requirements.

The PM approach yields a tuning bandwidth of typically ± 2 GHz, while the electromagnet approach can achieve tuning bandwidths in excess of an octave (albeit with higher power consumption, owing to the additional power needed to energize the electromagnet).

Waveguide Components

OFF THE SHELF FOR CUSTOM DESIGNS

• Attenuators • Couplers • Switches • Loads • Terminations • Adapters • Assemblies • Horns • Ferrite Components



We're Ready When You Are... Next Day Delivery Of Catalog Components

From The Largest Inventory Of Waveguide Components In The Industry
RECTANGULAR, MM-WAVE, & DOUBLE-RIDGED COMPONENTS

CUSTOM DESIGNS

Custom designs are a Waveline specialty. If you don't see the product or design in our catalog, we probably have your "special" in our design files. Waveline now offers a complete line of Pin Diode Switches, Attenuators & Phase Shifters. Waveline has the expertise and capabilities to integrate waveguide and solid-state designs for subassemblies.

CALL OR WRITE

waveline®



P.O. Box 718, West Caldwell, NJ 07006
(973) 226-9100 Fax: 973-226-1565
E-mail: wavelineinc.com



1. The MLTO series of PM YIG oscillators are supplied in 0.625-in.-diameter TO-8 housings.



2. The MLMB series of electromagnetic YIG oscillators are housed in PCB-mount enclosures.



To accomplish wideband FM with these different magnet structures, different design approaches and different FM driver configurations were required. For an end user, the results are the same, with FM tuning coils capable of 3-dB bandwidths in excess of 20 MHz and with standard FM coil sensitivity the same for the two YIG oscillator types, at 150 kHz/mA. For either type of oscillator and FM coil, the minimum frequency deviation is ± 15 MHz.

To verify the wideband capabilities of the FM coils and drivers in both YIG oscillator types, swept-frequency hands-on testing was performed by Micro Lambda Vice President of Engineering Dave Suddarth and President John Nguyen. Testing was performed with the aid of a swept-function generator capable of 30-MHz bandwidth, an FM discriminator, the various FM coil drivers under test, and a digital storage oscilloscope (DSO).

Test results were impressive. By way of example: Both oscillator types were studied at an RF/microwave frequency of

6.662 GHz using different five-turn FM coils in custom test fixtures. A 2-to-8-GHz TO-8 PM YIG oscillator was characterized by means of a linear FM sweep from 1 Hz to 30 MHz, exhibiting a 3-dB FM bandwidth of 28 MHz. Similarly, an electromagnet-based 3-to-8-GHz YIG oscillator was evaluated with a linear FM sweep from 1 Hz to 25 MHz, yielding a 3-dB FM bandwidth of 21 MHz.


This new wideband FM capability should make these YIG oscillators candidates for any designer seeking low phase noise, but put off by the relatively narrow 3-dB FM bandwidth. The 3-dB FM bandwidth of 20 MHz or more clears the way for a wide range of applications to 40 GHz and beyond—whether in terrestrial and satellite receivers, test equipment, or military electronic systems. **mw**

MICRO LAMBDA WIRELESS INC., 46515 Landing Pkwy., Fremont, CA 94538; (510) 770-9221, www.microlambdawireless.com

microwaves&rf DirectConnection

TO ADVERTISE, CONTACT A SALES REPRESENTATIVE at <http://mwrf.com/advertising>

GaN Transistor GP2001
Demo Amp TB256
20-3000MHz



28VDC

5W

10dB


RF polyfet rf devices
www.polyfet.com
 TEL (805) 484-4210

Transient Immunity Testers from AVTECH


The Avtech AVRQ series of high-voltage, high-speed pulse generators is ideal for testing the common-mode transient immunity (CMTI) of next-generation optocouplers, isolated gate drivers, and other semiconductors.

- ◆ Kilovolt amplitudes (± 1 , ± 1.5 , -2 kV)
- ◆ Transition times down to 10 ns, dV/dt rates up to 120 kV/us
- ◆ Switchable daughterboards to handle a variety of DUT package styles
- ◆ GPIB, RS-232 ports standard
- ◆ Ethernet / VXI optional

Unstable optocoupler DUT logic output!



-1.5 kV pulse from model AVRQ-5-B, with < 10 ns fall time.



Prices, manuals, datasheets & test results:
<http://www.avtechpulse.com/semiconductor>
info@avtechpulse.com

AVTECH

4-Channels
in 1 Compact Device



Ultra-Wideband
10 MHz to 13 GHz



Power Handling
up to 2W



NEW! Programmable ATTENUATORS

0 to 120dB 0.25dB Step 1 MHz to 13 GHz*


from \$395

Features

- Models with attenuation range up to 30, 60, 90, 110 or 120 dB
- Choose from USB, Ethernet, RS232 and SPI control options
- Use our software or yours! User-friendly GUI and DLLs included[†]
- Sweep or hop attenuation levels
- Save and recall customized attenuation patterns
- Pocket-sized package, as small as 3.0 x 2.0 x 0.6"
- **Now** 16 unique models in stock, ready to ship!

* Specs may vary by model. See data sheets for specific model information.

[†] No drivers required. DLL objects for 32/64 bit Windows® environments using ActiveX® and .NET® frameworks.



Our new RC4DAT-6G-95 provides four channels with synchronized or independent control from one simple interface for multi-channel MIMO testing, cellular base station handover testing and much more!

Visit minicircuits.com for detailed model specs, application notes, and more!
Place your order today and have them on your test bench as soon as tomorrow!



www.minicircuits.com/products/programmable_attenuators.shtml



ADVERTISER	PAGE
A	
ADVANCED TEST EQUIPMENT RENTALS	16
www.atecorp.com	
ANRITSU CORPORATION	C2
www.goanritsu.com/MWRFVNA	
ARRA INC.	C3
www.arra.com	
B	
BOONTON	C4
www.boonton.com	
C	
CALIFORNIA EASTERN LAB.	4
www.cel.com/switches	
CIAO WIRELESS INC.	17
www.ciaowireless.com	
COILCRAFT	2
www.coilcraft.com	
CPI BEVERLY MICROWAVE DIVISION	72
www.cpii.com/bmd	
CTT	67
www.cttinc.com	
D	
DBM CORP	79
www.dbmcorp.com	
E	
ECLIPSE MICROWAVE	95
www.eclipsemdi.com	
ELECTRONICA	88
www.electronica.de/en/tickets	
F	
FAIRVIEW	24,25
www.fairviewmicrowave.com	
H	
HEROTEK INC	13
www.herotek.com	
HUBER + SUHNER	58
www.hubersuhner.com	
I	
IWCE	89
www.criticalTEforum.com	
J	
JFW INDUSTRIES INC	53
www.jfwindustries.com	
K	
KEYSIGHT TECHNOLOGIES - USA	11
www.keysight.com/find/5G-Insight	
KOAXIS INC	84
www.koaxis.com	
KRYTAR	66
www.krytar.com	
L	
L-3 NARDA-MITEQ	3
www.nardamiteq.com	

ADVERTISER	PAGE
L	
LINEAR TECHNOLOGY CORPORATION	19
www.linear.com/product/LTC5549	
M	
M/A COM TECHNOLOGY SOLUTIONS, INC	8-9
www.macom.com/gan	
MECA ELECTRONICS INC	7
www.e-MECA.com	
MINI-CIRCUITS/SCI COMPONENTS.....	12,14-15,23, 30-31, 33,3749,55,59,61,63,65, 69,71,77,83,85,87,91,93,97,103
www.minicircuits.com	
N	
NI AWR	73
www.ni.com/awr	
NI MICROWAVE COMPONENTS	26
www.ni-microwavecomponents.com/quicksyn	
O	
OMMIC	94
www.ommic.com	
P	
PASTERNAK ENTERPRISES	34
www.pasternack.com	
PLANAR MONOLITHICS INDUSTRIES	1
www.pmi-rf.com	
PULSAR MICROWAVE CORP	18
www.pulsarmicrowave.com	
R	
ROHDE & SCHWARZ	41
www.rohde-schwarz.com/ad/highend	
S	
SAGE MILLIMETER INC	43
www.sagemillimeter.com	
SKYWORKS	6
www.skyworksinc.com/loT	
SPECTRANETIX	70
www.spectranetix.com/products	
SR TECHNOLOGIES	82
www.srtechnology.com	
SYNERGY MICROWAVE	29,47
www.synergymwave.com	
V	
VPT	62
www.vptpower.com	
W	
W.L. GORE & ASSOCIATES INC	56
www.gore.com/teft	
WAVELINE INC	101
www.wavelineinc.com	

This index is provided as an additional service by the publisher, who assumes no responsibility for errors or omissions.

Subscription Assistance and Information:
(ISSN 0745-2993)

Microwaves & RF is published monthly. **Microwaves & RF** is sent free to individuals actively engaged in high-frequency electronics engineering. In addition, paid subscriptions are available. Subscription rates for U.S. are \$95 for 1 year (\$120 in Canada, \$150 for International). Published by Penton Media, Inc., 9800 Metcalf Ave., Overland Park, KS 66212-2216. Periodicals Postage Paid at Kansas City and additional mailing offices. POSTMASTER: Send change of address to *Microwaves & RF* PO Box 2100, Skokie, IL 60076-7800. For paid subscription information, please contact *Microwaves & RF* at PO Box 2100, Skokie IL 60076-7800. Canada Post Publications Mail agreement No. 40612608. Canada return address: IMEX Global Solutions PO Box 25542, London ON N6C 6B2.

Back issues of *MicroWaves* and *Microwaves & RF* are available on microfilm and can be purchased from National Archive Publishing Company (NAPC). For more information, call NAPC at 734-302-6500 or 800-420-NAPC (6272) x 6578. Copying: Permission is granted to users registered with the Copyright Clearance Center, Inc. (CCC) to photocopy any article, with the exception of those for which separate copyright ownership is indicated on the first page of the article, provided that a base fee of \$1.25 per copy of the article plus 60 cents per page is paid directly to the CCC, 222 Rosewood Dr., Danvers, MA 01923. (Code 0745-2993/02 \$1.25 +.60) Copying done for other than personal or internal reference use without the expressed permission of Penton Media, Inc., is prohibited. Requests for special permission or bulk orders should be addressed in writing to the publisher.

Copyright 2016 • Penton • All rights reserved. Printed in the U.S.



The best deal in town
... from ARRA, of course!

FIXED ATTENUATORS DC-18 GHz

- Models to 55 dB
- SMA or Type N conn.
- 50 W average models

Freq. Range (GHz)	Average Power (W)	Model No.	
		N Conn.	SMA Conn.
DC-18.0	1	N9412 *	9412 *
DC- 5.0	1	N4402 *	4401 *
DC- 4.0	5	N4405 *	4405 *
DC- 4.0	10	N4410 *	4410 *
DC- 4.0	25	N4425 *	4425 *
DC- 4.0	50	N4450 *	4450 *

*Value of attenuation

4425 Types



9412 & 4401 Types
(1.14")



N9412 Types
(2.42")

Call (631) 231-8400 or
Fax (631) 434-1116

... the last word in variable attenuators

ARRA INC.

15 Harold Court • Bay Shore, N.Y. 11706



The best deal in town
... from ARRA, of course!

BROADBAND COAXIAL TERMINATIONS

- DC-18 GHz model
- 50 W model
- SMA or Type N conn.

Freq. Range (GHz)	Average Power (W)	Model No.	
		N Conn.	SMA Conn.
DC-18.0	1	N9512	9512
DC-12.4	2	N9505	9505
DC-12.4	5	N9510	9510
DC- 8.0	10	N9525	9525
DC- 8.0	25	N9550	
DC- 8.0	50		

Call (631) 231-8400 or
Fax (631) 434-1116

... the last word in variable attenuators

ARRA INC.

15 Harold Court • Bay Shore, N.Y. 11706



The best deal in town
... from ARRA, of course!

WAVEGUIDE LOADS



- Low VSWR
- Fast delivery!
- WR284 thru WR62

Freq. Range (GHz)	Medium Power		High Power	
	Average (W)	Model No.	Average (W)	Model No.
2.60-3.95	1200	284-925	4500	284-920
3.30-4.90	1000	229-925	3000	229-920
3.95-5.85	750	187-925	2000	187-920
4.90-7.05	625	159-925	1500	159-920
5.85-8.20	500	137-925	1000	137-920
7.05-10.0	425	112-925	600	112-920
7.00-11.0	325	102-925	500	102-920
8.20-12.4	225	90-925	500	90-920
12.4-18.0	200	62-925	250	62-920

Call (631) 231-8400 or
Fax (631) 434-1116

... the last word in variable attenuators

ARRA INC.

15 Harold Court • Bay Shore, N.Y. 11706



The best deal in town
... from ARRA, of course!

WAVEGUIDE COMPONENTS & SPECIAL ASSEMBLIES

Write for new literature or call (631) 231-8400




Call (631) 231-8400 or Fax (631) 434-1116

... the last word in variable attenuators


ARRA INC.

15 Harold Court • Bay Shore, N.Y. 11706

Don't Settle for Average.



Demand Peak Performance.



The 55 Series USB Peak Power Sensor *Real-Time Power Measurements for Complex Communications Signals*

Others claim to have fast average measurements, but only the 55 Series measures continuous and burst average power faster than anyone in the industry. It adds wide-band peak and crest factor measurements, allowing you to see all aspects of your device's performance. This USB Sensor delivers results 100 times faster than conventional meters and with its *Real-Time Power Processing™* technology captures all glitches with 100ps resolution.

- 195 MHz Video Bandwidth
- 3 ns risetime
- 100,000 measurements/sec
- 100 MHz Sample Rate
- Multi-channel synchronized measurements

For more information visit us at www.boonton.com or call +1 973-386-9696.